

TelevisGo v10

The expandable supervisor with FREE Studio Plus applications IEC 61131-3

User Guide

TGO02_03EN

05/2026



Legal information

The information provided in this document contains general descriptions, technical characteristics and/or recommendations related to products/solutions.

This document is not intended as a substitute for a detailed study or operational and site-specific development or schematic plan. It is not to be used for determining suitability or reliability of the products/solutions for specific user applications. It is the duty of any such user to perform or have any professional expert of its choice (integrator, specifier or the like) perform the appropriate and comprehensive risk analysis, evaluation and testing of the products/solutions with respect to the relevant specific application or use thereof.

The Schneider Electric brand and any trademarks of Schneider Electric and its subsidiaries referred to in this document are the property of Schneider Electric or its subsidiaries. All other brands may be trademarks of their respective owner.

This document and its content are protected under applicable copyright laws and provided for informative use only. No part of this document may be reproduced or transmitted in any form or by any means (electronic, mechanical, photocopying, recording, or otherwise), for any purpose, without the prior written permission of Schneider Electric.

Schneider Electric does not grant any right or license for commercial use of the document or its content, except for a non-exclusive and personal license to consult it on an "as is" basis.

Electrical equipment should be installed, operated, serviced, and maintained only by qualified personnel only. No responsibility is assumed by Schneider Electric for any consequences arising out of the use of this material.

Schneider Electric reserves the right to make changes or updates with respect to or in the content of this document or the format thereof, at any time without notice.

To the extent permitted by applicable law, no responsibility or liability is assumed by Schneider Electric and its subsidiaries for any errors or omissions in the informational content of this document, as well as any non-intended use or misuse of the content thereof.

Table Of Contents

Safety information	6
About the document	8
Before first use	14
Before first use	15
Introduction	16
Description	17
Models	18
Accessories available	18
Pack Contents	19
Languages supported	21
Browser	21
Types of network that can be monitored	22
Compatible modems	23
Compatible devices	23
Hardware compatible with TelevisGo v10	23
Configuring the TelevisGo v10	24
Cybersecurity	25
Overview	26
Defense-in-Depth	26
Security hardening guidelines	28
Secure disposal guidelines	31
Secure operation guidelines	32
Account management guidelines	33
Mechanical installation	36
Before starting	37
Disconnecting Power	37
Operating environment	38
Installation Considerations	38
TelevisGo v10 C Mechanical Installation	39
TelevisGo v10 DP Mechanical Installation	40
Electrical connections	41
Best wiring practices	42
Hardware TelevisGo v10 C	45
Hardware for TelevisGo v10 DP	46
Connecting a network	47
Technical specifications	50
Technical data	51
Further information	53
Power supply	53
User interface and device configuration	54
Accessing the user interface	55
Login	56
Changing the password	57
Page structure	58

Status bar	58
Navigation menu	59
Initial device configuration	60
Status icons	60
Buttons and selectors	61
Equipment	64
Introduction	65
Viewing and filtering network equipment	66
Basic device information tab	67
Viewing equipment data	69
Network devices list	71
Adding equipment	73
Equipment data settings	75
Device resources	77
Equipment alarms	79
History	80
Parameters	81
Commands	82
Alarms	83
Introduction	84
Viewing and filtering network alarms	85
Basic device alarm information tab	87
Alarm details	89
History	90
Introduction	91
Alarm log	92
Data tables and charts	94
Functions	101
Introduction	102
Start/Stop acquisition	103
Scheduled actions start/stop	104
Commands	105
Parameters	107
List of controller parameters	108
List of algorithm parameters	109
Writing on more than one device	115
RVD (Remote Virtual Device)	116
Layout	117
Settings	119
Introduction	120
Adding/editing a fieldbus interface	121
User management	127
Alarm configuration	130
Scheduler	138
Registration interval settings	150
System general settings	152
Computer	159

Introduction	160
Device settings	161
Updating the TelevisGo v10	162
Updating the system	163
Updating algorithm drivers	164
Updating device drivers	165
Reboot	166
License updating	166
System backup/restore	167
Activity logging	168
Configuring HTTPS protocol	170
Certificates	171
Installing the certificate on other PCs	172
Installing a new certificate	173
Administrative tools	174
Restoring the disk image	175
Downloading files	176
Remote data access protocol	177
Data protocol	178
FAQs	179
FAQs	180

Safety information

Important information

Read these instructions carefully and visually inspect the equipment to familiarize yourself with the controller before installing it and/or putting it into operation or servicing it. The following warning messages may appear anywhere in this documentation or on the equipment to warn of potential dangers or to call attention to information that can clarify or simplify a procedure.



The addition of this symbol to a danger warning label "Danger" or "WARNING" indicates the existence of an electrical danger that could result in personal injury should the user fail to follow the instructions.



This is the safety warning symbol. It is used to warn the user of the potential dangers of personal injury. Observe all the safety warnings that follow this symbol to avoid the risk of serious injury or death.

DANGER

DANGER indicates a dangerous situation that, unless avoided, **will result in death** or cause serious injuries.

WARNING

WARNING indicates a potentially dangerous situation which, if not avoided, **could result in death** or serious injury.

CAUTION

CAUTION indicates a potentially dangerous situation which, if not avoided, **could result in** minor or moderate injury.

NOTICE

NOTICE used in reference to procedures not associated with physical injuries.

Note

Electrical equipment should be installed, operated, serviced, and maintained only by qualified personnel only. No responsibility is assumed by Schneider Electric and Eliwell for any consequences arising out of the use of this material. A qualified person is someone who has specific skills and knowledge regarding the structure and the operation of electrical equipment and who has received safety training on how to avoid the inherent dangers.

Personnel qualification

Only personnel with suitable training and an in-depth knowledge and understanding of the content of this manual and other documentation relating to the product in question are authorized to work on and with this product.

The qualified employee must be capable of identifying any hazards that may arise from the parameters, changing the value of the parameters and from using mechanical, electrical and electronic equipment in general. Plus, they must be familiar with accident prevention standards, provisions and regulations, which must be observed while the system is being designed and implemented.

Permitted use

The device must be installed and used in accordance with the instructions provided. In particular, parts carrying dangerous voltages must not be accessible under normal conditions.

TelevisGo v10 is a supervisor for monitoring, recording and handling data, remote viewing and maintenance of the connected devices for refrigeration systems used in the processing, storage and distribution of foodstuffs.

It must be adequately protected from water and dust with regard to the application, and must only be accessible using tools or a keyed locking mechanism.

Improper use

Any use other than that described in the previous paragraph, "Permitted use", is strictly prohibited.

The functional security protection devices, required by international or local laws, must be installed outside this device.

Liability and residual risks

Electrical equipment must be installed, used and repaired by qualified personnel only.

The liability of Schneider Electric and Eliwell is limited to the correct and professional use of the product according to the directives referred to herein and in the other supporting documents, and does not cover any damage (including but not limited to) resulting from the following causes:

- unspecified installation/use and, in particular, in contravention of the safety requirements of the legislation in force in the country of installation and/or specified in this document;
- use on equipment which does not provide adequate protection against electrocution, water and dust in the actual installation conditions;
- use on equipment which allows access to dangerous components without the use of tools and/or a keyed locking mechanism;
- tampering with and/or modification of the product;
- installation/use on equipment that does not comply with the regulations in force in the country of installation.

Disposal



The equipment (or product) must be subjected to separate waste collection in compliance with the local legislation on waste disposal.

About the document

Purpose of the document

The TelevisGo v10 user manual provides comprehensive details on the device's specifications, installation, configuration, and operation for refrigeration systems. The device supports Ethernet, GSM modems, USB, and RS232 interfaces, and can manage up to 224 devices. The manual covers various models, available accessories, mechanical and electrical installation procedures, user interface navigation, alarm management, historical data viewing, and system updates. Additionally, it provides instructions for managing network settings, updating drivers, performing backups, and restoring the system.

Note regarding validity

This document is valid for the TelevisGo v10 device.

The characteristics of the products described in this document are intended to match the characteristics that are available on www.eliwell.com. As part of our corporate strategy for constant improvement, we may revise the content over time to enhance clarity and accuracy. If you see a difference between the characteristics in this document and the characteristics on www.eliwell.com, consider www.eliwell.com to contain the latest information.

General Cybersecurity Information

In recent years, the growing number of networked machines and production plants has seen a corresponding increase in the potential for cyber threats, such as unauthorized access, data breaches, and operational disruptions. You must, therefore, consider all possible cybersecurity measures to help protect assets and systems against such threats. To help keep your Schneider Electric products secure and protected, it is in your best interest to implement the cybersecurity best practices as described in the [Cybersecurity Best Practices](#) (English document). Schneider Electric provides additional information and assistance:

- Subscribe to the Schneider Electric [security newsletter](#).
- Visit the [Cybersecurity Support Portal](#) to:
 - Find Security Notifications
 - Report vulnerabilities and incidents
- Visit the [Schneider Electric Cybersecurity and Data Protection Posture](#) to:
 - Access the 'cybersecurity posture'
 - Learn more about cybersecurity in the cybersecurity academy
 - Explore the cybersecurity services from Schneider Electric

Available Languages of this Document

This document is available in the following languages:

- Italian (TGO02_03IT)
- English (TGO02_03EN)
- Spanish (TGO02_03ES)
- German (TGO02_03DE)
- French (TGO02_03FR)
- Russian (TGO02_03RU)

Related documents

Publication title	Reference code
TelevisGo Migration Tool manual	TGOMT
TelevisGo Modbus_TCP BMS Config Tool manual	9MA00270 (IT) - 9MA10270 (EN)
TelevisGo v10 C instruction sheet	9IS54970 (6L) - 9IS54971 (EN-AR)
TelevisGo v10 DP instruction sheet	9IS54915 (6L) - 9IS54916 (AR)
SerialAdapter Instruction Sheet	9IS64615 (6L)
TelevisGo Windows Spare SSD Instruction Sheet	9IS64599 (6L)
EthernetAdapter Instruction Sheet	9IS54871 (10L)
Cybersecurity Best Practices	Refer to Cybersecurity Best Practices (English document)

The available technical documentation and other technical information can be downloaded from the website: www.eliwell.com

Environmental Data

For product compliance and environmental information refer to the Schneider Electric [Environmental Data Program](#).

Information on non-inclusive or insensitive terminology

As part of a group of responsible and inclusive companies, we are currently updating our communications and products that contain non-inclusive terminology. Nevertheless, until we have completed this process, our content may still include standardized industry terminology which may be considered inappropriate by our customers.

Product related information

DANGER

HAZARD OF ELECTRIC SHOCK, EXPLOSION, FIRE OR ARC FLASH

- Disconnect all power from all equipment including connected devices prior to removing any covers or doors, or installing or removing any accessories, hardware, cables or wires.
- Always use a properly rated voltage sensing device to confirm the power is off where and when indicated.
- Before powering the device back up, fit back and fix all the covers, hardware components and wiring.
- Verify the earthing connections on all earthed devices.
- Use this device and all connected products only at the specified voltage.

Failure to follow these instructions will result in death or serious injury.

WARNING

LOSS OF CONTROL

- Carry out a new network scan every time the type, configuration or number of controllers monitored is changed.
- The installation designer must consider the potential failure modes of the control circuit and, for some critical control functions, provide a means for reaching a safe condition during and after a circuit failure. Examples of critical control functions are the emergency stop and end of travel stop, power supply cut-off and restarting.
- Redundant control circuits that are separate from the TelevisGo v10 must be provided for critical control functions.
- The control circuits can incorporate communication equipment such as proxy modems or network gateways. Keep in mind the implications of transmission delays or sudden connection failures.
- Comply with all standards regarding accident protection and local applicable safety directives.
- Every implementation of this device must be tested individually and completely in order to check its proper operation before putting it into service.
- Do not disassemble, repair or modify this equipment.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Communication between TelevisGo v10 and **SerialAdapter/EthernetAdapter** is susceptible to electromagnetic interference and the transmission of alarm signals may not be possible.

WARNING

UNINTENDED EQUIPMENT OPERATION

- Use appropriate safety interlocks where personnel and/or equipment hazards exist.
- Do not use this equipment for safety-critical functions.
- Do not connect wires to unused terminals and/or terminals indicated as “No Connection (N.C.)”.
- Install TelevisGo v10 and SerialAdapter in an environment in which EMC disturbance is below the limits specified in standard EN61000-6-1 (residential, commercial and light industry environments).
- Configure the "LifeTest" function to make sure the TelevisGo v10 is active. Non-receipt of the periodic email indicates a malfunction of the TelevisGo v10 or the email sending service.
- The load equivalent to all the bus RS485 nodes should not exceed 30 Unit Load (for the definition of Unit Load refer to standard TIA/EIA-485-A).
- For the connection to the supervision system, use a specific shielded “twisted pair” cable (for example: BELDEN cable model 8762).

Failure to follow these instructions can result in death, serious injury, or equipment damage.

WARNING

HAZARD OF OVERHEATING AND/OR FIRE

Install and use the equipment exclusively in a protected environment, to prevent direct exposure to sunlight and atmospheric agents.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

The pages on the website have been designed to set up and monitor the system and to access the equipment from a web browser, via a web server.

Always use a secure protocol (HTTPS) for installation of a TLS certificate generated by a trusted CA (Certification Authority).

WARNING

UNINTENDED EQUIPMENT OPERATION

Only use software approved by Eliwell when using this equipment.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Take the suitable care and precautions when using this product as a control device, to avoid unforeseen consequences resulting from the operation of the controlled machine, variations in controller status or changes to the machine data memory or operating parameters.

WARNING

UNINTENDED EQUIPMENT OPERATION

- Before attempting to control the application remotely, you must be perfectly familiar with the application and the machine.
- Take the necessary precautions to guarantee that you are working on the anticipated machine remotely by using clear identification documentation within the application and the corresponding remote connection.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Eliwell adheres to industry best practices in the development and implementation of control systems. This includes a Defense-in-Depth approach to guarantee an industrial control system. This approach protects the controller with one or more firewalls to limit access exclusively to authorized personnel and protocols.

⚠ WARNING**UNAUTHORISED ACCESS AND SUBSEQUENT NETWORK INTRUSION**

- Assess whether the room or the machines are connected to the critical infrastructure and, if so, take suitable preventative measures, based on “defense-in-depth” strategy, before connecting the automation system to any network.
- Minimize the number of devices connected to a network.
- Isolate your industrial network from other networks within the company.
- Protect any network from unintentional access using firewalls, VPNs or other proven security measures.
- Monitor activity within the systems.
- Prevent direct access or direct connection to the devices concerned by unauthorized individuals or unauthorized actions.
- Prepare a restore plan that includes system backup and process information.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Flammable refrigerant gases

This equipment is designed to operate in non-hazardous locations and where applications which generate (or could potentially generate) hazardous environments have been isolated. Install this equipment only in areas and with applications known to be constantly free from hazardous atmospheres.

⚠ DANGER**RISK OF EXPLOSION**

- Install and use this equipment in non-hazardous locations only.
- Do not install or use this equipment in applications which could generate hazardous atmospheres, such as those which use flammable refrigerants.

Failure to follow these instructions will result in death or serious injury.

For information regarding the use of control equipment in applications capable of generating hazardous materials, please contact the relevant national regulatory bodies or certifying authorities.

Before you start

Do not use this product on machines without effective protection for the work area.
The lack of effective protection for the work area on a machine may lead to serious injury for the machine operator.

 WARNING
EQUIPMENT WITHOUT PROTECTION Do not use this software or the relative automation equipment on a device lacking protection on the workstation. Failure to follow these instructions can result in death, serious injury, or equipment damage.

This automation equipment and the corresponding software are used to control various industrial and commercial processes.

Only the user, the machine manufacturer or the system integrator can be up-to-date in terms of all the conditions and factors present when preparing, starting up and servicing the machine and therefore only they are able to determine which automation equipment and corresponding safety devices and interlocks can be used correctly.

When the automation and control equipment and the relative software are selected for a particular application, the applicable local and national standards and regulations must also be taken into consideration. Furthermore, the manual for accident prevention of the National Safety Council (recognized nationally in the United States of America) provides very useful information.

Before putting the equipment into service, make sure that all the safety devices and appropriate mechanical/electrical interlocks relating to the protection of the workstation have been installed. All the interlocks and safety devices relating to workstation protection must be coordinated with the corresponding software programming and automation instruments.

Start-up and testing

Before using the electric control and automation equipment for normal operation after installation, the system should be subjected to a start-up test by qualified personnel to make sure the equipment is functioning correctly.

It is important to carry out the preparations for this check and that sufficient time is provided in order to completely and satisfactorily perform the test.

 WARNING
DANGER WHEN STARTING-UP THE EQUIPMENT <ul style="list-style-type: none">• Verify that all installation and preparation procedures have been completed.• Before performing the operating tests, remove all the locks or other temporary retaining devices used when shipping the device components.• Remove any tools, measuring instruments and debris from the equipment. Failure to follow these instructions can result in death, serious injury, or equipment damage.

Perform all the start-up tests recommended in the equipment documentation. Conserve all equipment documentation for future consultation.

The custom software must be tested in a simulated environment as well as in the real environment.

Check that the completed system is free of short circuits and that the temporary earth system is not installed in compliance with local standards (for example the National Electrical Code in the US). If it is necessary to perform high potential voltage tests, comply with the recommendations provided in the equipment documentation in order to avoid damaging the device.

Before powering the equipment:

- Close the door in the equipment casing.
- Remove all the temporary earth systems from the incoming power supply lines.
- Perform all the start-up tests recommended by the manufacturer.

Terminology sourced from standards

The technical terms, terminology, symbols and corresponding descriptions in this manual, or which appear on the products themselves, are generally sourced from the terms or definitions used in international standards. In the context of functional safety systems, start-ups and general automation, this may include, but is not limited to, terms such as safety, safety function, protected status, fault, fault reset, malfunctioning, fault, error, error message, hazardous, etc.

Among others, these standards include:

Standard	Description
IEC 61131-2:2007	Programmable controllers, part 2: Equipment requirements and tests.
ISO 13849-1:2015	Safety of machinery: Safety related parts of control systems. General principles for design.
EN 61496-1:2013	Safety of machinery: Electro-sensitive protective equipment. Part 1: General requirements and tests.
ISO 12100:2010	Safety of machinery - General principles for design - Risk assessment and risk reduction.
EN 60204-1:2006	Safety of machinery - Electrical equipment of machines - Part 1: General requirements.
ISO 14119:2013	Safety of machinery - Interlocking devices associated with guards - Principles for design and selection.
ISO 13850:2015	Safety of machinery - Emergency stop - Principles for design.
IEC 62061:2015	Safety of machinery - Functional safety of safety-related electrical, electronic, and electronic programmable control systems.
IEC 61508-1:2010	Functional safety of electrical/electronic/programmable electronic safety-related systems: General requirements.
IEC 61508-2:2010	Functional safety of electrical/electronic/programmable electronic safety-related systems: Requirements for electrical/electronic/programmable electronic safety-related systems.
IEC 61508-3:2010	Functional safety of electrical/electronic/programmable electronic safety-related systems: Software requirements.
IEC 61784-3:2016	Industrial communication networks - Profiles - Part 3: Functional safety fieldbuses - General rules and profile definitions.
2006/42/EC	Machinery Directive.
2014/30/EU	Electromagnetic Compatibility Directive.
2014/35/EU	Low Voltage Directive.

Plus, the terms used in this document may be used in passing as they are sourced from other standards such as:

Standard	Description
IEC 60034 series	Rotating electrical machines.
IEC 61800 series	Adjustable speed electrical power drive systems.
IEC 61158 series	Digital data communications for measurement and control – Fieldbus for use in industrial control systems.

Finally, the term "operating area" may be used in relation to the description of specific hazards, and is defined as for a hazard area or hazardous area in the Machinery Directive (2006/42/EC) and ISO 12100:2010.

NOTE: The abovementioned standards may or may not be applicable to the specific products mentioned in this documentation. For further information concerning individual standards applicable to the products described herein, please refer to the table of characteristics for these product references.

Before first use

Contents

This section includes the following topics:

Before first use	15
------------------------	----

Before first use

Before installing TelevisGo v10, carefully read this chapter which lists the components, not included in the package, necessary to complete the initial startup procedure.

Necessary components

- USB Mouse
- USB Keyboard
- Display with HDMI or DP interface cable.

Initial startup procedure

1. Connect the mouse, keyboard, and monitor to TelevisGo v10
2. Power on the monitor and TelevisGo v10
3. Press the "ON/OFF" button on TelevisGo v10 (see [Hardware TelevisGo v10 C](#) or [Hardware TelevisGo v10 DP](#)).
4. If the keyboard layout is different from English, to avoid entering a password different from the intended one, you can:
 - press  to show/hide the entered password
 - press , at the bottom right, to open the Control Panel and enable the Windows virtual keyboard
 - press "ENG", at the bottom right, to open the selection box for one of the preloaded keyboards
 - ENG = keyboard with English layout
 - ITA = keyboard with Italian layout
 - ESP = keyboard with Spanish layout
5. When prompted to change the Windows password, enter:
 - **Current password:** none (leave blank)
 - **New password:** enter a new password (see minimum security criteria)
 - **Confirm password:** re-enter the new password.
6. Complete the procedure by pressing the **Save** key.

NOTE: Store the new password in a safe place and/or create a recovery disk. The system administrator password is required for recovery operations and cannot be retrieved from the system itself.

NOTICE

LOSS OF FUNCTION

Loss of the Administrator user password prevents access to system configuration. The password cannot be recovered.

Failure to follow these instructions can result in equipment damage.

NOTE: in the event of a lost password, contact Eliwell Technical Support to have it reset. The procedure requires Technical Support to be able to connect to TelevisGo v10 remotely.

NOTE: a secure password is one that has not been shared with or given to unauthorized personnel, and that does not contain personal or otherwise obvious information. Do not exceed 50 characters.

For further information see "Operating System Password" section.

NOTE: Minimum password security criteria. For more information, please refer to the Microsoft website (<https://learn.microsoft.com/en-us/windows/security/threat-protection/security-policy-settings/password-must-meet-complexity-requirements>):

- Minimum 8 characters
- 1 numerical digit (0, 1, ... , 9)
- 1 uppercase letter (A, B, ... , Z)
- 1 lowercase letter (a, b, ... , z)
- 1 special character (!, !, " \$%^&*()_+ -=[]{};: '@#~<>./?)

Introduction

Contents

This section includes the following topics:

Description	17
Models	18
Accessories available	18
Pack Contents	19
Languages supported	21
Browser	21
Types of network that can be monitored	22
Compatible modems	23
Compatible devices	23
Hardware compatible with TelevisGo v10	23
Configuring the TelevisGo v10	24

Description

TelevisGo v10 is a supervisor for monitoring, recording and handling data, remote viewing and maintenance of the connected devices for refrigeration systems used in the processing, storage and distribution of foodstuffs.

TelevisGo v10 records data, manages alarms and provides remote access to network device data to easily monitor HACCP data and schedule maintenance activities.

It has the following connectivity systems:

TelevisGo v10 C	<ul style="list-style-type: none"> • 2 Ethernet RJ45 ports (built-in) • 4 USB ports (1x USB 2.0 + 3x USB 3.2) • 4 RS232 serial ports • 1 HDMI port • 1 Display port
TelevisGo v10 DP	<ul style="list-style-type: none"> • 2 Ethernet RJ45 ports (built-in) • 4 USB ports (2x USB 2.0 + 2x USB 3.0) • 4 RS232 serial ports • 1 HDMI port • 1 Display port

TelevisGo v10 can be accessed remotely via a web browser without the need to install additional software (see ["Supported browsers"](#)).

The multilingual user interface supports 12 languages (Italian, English, Spanish, German, French, Russian, Dutch, Polish, Portuguese, Chinese, Turkish and Japanese) but other languages can be installed at a later time.

TelevisGo v10 is a software platform which can be updated with new functions and offers the option of transferring data to centralized systems.

The license is used to manage up to a maximum of 224 devices and 3000 acquisition points.

As Administrator, all aspects of the system can be integrally controlled via remote access (see ["Configuring the TelevisGo v10"](#)).

Models

The available models are listed below:

TelevisGo v10 C

Product	Description	no. of devices (maximum)
TGOFXE013E00K	TelevisGo v10 C /1 KIT SerialAdapter	1
TGOFXE103E00K	TelevisGo v10 C /10 KIT SerialAdapter	10
TGOFXE1H3E00K	TelevisGo v10 C /100 KIT SerialAdapter	100
TGOFXE2H3E00K	TelevisGo v10 C /224 KIT SerialAdapter	224
TGOFXE303E00K	TelevisGo v10 C /30 KIT SerialAdapter	30
TGOFXE303E02K	TelevisGo v10 C /30 KIT SerialAdapter (AR)	30
TGOFXE603E00K	TelevisGo v10 C /60 KIT SerialAdapter	60
TGOFXE603E02K	TelevisGo v10 C /60 KIT SerialAdapter (AR)	60
TGOFXE103ER0K	TelevisGo v10 C LE /10 KIT SerialAdapter	10
TGOFXE303ER0K	TelevisGo v10 C LE /30 KIT SerialAdapter	30
TGOFXE603ER0K	TelevisGo v10 C LE /60 KIT SerialAdapter	60

TelevisGo v10 DP

Product	Description	no. of devices (maximum)
TGOEXE101ER0K	TelevisGo v10 DP LE /10 KIT SerialAdapter	10
TGOEXE301ER0K	TelevisGo v10 DP LE /30 KIT SerialAdapter	30
TGOEXE601ER0K	TelevisGo v10 DP LE /60 KIT SerialAdapter	60
TGOEXE101E00K	TelevisGo v10 DP /10 KIT SerialAdapter	10
TGOEXE301E00K	TelevisGo v10 DP /30 KIT SerialAdapter	30
TGOEXE301E02K	TelevisGo v10 DP /30 KIT SerialAdapter (AR)	30
TGOEXE601E00K	TelevisGo v10 DP /60 KIT SerialAdapter	60
TGOEXE601E02K	TelevisGo v10 DP /60 KIT SerialAdapter (AR)	60
TGOEXE1H1E00K	TelevisGo v10 DP /100 KIT SerialAdapter	100
TGOEXE2H1E00K	TelevisGo v10 DP /224 KIT SerialAdapter	224

Accessories available



RISK OF ELECTRIC SHOCK, FIRE OR ARC FLASH

Only connect compatible accessories to the device.

Failure to follow these instructions will result in death or serious injury.

Contact a representative Eliwell for further information regarding compatible accessories.

Depending on your own applications, the following accessories may be purchased separately:

Accessory	Description
LTE modem	"MODEM 4G LTE W/ANT PSU TRB 142" model (product code SAM4G0S00AA00). Must be connected to COM3 or COM4 .
SerialAdapter	Module with RS232 / RS485 interface. Must be connected to COM1 or COM2 .
EthernetAdapter	Module with Ethernet / RS485 interface. EthernetAdapter supports device networks with Modbus protocol.
BusAdapter	Device with TTL/RS485 communication interface for connecting Eliwell controllers to the RS485 Fieldbus.


Pack Contents

TelevisGo v10 C



Label	Description
1	TelevisGo v10 C device
2	TelevisGo v10 C power supply unit and power cable
3	TelevisGo v10 C instruction sheet.
4	1x SerialAdapter kit (see 'KIT SerialAdapter ' section)


KIT SerialAdapter



Label	Description
1	SerialAdapter device (1) with relative Instruction sheet
2	SerialAdapter power supply (1) with relative Instruction sheet
3	SerialAdapter connection wiring with TelevisGo v10(1)

(1): One **SerialAdapter** kit is supplied with the TelevisGo v10. Additional kits can be purchased separately (code: KIT SAT1AMM1000AK).

TelevisGo v10 DP



Label	Description
1	TelevisGo v10 DP device
2	TelevisGo v10 DP power supply unit and power cable
3	SerialAdapter device
4	TelevisGo v10 DP instruction sheet

Languages supported

The software features the following languages:

- Italian
- English
- Spanish
- German
- French
- Russian
- Dutch
- Polish
- Portuguese
- Chinese
- Turkish
- Japanese

Browser

Browsers supported

Platform	Browser	Minimum version
Personal Computer	Google Chrome	146
	Microsoft Edge	147
	Safari	26.4
Tablet/Smartphone	Google Chrome for Android	146
	Safari for iOS	26.4

For the best performance and security, regularly check for and install updates for all supported web browsers. We recommend keeping your preferred browser up to date.

Browsers not supported

Platform	Browser
Personal Computer	Firefox
Tablet/Smartphone	Firefox for Android
	Samsung Internet
	Opera mobile

Updating the application

The cache settings can influence the loading process of the new system version.

NOTICE

INOPERABLE DEVICE

Following an application update, clear the browser history used to access the system.
Failure to follow these instructions can result in equipment damage.

Types of network that can be monitored

Communication between TelevisGo v10 and **SerialAdapter** is susceptible to electromagnetic interference and the transmission of alarm signals may not be possible.

⚠ WARNING
UNINTENDED EQUIPMENT OPERATION
<ul style="list-style-type: none"> • Install TelevisGo v10 and SerialAdapter in an environment in which EMC disturbance is below the limits specified in standard EN61000-6-1 (residential, commercial and light industry environments). • Configure the "LifeTest" function to make sure the TelevisGo v10 is active. Non-receipt of the periodic email indicates a malfunction of the TelevisGo v10 or the email sending service. • The load equivalent to all the bus RS485 nodes should not exceed 30 Unit Load (for the definition of Unit Load refer to standard TIA/EIA-485-A). • For the connection to the supervision system, use a specific shielded "twisted pair" cable (for example: BELDEN cable model 8762).
Failure to follow these instructions can result in death, serious injury, or equipment damage.


TelevisGo v10 has been approved for the following networks:


- **RS232/RS485** networks which use the **SerialAdapter** module as a gateway.
- **Ethernet/RS485** networks which use the **LanAdapter/EthernetAdapter** module as a gateway.

Signal propagation in an Ethernet network depends on bus traffic, making access times to the **LanAdapter** or the **EthernetAdapter** non-deterministic and potentially influencing TelevisGo v10 access time to the various resources with possible No-Link (loss of communication with the device).

NOTICE
INOPERABLE DEVICE
Eliwell guarantees the correct operation of networks using a maximum of 10 LanAdapter devices or 10 EthernetAdapter devices.
Failure to follow these instructions can result in equipment damage.

Examples of usable networks are given below:





Compatible modems

TelevisGo v10 is compatible with RS232-interface LTE/GSM modems:

- powered by SIEMENS TC35-type technology.
- "MODEM 4G LTE W/ANT PSU TRB 142" model (product code SAM4G0S00AA00).

NOTICE

INOPERABLE DEVICE

Make sure the PIN code on the Modem SIM card is disabled.

Failure to follow these instructions can result in equipment damage.

Modem connection can be performed directly via RS232.

Compatible devices

The list of compatible devices and the corresponding drivers is available on the website www.eliwell.com.

Hardware compatible with TelevisGo v10

The TelevisGo v10 software is compatible with and can be installed on all models with the code **TGOFXE.....**, **TGOEXE.....**, **TGODXE.....** and **TGODQE.....**

Configuring the TelevisGo v10

Users should be aware of the following:

- The default time zone is **GMT+1**
- TelevisGo v10 requires the creation of secure passwords for all users. On first access, only the “Administrator” user will be present.
To access, enter **Administrator** as the user and **0 (zero)** as the default password and you will be redirected to the password change page.
- Disconnect the USB devices after every maintenance procedure.

WARNING

UNAUTHORISED ACCESS

Do not give the password to unauthorized individuals or non-qualified personnel.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Carefully consider the implications of giving access to other people.

NOTICE

LOSS OF FUNCTION

Loss of the Administrator user password prevents access to system configuration. The password cannot be recovered.

Failure to follow these instructions can result in equipment damage.

NOTE: in the event of a lost password, contact Eliwell Technical Support to have it reset. The procedure requires Technical Support to be able to connect to TelevisGo v10 remotely.

NOTE: a secure password is one that has not been shared with or given to unauthorized personnel, and that does not contain personal or otherwise obvious information. Do not exceed 50 characters.

NOTE: Minimum password security criteria. For more information, please refer to the Microsoft website (<https://learn.microsoft.com/en-us/windows/security/threat-protection/security-policy-settings/password-must-meet-complexity-requirements>):

- Minimum 8 characters
- 1 numerical digit (0, 1, ... , 9)
- 1 uppercase letter (A, B, ... , Z)
- 1 lowercase letter (a, b, ... , z)
- 1 special character (|!'" \$%^&*()_+=[\];: '@#~<>,./?)

TelevisGo v10 is dedicated exclusively to executing the pre-installed application. Installing any other type of application may negatively affect the running of the entire system. The only installation permitted is anti-virus software.

NOTICE

INOPERABLE DEVICE

- Do not install any software on the TelevisGo v10 device with the exception of an anti-virus program.
- Make sure USB storage devices are disconnected to ensure the correct reboot of the computer.
- Make sure the anti-virus program installed does not block the TCP/UDP ports used by TelevisGo v10.
- Make sure the anti-virus program installed does not conflict with TelevisGo v10.
- Make sure the actions performed by the anti-virus program do not impact system performance.
- Do not inhibit active TelevisGo v10 services.
- Do not delete the “Eliwell” folder in the main directory on the “C:\” drive, nor any of the files or folders stored in it.

Failure to follow these instructions can result in equipment damage.

The user is responsible for choosing the type of anti-virus software to be installed.

Cybersecurity

Contents

This section includes the following topics:

Overview	26
Defense-in-Depth	26
Security hardening guidelines	28
Secure disposal guidelines	31
Secure operation guidelines	32
Account management guidelines	33

Overview

This Eliwell product features functions that enable information security. These functions are enabled by default and can be configured according to your installation requirements.

NOTE: deactivating or changing the settings for these individual functions can have a positive or negative effect on the overall strength of the device security and ultimately, the security-related behavior of the network.

It is also necessary to observe best practices in order to ensure robust system protection and the security of the system as a whole.

For more information, please refer to: “[Cybersecurity Best Practices](#)” (English language only).

Eliwell adheres to industry best practices in the development and implementation of control systems. This includes a defense-in-depth approach to guarantee an industrial control system. This approach protects the controller with one or more firewalls to limit access exclusively to authorized personnel and protocols.

 **WARNING**

UNAUTHORISED ACCESS AND SUBSEQUENT NETWORK INTRUSION

- Assess whether the room or the machines are connected to the critical infrastructure and, if so, take suitable preventative measures, based on “defense-in-depth” strategy, before connecting the automation system to any network.
- Minimize the number of devices connected to a network.
- Isolate your industrial network from other networks within the company.
- Protect any network from unintentional access using firewalls, VPNs or other proven security measures.
- Monitor activity within the systems.
- Prevent direct access or direct connection to the devices concerned by unauthorized individuals or unauthorized actions.
- Prepare a restore plan that includes system backup and process information.


Failure to follow these instructions can result in death, serious injury, or equipment damage.

Defense-in-Depth

Overview

The protection levels of the equipment are:

1. User security guidance
2. Secure Network Access (Intranet/VPN)
3. Centralized Monitoring & Alerts Management
4. Secure by Default
5. Authentication and Authorization
6. Software Authenticity
7. Physical protection



1. User security guidance

The User Guide is the first line of defence since it contains Safety Messages, Recommendations, etc.

2. Secure Network Access (Intranet/VPN)

The product is typically placed inside the customer's Intranet or VPN, so it benefits from the network's internal segmentation and controlled access, which significantly reduces exposure to external rogue actors. Its position behind perimeter defenses and authenticated tunnels makes unsolicited access from outside the organization far less likely. The equipment uses a hardened network interface with several ports intentionally blocked for security (see '[List of protocols and ports managed](#)' section). These ports are not required for normal operation, and opening them is strongly discouraged, as it may increase the attack surface. Administrators should not change the default port configuration unless explicitly instructed by authorized support staff. All communication must occur through the officially supported ports and protocols.

3. Centralized Monitoring & Alerts Management

TelevisGo v10 supports 24x7 centralized monitoring, continuously sending system data and alarms to a remote monitoring platform operated by a service provider. Any failure - such as software issues, cyber incidents, or power outages - is immediately detected, enabling rapid response and high system availability.

4. Secure by Default

To keep the attack surface as small as possible, the product is delivered out-of-the-box with unnecessary services removed or disabled, and unnecessary ports blocked.

5. Authentication and Authorization

The product follows a Secure by Default design philosophy and is shipped with secure factory settings. The system implements a role-based access control (RBAC) model to ensure secure and granular user management. Each user must authenticate with a unique set of credentials before accessing any system functionality. After successful authentication, the user is granted access only to the features and resources explicitly permitted by their assigned role. Authorization policies define the operations each user is allowed to perform, preventing unauthorized access to sensitive configuration settings or network data. Administrators can create, modify, and deactivate user accounts as needed.

6. Software authenticity

The product is delivered with signed software, which guarantees authenticity, and can only be updated using Schneider Electric and/or Eliwell signed software. The equipment can only be updated or upgraded with files digitally signed by Schneider Electric/Eliwell.

7. Physical protection

Make sure to install the equipment in a restricted access area accessible only by authorized personnel and protect the access to the communication ports.

Security hardening guidelines

This section outlines the operational guidelines for securely connecting a new equipment to the corporate network or the Internet. These measures are intended to minimize the attack surface, restrict access to essential services only, and ensure that IP configurations comply with the organization's security policies.

Requirements

Have the necessary permissions to manage network configuration.

Firewall Configuration

Proper firewall configuration is essential to limiting equipment exposure and enabling access solely to the services required for its operation.

General principles:

- Apply the principle of least privilege: all traffic is blocked by default; only what is strictly necessary is allowed.
- Enable only the ports and protocols required by the provided service.
- Restrict access to authorized networks or IP addresses only (for example, corporate subnets, management servers).
- Block all traffic originating from unrecognized or unauthorized networks.
- Enable logging of permitted and denied connections to support auditing and troubleshooting activities.
- Periodically review the configuration to ensure no obsolete or unnecessary rules have been added.

IP Address and Subnet Mask Assignment (Restrictive Approach)

A restrictive IP configuration enhances network segmentation and reduces equipment exposure.

Configuration Guidelines

- Assign static IP addresses when required, following the network infrastructure plan.
- Configure the smallest feasible subnet mask based on the actual number of equipment expected on the network segment.
- Avoid using overly large subnets unless necessary, to reduce broadcast traffic propagation.
- Assign the equipment to the appropriate VLAN based on its role, criticality, and operational requirements.
- Isolate critical equipment in dedicated subnets protected by Access Control Lists (ACLs) and specific firewall rules.
- Record all IP configuration details to facilitate management, maintenance, and security audits.

Information security configuration recommendations

There are several recommendations available for secure configuration of the device.

⚠ WARNING
UNINTENDED EQUIPMENT OPERATION
<ul style="list-style-type: none"> • Before attempting to control the application remotely, you must be perfectly familiar with the application and the machine. • Take the necessary precautions to guarantee that you are working on the anticipated machine remotely by using clear identification documentation within the application and the corresponding remote connection.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

⚠ WARNING

UNAUTHORISED ACCESS AND SUBSEQUENT NETWORK INTRUSION

- Assess whether the room or the machines are connected to the critical infrastructure and, if so, take suitable preventative measures, based on “defense-in-depth” strategy, before connecting the automation system to any network.
- Minimize the number of devices connected to a network.
- Isolate your industrial network from other networks within the company.
- Protect any network from unintentional access using firewalls, VPNs or other proven security measures.
- Monitor activity within the systems.
- Prevent direct access or direct connection to the devices concerned by unauthorized individuals or unauthorized actions.
- Prepare a restore plan that includes system backup and process information.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Note: Make sure that users have the necessary authorization only.

⚠ WARNING

POTENTIAL COMPROMISE OF SYSTEM AVAILABILITY, STATE AND SECURITY

- Deactivate unused ports/services and default accounts, if possible, to minimize communication channels for damaging attacks.
- Position the network devices behind various cyber defense levels (firewalls, network segmenting and network intrusion detection and protection systems).
- Adopt cyber security best practices (for example: minimal privileges, separation of functions, etc.) to prevent unauthorized exposure, loss of or changes to data and registries, the interruption of services or accidental operation.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Note: the table below contains the risks and best practices associated with unprotected protocols. We strongly recommend adhering to these best practices.

Unprotected protocols	Risks	Best practices
SMTP	<ul style="list-style-type: none"> • malware threat • unauthorized access to data • data loss threat • email content transferred to clear text 	For publication: <ul style="list-style-type: none"> • select SMTP with SSL/TLS or SMART TLS configured for publication
HTTP	<ul style="list-style-type: none"> • cross-site scripting • improper session management • cross-site request forgery • interception and tampering 	For network configuration: <ul style="list-style-type: none"> • disable HTTP • select HTTPS for network connections For publication: <ul style="list-style-type: none"> • do not select HTTP • select HTTPS with authentication
FTP	<ul style="list-style-type: none"> • FTP brute-force attack • packet sniffing • spoofing attack • user credentials may be compromised, as the entire authentication is carried out in unencrypted text 	For publication: <ul style="list-style-type: none"> • do not use FTP • select HTTP with authentication or SMTP with SSL/TLS or SMART TLS configured for publication
Modbus TCP/IP	<ul style="list-style-type: none"> • message interception • information acquisition • arbitrary command release • unauthorized users can harvest and/or tamper with device configurations 	For Modbus device communications: <ul style="list-style-type: none"> • limit access to Modbus communications using the Modbus TCP/IP filter • disable the Modbus port for each network interface when not in use

NOTICE

UNINTENDED EQUIPMENT OPERATION

- Do not connect the power cable to the RS485 serial port terminal.
- Before switching on the equipment, make sure it is not damaged and that all cables are securely fastened.
- Observe the minimum curve radius of the Ethernet cable to avoid damaging the equipment (typically: eight times the overall diameter of the cable).

Failure to follow these instructions can result in equipment damage.

List of protocols and ports

Enabling protocols or ports can lead to cyber security issues.
Refer to: "[Cybersecurity Best Practices](#)" (English language only).

The following is a list of ports / services that are enabled and can be configured:

- Web server: TCP port 443 (HTTPS)
- Modbus TCP: TCP port 502
- XML interface: TCP port 8080 (data transfer)

The following is a list of secure by default features:

- Firewall enabled to prevent external access to TCP port 80
- Remote Desktop disabled (TCP port 3389, RDP)
- TCP port 139 (NetBIOS) closed
- UDP port 137 (NetBIOS) closed
- TCP port 445 (SMB) closed

Personnel qualification

Only personnel with suitable training and an in-depth knowledge and understanding of the content of this manual and other documentation relating to the product in question are authorized to work on and with this product.

The qualified employee must be capable of identifying any hazards that may arise from the parameters, changing the value of the parameters and from using mechanical, electrical and electronic equipment in general. Plus, they must be familiar with accident prevention standards, provisions and regulations, which must be observed while the system is being designed and implemented.

Secure disposal guidelines

Requirements

Make sure you have the necessary authorization

Procedure

The guidelines for removing the equipment and help prevent potential data disclosure are:

1. Restore default values (see '**Restore factory default**' section)
2. Remove the equipment (component / system) from its intended environment
3. Recycle the equipment properly (see '**Disposal**' section)

Restore default factory settings

If necessary, you can restore the device to its factory settings by loading the system image (see [Restoring the disk image](#) section).

This procedure will delete the entire contents of the hard disk: software, data and custom settings.

Disposal

For security reasons, before removing the equipment, we recommend to reset the equipment to the factory default (see '[Restore factory default](#)').

NOTICE

DISCLOSURE OF APPLICATION DATA

Reset the equipment to the default values to help prevent data disclosure.

Failure to follow these instructions can result in equipment damage.



The equipment (or product) must be subjected to separate waste collection in compliance with the local legislation on waste disposal.

Secure operation guidelines

Requirements

Be logged in as the **Administrator** or a user with administrative rights (see 'User management' section).

Equipment upgrade

<i>NOTICE</i>
LOSS OF APPLICATION DATA <ul style="list-style-type: none">• When accessing the USB stick, do not turn off or reset the equipment.• Do not insert or remove the USB stick while accessing it.• Make sure at least one email recipient has been configured for proper notifications delivery.• Back up the reports received via email. Failure to follow these instructions can result in equipment damage.

The product can be upgraded only with files digitally signed by Schneider Electric/Eliwell. If the authenticity check fails, the upgrade is not applied.

<i>NOTICE</i>
UNINTENDED EQUIPMENT OPERATION <p>Use authenticated Schneider Electric or Eliwell files only.</p> Failure to follow these instructions can result in equipment damage.

To restore normal system operation, restore the system from system image.

Account management guidelines

User management

User management is used to create groups of users with configurable authorizations.

Access can be limited to a few functions by assigning individual users to a group.

There are 5 default groups:

- **Administrators:** rights for all functions
- **Operators/Users/Services:** read / write rights for selected functions
- **Readers:** read-only rights for selected functions

Only the **Administrator** or a user with administrative rights can add, edit or remove users and groups.

According to the principle of least privilege, make sure all users have only the authorizations they need.

Information security configuration recommendations

Do not add more users than those requiring access and evaluate the system requirements before allowing users access to critical pages, for example **Device settings**.

⚠ WARNING
POTENTIAL COMPROMISE OF SYSTEM AVAILABILITY, STATE AND SECURITY
Change the default passwords to prevent unauthorized access to device settings and information.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

Operating System Password

On first access, you will be prompted to change the operating system password for security reasons.

Carefully consider the implications of giving access to other people.

⚠ WARNING
UNAUTHORISED ACCESS
<ul style="list-style-type: none"> • Change the default password immediately, replacing it with a new and secure password. • Do not give the password to unauthorized individuals or non-qualified personnel.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

A secure password is never shared and does not contain personal or obvious information. Furthermore, a combination of upper-case and lower-case letters and numbers offers greater security. The password must contain at least 8 characters. Please refer to the Microsoft website for further information (<https://learn.microsoft.com/en-us/windows/security/threat-protection/security-policy-settings/password-must-meet-complexity-requirements>):


- 1 numerical digit (0, 1, ... , 9)
- 1 uppercase letter (A, B, ... , Z)
- 1 lowercase letter (a, b, ... , z)
- 1 special character (|!'" \$%^&*()_+=[\];: '@#~<>,./?)

NOTICE
LOSS OF FUNCTION
Loss of the Administrator user password prevents access to system configuration. The password cannot be recovered.
Failure to follow these instructions can result in equipment damage.


Adopt cybersecurity best practices (for example: minimal privileges, separation of functions, etc.) to prevent unauthorized exposure, loss of or changes to data and registries, the interruption of services or accidental operation. Refer to company rules concerning password expiry.

Set Password at First Access


1. Switch on TelevisGo v10. The following screen will appear:



2. Click "OK". The following screen will appear:



3. Enter the current Password: Leave the box empty
4. Enter the New Password (at least 8 characters)
5. Enter the New Password to confirm
6. If the Password does not meet the requirement for the minimum number of characters, the following screen will appear:



A secure password is one that has not been shared with or given to unauthorized personnel, and that does not contain personal or otherwise obvious information. Do not exceed 50 characters.

The password must contain at least 8 characters. Please refer to the Microsoft website for further information (<https://learn.microsoft.com/en-us/windows/security/threat-protection/security-policy-settings/password-must-meet-complexity-requirements>):

- 1 numerical digit (0, 1, ... , 9)
- 1 uppercase letter (A, B, ... , Z)

- 1 lowercase letter (a, b, ... , z)
- 1 special character (|!'" \$%^&*()_+ -=[]{};: '@#~<>./?)

Mechanical installation

Contents

This section includes the following topics:

Before starting	37
Disconnecting Power	37
Operating environment	38
Installation Considerations	38
TelevisGo v10 C Mechanical Installation	39
TelevisGo v10 DP Mechanical Installation	40

Before starting

Read and understand this chapter before beginning the installation of your system.

Pay particular attention in conforming to any safety information, different electrical requirements, and normative standards that would apply to your machine or process in the use of this equipment.

The use and application of the information contained herein require expertise in the design and programming of automated control systems. Only you, the user, machine builder or integrator, can be aware of all the conditions and factors present during installation and setup, operation, and maintenance of the machine or process, and can therefore determine the automation and associated equipment and the related safeties and interlocks which can be effectively and properly used. When selecting automation and control equipment, and any other related equipment or software, for a particular application, you must also consider any applicable local, regional or national standards and/or regulations.

WARNING

REGULATORY INCOMPATIBILITY

Be sure that all used equipments and designed systems comply with all applicable local, regional and national regulations and standards.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Disconnecting Power

Assemble and install all options and modules before installing the control system.

Before dismantling the equipment, remove the control system from the wall or panel.

DANGER

HAZARD OF ELECTRIC SHOCK, EXPLOSION, FIRE OR ARC FLASH

- Disconnect all power from all equipment including connected devices prior to removing any covers or doors, or installing or removing any accessories, hardware, cables or wires.
- Always use a properly rated voltage sensing device to confirm the power is off where and when indicated.
- Before powering the device back up, fit back and fix all the covers, hardware components and wiring.
- Verify the earthing connections on all earthed devices.
- Use this device and all connected products only at the specified voltage.

Failure to follow these instructions will result in death or serious injury.

Operating environment

This equipment is designed to operate in non-hazardous locations and where applications which generate (or could potentially generate) hazardous environments have been isolated. Install this equipment only in areas and with applications known to be constantly free from hazardous atmospheres.

DANGER

RISK OF EXPLOSION

- Install and use this equipment in non-hazardous locations only.
- Do not install or use this equipment in applications which could generate hazardous atmospheres, such as those which use flammable refrigerants.

Failure to follow these instructions will result in death or serious injury.

For information regarding the use of control equipment in applications capable of generating hazardous materials, please contact the relevant national regulatory bodies or certifying authorities.

WARNING

UNINTENDED EQUIPMENT OPERATION

Install and use this equipment in compliance with the conditions described in the “Technical data” section of this document.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Installation Considerations

WARNING

UNINTENDED EQUIPMENT OPERATION

- Use appropriate safety interlocks where personnel and/or equipment hazards exist.
- Power line and output circuits must be wired and fused in compliance with local and national regulatory requirements for the rated current and voltage of the particular equipment.
- Do not use this equipment in safety-critical machine functions.
- Do not disassemble, repair, or modify this equipment.

Failure to follow these instructions can result in death, serious injury, or equipment damage.


For the mechanical dimensions, refer to [TelevisGo v10 C mechanical Installation](#) and [TelevisGo v10 DP mechanical dimensions](#).

TelevisGo v10 C Mechanical Installation

Mechanical dimensions

The mechanical characteristics of TelevisGo v10 C are:

- Length: 174 mm (6.85 in.)
- Depth: 105 mm (4.13 in.)
- Height: 35 mm (1.38 in.)




How to install/uninstall the controller

TelevisGo v10 C is intended for wall- or panel-mounting (on a flat surface).

NOTE: TelevisGo v10 C is only suitable for indoor use. DO NOT install it outdoors.

To install, secure the device to the wall/panel with 4 screws (not supplied) in line with the holes illustrated in the figure below:




Note: leave the area around the slits clear to allow air recirculation and device cooling.

TelevisGo v10 DP Mechanical Installation

Mechanical dimensions

The mechanical characteristics of TelevisGo v10 DP are:

- Length: 274 mm (10.79 in.)
- Depth: 155 mm (6.10 in.)
- Height: 62 mm (2.44 in.)




How to install/uninstall the controller

TelevisGo v10 DP is intended for wall- or panel-mounting (on a flat surface).

NOTE: TelevisGo v10 DP is only suitable for indoor use. DO NOT install it outdoors.

To install, secure the device to the wall/panel with 4 screws (not supplied) in line with the holes illustrated in the figure below:



Note: leave the area around the slits clear to allow air recirculation and device cooling.

Electrical connections

Contents

This section includes the following topics:

Best wiring practices	42
Hardware TelevisGo v10 C	45
Hardware for TelevisGo v10 DP	46
Connecting a network	47

Best wiring practices

Warnings

The following information describes the guidelines for wiring and the practices to follow when using the TelevisGo v10 device.

  DANGER
HAZARD OF ELECTRIC SHOCK, EXPLOSION, FIRE OR ARC FLASH <ul style="list-style-type: none"> • Disconnect all power from all equipment including connected devices prior to removing any covers or doors, or installing or removing any accessories, hardware, cables or wires. • Always use a properly rated voltage sensing device to confirm the power is off where and when indicated. • Before powering the device back up, fit back and fix all the covers, hardware components and wiring. • Verify the earthing connections on all earthed devices. • Use this device and all connected products only at the specified voltage. <p>Failure to follow these instructions will result in death or serious injury.</p>

 WARNING
HAZARD OF OVERHEATING AND/OR FIRE Install and use the equipment exclusively in a protected environment, to prevent direct exposure to sunlight and atmospheric agents. <p>Failure to follow these instructions can result in death, serious injury, or equipment damage.</p>

 WARNING
UNINTENDED EQUIPMENT OPERATION <ul style="list-style-type: none"> • Install TelevisGo v10, SerialAdapter and EthernetAdapter in an environment in which EMC disturbance is below the limits specified in standard EN61000-6-1 (residential, commercial and light industry environments). • Configure the "LifeTest" function to make sure the TelevisGo v10 is active. Non-receipt of the periodic email indicates a malfunction of the TelevisGo v10 or the email sending service. <p>Failure to follow these instructions can result in death, serious injury, or equipment damage.</p>

 WARNING
LOSS OF CONTROL <ul style="list-style-type: none"> • Carry out a new network scan every time the type, configuration or number of controllers monitored is changed. • The installation designer must consider the potential failure modes of the control circuit and, for some critical control functions, provide a means for reaching a safe condition during and after a circuit failure. Examples of critical control functions are the emergency stop and end of travel stop, power supply cut-off and restarting. • Redundant control circuits that are separate from the TelevisGo v10 must be provided for critical control functions. • The control circuits can incorporate communication equipment such as proxy modems or network gateways. Keep in mind the implications of transmission delays or sudden connection failures. • Comply with all standards regarding accident protection and local applicable safety directives. • Every implementation of this device must be tested individually and completely in order to check its proper operation before putting it into service. • Do not disassemble, repair or modify this equipment. <p>Failure to follow these instructions can result in death, serious injury, or equipment damage.</p>

Wiring guidelines

Observe the following standards when wiring the TelevisGo v10 device:

- Keep the communication wiring separate from the power wiring. Keep these two types of cables in separate conduits.
- Check that the operating conditions and surroundings comply with the specification values.
- Use wires of the correct diameter and suited to the voltage and current requirements.
- Use copper conductors (required).
- Use twisted-pair shielded wires for networks and field buses.

Use shielded wires, correctly earthed for the communication connections. If shielded wires cannot be used for these connections, the electromagnetic interference may deteriorate the signal. Deteriorated signals can result in the device, modules or attached equipment operating incorrectly.

WARNING

UNINTENDED EQUIPMENT OPERATION

- Use shielded cables for all communication signals.
- Earth the wire shields for all communication signals in a single point.
- The signal cables (communication and relative power supplies) of the device must be laid separately from the power cables.
- Reduce the length of the connections as far as possible and avoid winding them round electrically connected parts.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Connections

The TelevisGo v10 device has the following communication ports:

- 4 RS232 serial ports
- 1 RJ45 Ethernet port

Take extra care when performing serial line connections.

Incorrect wiring may lead to faulty operation or breakdown of the equipment.

RS232/RS485

Connection is assured via the **Serial**Adapter and the system device must be connected using a cable with conductors of cross-section 0.5 mm²:

- Use a shielded "twisted pair" cable specifically for RS485. For laying wires, comply with the indications given in standard EN 50174 on information technology wiring. Extra care must be taken in separating data transmission circuits from power lines.
- The length of the RS485 network connected directly to the device is 1200 m (in compliance with ANSI TIA/EIA RS485-A and ISO 8482:1987 (E)).
- Single terminal board with 3 conductors which must all be used ("+" and "-" for the signal; "G" for 0 V earth signal).
- The network must have BUS DAISY CHAIN topology and must be equipped with 120 Ω - 1/4 W electrical termination between the "+" and "-" terminals and each of the two ends of the BUS, or enable those already provided on the devices.

Ethernet

The Ethernet connection is used by TelevisGo v10 to communicate on an Ethernet network via TCP/IP protocol. The main Ethernet features are:

- Protocol: Modbus TCP/IP
- Type of connector: RJ45
- Driver: 10 M / 100 M with auto-negotiation
- Cable type: shielded

Special Handling Considerations


When handling the equipment, use caution to avoid damage caused by electrostatic discharge. In particular, contact with uncovered connectors is likely to damage the controller due to electrostatic discharge.

⚠ WARNING
UNINTENDED EQUIPMENT OPERATION DUE TO ELECTROSTATIC DISCHARGE
<ul style="list-style-type: none"> • Store the equipment in the protective packaging until ready for installation. • Before handling the equipment, always discharge the static electricity from the body by touching an earthed surface or type-approved antistatic mat.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

Before any operations, check that the device is connected to a suitable external power supply. Please refer to "**Power supply**".

Hardware TelevisGo v10 C


The TelevisGo v10 C connectors are as follows:



Number	Label	Description
1	RST	Reset button
2	LAN	2x Ethernet ports RJ45 (LAN A and LAN B)
3	USB	1x USB 2.0 port and 3x USB 3.2 ports
4	HDMI	HDMI port - for external monitor
5	BTR	Battery status LED
6	HDD	HDD operating LED
7	PWR	Power LED. PWR (Power): Green LED = normal operation and amber LED = standby
8	DC 12V	12 Vdc power supply connector
9	GND	TelevisGo v10 C grounding connection
10	Display	Display port - for external monitor
11		ON/OFF button
12	Line-Out	Audio output
13	COM4	COM4 (RS232) serial port - for external modem
14	COM3	COM3 (RS232) serial port - for external modem
15	COM2	COM2 (RS232) serial port - for SerialAdapter
16	COM1	COM1 (RS232) serial port - for SerialAdapter

Hardware for TelevisGo v10 DP

The TelevisGo v10 DP connectors are as follows:




Number	Label	Description
1	USB 3.0	2x USB 3.0 ports
2	LAN	2x Ethernet ports RJ45 (LAN A and LAN B)
3	HDMI	HDMI port - for external monitor
4	Display	Display port - for external monitor
5	COM1	COM1 (RS232) serial port - for Serial Adapter
6	COM2	COM2 (RS232) serial port - for Serial Adapter
7	COM3	COM3 (RS232) serial port - for external modem
8	COM4	COM4 (RS232) serial port - for external modem
9	DC 12V	12 Vdc power supply connector
10		ON/OFF button
11	USB	2x USB 2.0 ports
12	HDD	HDD operating LED
13	SYS	Power supply LED

Connecting a network

SerialAdapter, **LanAdapter**, **EthernetAdapter** or Modbus TCP modules and system devices must be connected using a cable with conductors with cross-section 0.5 mm^2 (see "Connections").

SerialAdapter connection

Carry out the connection of the **SerialAdapter** module to the **TelevisGo v10** unit, including its power supply, as follows:




Device configuration

Before configuring a network using **TelevisGo v10**, each device in the network must be assigned a unique address within the same serial port, **LanAdapter** or **EthernetAdapter**, setting the following parameters based on the device protocol used:

- Device with Micronet protocol: parameters "**FAA**" (0...14) and "**dEA**" (0...14).
- Device with Modbus protocol: parameter "**Adr**" (1...255).

Network connected with Ethernet / serial gateway Modbus (EthernetAdapter)

An Ethernet/RS485 network is connected via **EthernetAdapter** as follows:



In the example the following devices were used:

- 1 **EthernetAdapter**
- 1 EWCM 9000 PRO-HF
- 2 **BusAdapter 150 Dongle**
- 2 EWNNext
- 1 FREE Optima

Signal propagation in an Ethernet network depends on bus traffic, making access times to the **EthernetAdapter** non-deterministic and potentially influencing TelevisGo v10 access time to the various resources with possible No-Link (loss of communication with the device).


NOTICE

INOPERABLE DEVICE

If connection proves difficult, check if the right profile has been assigned to the network; if not, change it accordingly.
Failure to follow these instructions can result in equipment damage.

Network connected with RS232

An RS232/RS485 network is connected via a **SerialAdapter** as follows:



In the example the following devices were used:

- 1x **SerialAdapter**
- 2x **BusAdapter**
- 2x EWNxt
- 1x TelevisIn

The **SerialAdapter** converter can only be connected to **COM1** or **COM2** as it is powered by them. Other serial accessories (modems) must be connected to serials **COM3** or **COM4**.

NOTICE

INOPERABLE DEVICE

Select the serial port which is suitable for the accessory you want to connect.
Failure to follow these instructions can result in equipment damage.

Technical specifications

Contents

This section includes the following topics:

Technical data	51
Further information	53
Power supply	53

Technical data

TelevisGo v10 C Technical data

Feature	Description
The product also complies with the following harmonized standards:	EN 62368-1
Product group:	End product
Classification of use by:	Skilled person
Equipment mobility:	Mobile
Method of mounting:	see section ' Mechanical Installation '
Degree of protection provided by enclosure:	IP30
Pollution degree:	2
Insulation class:	III
Power supply:	10...36 Vdc - via external power supply 100...240 Vac ($\pm 10\%$) 50/60 Hz(*)
Power supply connection type:	Not directly connected to line voltage (ES1)
Power systems:	Not to the AC line voltage
Ambient operating conditions:	Temperature: -20...60 °C (-4...140 °F) with airflow of 0.7 m/s (according to IEC Standard 60068-2-14). Humidity: 10...95% RH (non-condensing)
Transportation and storage conditions:	Temperature: -40...85 °C (-40...185 °F) Humidity: 10...95% RH (non-condensing)
Manufacturer's specified Tma (°C):	60 °C
Altitude during operation (maximum):	2000 m (6560 ft)
Mass of equipment:	0.80 kg (1.80 lb)
Special installation location:	Restricted access area

- (*) Only use the power adapter supplied or equivalent 100...240 Vac - 50/60 Hz - 24 Vdc $\pm 10\%$ 60 W. Contact Eliwell Technical Support for details.

WARNING

UNINTENDED EQUIPMENT OPERATION

Do not exceed any of the nominal values specified in the environmental and electric characteristics tables.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

TelevisGo v10 DP Technical data

Feature	Description
The product also complies with the following harmonized standards:	EN 62368-1
Product group:	End product
Classification of use by:	Skilled person
Equipment mobility:	Mobile
Method of mounting:	see section " Mechanical Installation "
Degree of protection provided by enclosure:	IPX0
Pollution degree:	2
Insulation class:	III
Power supply:	12 Vdc - via external power supply 100...240 Vac ($\pm 10\%$) 50/60 Hz(*)
Power supply connection type:	Not directly connected to line voltage (ES1)
Power systems:	Not to the AC line voltage
Ambient operating conditions:	Temperature: 0...40 °C (32...104 °F) with airflow of 0.5 m/s (according to IEC Standard 60068-2-14). Humidity: 10...90% RH (non-condensing)
Transportation and storage conditions:	Temperature: -20...60 °C (-4...140 °F) Humidity: 10...90% RH (non-condensing)
Manufacturer's specified Tma (°C):	40 °C
Altitude during operation (maximum):	2000 m (6560 ft)
Mass of equipment:	1.94 kg (4.28 lb)
Special installation location:	Restricted access area

- (*) Only use the power adapter supplied or equivalent 100...240 Vac - 50/60 Hz - 12 Vdc $\pm 10\%$ 60 W. Contact Eliwell Technical Support for details.

WARNING

UNINTENDED EQUIPMENT OPERATION

Do not exceed any of the nominal values specified in the environmental and electric characteristics tables.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

Further information

Feature	Description
Maximum number of devices connected:	224
Operating system:	Windows 10 IoT Enterprise LTSC 2021 (English). NOTE: the label with the license number is applied to the device
User interface:	User interface for supervision and remote control
Software update:	Remote (via internet)
Connections:	<ul style="list-style-type: none"> Ethernet (RJ45) external GSM modem integrated USB
Power failures:	Non-volatile internal memory, duration 10 years
Registration interval:	Can be configured between 1 minute and 2 hours (default 15 minutes) ⁽¹⁾
Registration time:	1 year's worth of data guaranteed for 1500 analogue resources (if registration interval is 15 minutes) ⁽²⁾
Maximum relative weather measurement error and weather recording error:	< 0.1 %
Climate range:	'type A' in air
Languages supported:	Italian / English / Spanish / German / French / Russian / Dutch / Polish / Portuguese / Chinese / Turkish / Japanese

- (1) The minimum interval that can be set to make certain of re-reading all resources depends on the network response time (see 'Real-time data').
- (2) The presence of digital resources or machine statuses subject to a higher or lower number of variations may change the duration of the specified archive period. In this case, refer to the archive user interface pages to verify the memory capacity of your system (see '[Registration interval settings](#)').

Power supply

The device is powered at 10...36 Vdc (TelevisGo v10 C) or 12 Vdc (TelevisGo v10 DP) via an external power supply 100...240 Vac ($\pm 10\%$) 50/60 Hz.

According to the requirements of the individual unit and/or the country of installation, if the mains voltage in the country is within the operating range, the device can be connected directly to the mains.

To avoid accidentally switching off the computer, the ON/OFF button must be pressed for at least 4 seconds.

In the event of a blackout, the computer and application restart automatically when the mains power is restored.

User interface and device configuration

Contents

This section includes the following topics:

Accessing the user interface	55
Login	56
Changing the password	57
Page structure	58
Status bar	58
Navigation menu	59
Initial device configuration	60
Status icons	60
Buttons and selectors	61

Accessing the user interface

TelevisGo v10 has an advanced user interface, accessed via web browser from any PC or mobile device, in order to analyze data and control all functions of the system.

To access the WEB interface, TelevisGo v10 must be switched on and connected to the Internet.

TelevisGo v10 will automatically open a local browser page with the device address.

The factory-set network parameters are as follows:

Ethernet 1 (ETH1)

- **Static IP address** = 192.168.1.50
- **Subnet mask** = 255.255.255.0

Ethernet 2 (ETH2)

- **Static IP address** = 192.168.1.51
- **Subnet mask** = 255.255.255.0

To ensure proper connection between the computer and TelevisGo v10 (Ethernet), the computer must have an IP address configured that is compatible with TelevisGo v10 subnet mask (normally the same Subnet mask and IP address, in which only the fourth numerical block changes to be different for each element in the sub-network).

For more detailed information and special installations, contact the network administrator.

Incorrect configuration of the network connection parameters or the router can prevent connection to the TelevisGo v10 and the device network via web interface.

NOTICE


INOPERABLE DEVICE

Make sure the configuration for the network connection and the router is correct.

Failure to follow these instructions can result in equipment damage.

Login

The Login page is used to access the system with your credentials and to select the language used by the user interface (by default this is the browser language).



The window contains:

1. Plant name
2. Registration status ( = started,  = stopped) and number of services () connected to TelevisGo v10.
NOTE: The number is present only if at least one service is connected.
3. Alarm status ( = alarms active,  = no alarm active,  = non-computable alarms).
4. Number of users connected to TelevisGo v10 ().
NOTE: The number is present only if at least one user is connected.
NOTE: TelevisGo v10 can be connected simultaneously to a maximum of 3 different users.
5. Select user interface language
6. Enter username
7. Enter password
8. Show password ()
9. Access TelevisGo v10 ()
10. System information

For more details relating to the icons, refer to the “[Status bar](#)” section.

NOTE: with the exception of real-time pages (Equipment and Alarms), the session automatically expires after 20 minutes of inactivity.

NOTE: if the user enters an incorrect password, the message “Wrong password” will appear:



If 3 consecutive incorrect password entry attempts are made, the message “The user is temporary disabled” will appear.



The user will be locked out for 10 minutes. At the end of this period the user can attempt login again.

Changing the password

The following password change screen opens:

Change your password

Current password*

1

New password*

2

3

- Minimum 8 chars
- Minimum 1 lowercase letter
- Minimum 1 digit
- Minimum 1 uppercase letter
- Minimum 1 special char
 \!@#\$%^&*()_+=[\]{};:'@#~<>./?

Confirm password*

4

Expiration*

5 90 days ▼

6 Change

The window contains:

1. **Current password:** enter the current password.
 : show/hide the password entered
2. **New password:** enter the new password.
 : show/hide the password entered
3. **Password content:** list of characters that the password should contain
 - Minimum 8 characters
 - 1 numerical digit (0, 1, ... , 9)
 - 1 uppercase letter (A, B, ... , Z)
 - 1 lowercase letter (a, b, ... , z)
 - 1 special character (\!@#\$%^&*()_+=[\]{};:'@#~<>./?)
4. **Confirm password:** enter the new password.
 : show/hide the password entered
5. **Expiration:** select the password expiry period from pre-set options:
 - 90 days
 - 180 days
 - 1 year
 - never
6. **Change:** save the changes and redirect the user to the "Home" page (🏠).

NOTE: when the password expires, the user will be redirected straight to the password change page. Once it has been changed, they will be taken to the "Home" page.

Page structure

All pages in the web application have the same structure, i.e.:

- Status bar
- Navigation menu
- Work area

Status bar

The status bar is always shown at the top of the window, providing important system status information. The Status Bar consists of the following elements, displayed as text and icons:

Plant name:		shows the system name.
Registration status and number of connected services:		Started: acquisitions are active and the total number of connected services.
		Stopped: acquisitions are not active.
Alarm status:		Active: active alarms are present.
		Not active: no active alarms are present.
		Not computable: non-computable alarms are present.
Username and number of connected users:		<p>indicates the name of the user and the total number of connected users. The drop-down menu shows the following icons:</p> <ul style="list-style-type: none"> •  = End the session for the current user and return to the Login screen •  = Edit the password for the current user •  = Set the screen shown as the default screen for the current user. This function is only available on screens that can be configured as default screens.

Navigation menu

The navigation menu is shown at the top of the page and contains the hypertext links to the different sections of the application:

	---	Used to go back to the default screen. For the factory setting, go back to the "Equipment" page.
	Equipment	Used to: <ul style="list-style-type: none"> view network devices filter by individual devices (name, model, etc.) configure individual devices add new devices add new interfaces
	Alarms	Used to: <ul style="list-style-type: none"> view devices in alarm mode and the relevant status acknowledge alarms, entering any notes required view detailed reports for the various alarms configure categories, actions and time intervals
	History	Used to view/configure: <ul style="list-style-type: none"> alarm history data archive in table form data archive in chart form energy reports in table form energy reports in chart form
	Functions	Used to: <ul style="list-style-type: none"> start/inhibit acquisition view controller commands view controller parameters activate the RVD (Remote Virtual Device) function (if present for the device) view/edit layouts
	Settings	Used to view: <ul style="list-style-type: none"> interfaces users and groups of users alarms (categories, actions, time intervals) scheduled actions General settings (Life Test, Alarms, Media, etc.)
	Computer	Used to: <ul style="list-style-type: none"> manage network settings update the application, functions and languages update parameter maps, layout pages and various settings update algorithm and device drivers restart the application TelevisGo v10 update the license backup and restore the system view the reports (.TXT) for activities carried out

Some menus have a number of associated commands listed under the menu bar (sub-menu) (example: "Alarm History", "Historical Table", ...).

Clicking a menu changes the sub-menu but not the current page.

Clicking a sub-menu heading changes the current page.

Initial device configuration

On first start-up:

- navigate to the “Equipment” page (on first start-up the page will be empty)
- click “Add device(s)”
- click "Interfaces"
Note: the COM1 interface is pre-configured by default
- add any interfaces present in the network in addition to the COM1 interface (see [Interface definition](#))
- press the back button 
- add network devices (see [Adding a device](#))

Status icons

The user interface illustrates the status of the system and the device network.

Acquisition status	
	Data acquisition running.
	Data acquisition not running.
	No information on data acquisition.
	Start/Stop data acquisition.
Alarm status	
	Alarm active.
	Active alarm viewed by the user.
	Alarm reset.
	Alarm has never been active.
	No information on alarm status. Note: check the data acquisition status.
Resource status	
	Compressor: On / Off.
	Defrost: On / Off.
	Port: Open / Closed.
	Fans: On / Off.
Inputs and regulators	
	Analogue resources.
	Digital resources.
	Machine status.
	Alarms.
NoLink	
	NoLink: no communication with the device.
Filters	
	Identifies the devices on which the algorithm works.
	Identifies an input resource on which the algorithm works.
	Identifies an output resource on which the algorithm works.

Buttons and selectors

Acquisition status		
	Start/Edit	Start/edit TelevisGo v10 acquisition status.
Data viewing screens		
	Expand	Expand the view of all elements in a list.
	Collapse	Collapse the view of all elements in a list.
	Select all	Select all the elements in a list.
	Deselect All	Deselect all the elements in a list.
	Print	Exports the data in PDF format for printing.
	Confirm	Confirms alarm selection. Alarm icon turns from red to yellow.
Data archive		
	Update data	Update the data after one or more filters have been edited.
	Data archive window	Show/hide the data selection window.
	Profile window	Show/hide the profile management window.
	Load selected Profile	Upload the selected profile to the TelevisGo v10.
	Delete selected Profile	Delete the selected profile from the TelevisGo v10.
	Save current profile	Save the selected profile.
	Time interval window	Show/hide the window used to set time intervals.
	Interval forward	Move the interval for the data shown forward.
	Interval back	Move the interval for the data shown back.
	Resources window	Show/hide the "Resources" window.
	Select resources	Manually select the instruments and resources to view.
	Legend window	Show/hide the window providing the colors legend (charts only).
	Print/Export window	Show/hide the Print/Export window for the data shown.
	Export	Export the elements shown in .csv format into a folder selected by the user.
Network configuration		
	Enter interface	Enter a new network interface.
FUNCTIONS		
		Select an instrument from the network, viewing its parameters and the RVD (Remote Virtual Device), if applicable.
	Select all	Select all the elements in a list.
	Deselect All	Deselect all the elements in a list.
	Expand	Expand the view of all elements in a list.

	Collapse	Collapse the view of all elements in a list.
	Cancel filters	Cancel all filters applied.
	Execute	Send the command to the selected instruments.
	Apply command filter	Hide the commands which are not applicable for the selected devices. If activated, the  icon will appear.
	Remove command filter	Removes the previously applied command filter.
	Write on ...	Write the values of the current instrument on one or more selected instruments.
	View the last operation report	View the result of the last parameter writing procedure.
	Save parameter map	Save a parameter map to disk.
	Load parameter map	Load a parameter map from the disk.
	Print	Print the elements shown.
	Zoom	View in full screen mode.
	Restore	Restore normal view.
	Rebuild all layouts	Update the list of loaded layouts.
SETTINGS		
	Edit	Enable active page editing.
	Select all	Select all the elements in a list.
	Select devices present	Select the devices present.
	Select invalid devices	Select devices that are not valid.
	Deselect All	Deselect all the elements in a list.
	Expand	Expand the view of all elements in a list.
	Collapse	Collapse the view of all elements in a list.
	Profile manager	Open a new screen where a profile can be created, edited or removed.
	Export profiles	Export the selected profiles.
	Cancel filters	Cancel all filters applied.
	User group	Indicate the user group.
	users	Indicate individual users.
	Add	Add an element (network, user, scheduled activity, time interval, etc.)
	Remove	Remove an element (network, user, scheduled activity, time interval, etc.)
	Edit	Edit an element (network, user, scheduled activity, time interval, etc.)
	Save	Save any changes you have made.

	Cancel	Cancels and exits without saving the changes made.
	Preview	Preview of the instruments on which the selected action will be performed.
COMPUTER		
	Edit	Enable active page editing.
	Application	Update TelevisGo v10 application.
	Functions	Update/load the software applications.
	Languages	Update/load the system glossaries.
	Parameters map	Load a parameters map.
	Layout pages	Load a layout.
	General settings	Load the file "Forced_setting.txt". This file is sent via an update (in the .zip file) or via Eliwell Technical Support.
	Scheduled actions	Update/load the scheduled actions.
	Alarm categories	Update/load the alarm categories.
	Device/algorithms drivers	Update the drivers for the instruments/algorithms.
	Reboot	Reboot the TelevisGo v10 application.
	Backup	Back up the configuration for restoring at a later stage.
	Restore	Restore the configuration saved using the backup function.

Equipment

Contents

This section includes the following topics:

Introduction	65
Viewing and filtering network equipment	66
Basic device information tab	67
Viewing equipment data	69
Network devices list	71
Adding equipment	73
Equipment data settings	75
Device resources	77
Equipment alarms	79
History	80
Parameters	81
Commands	82

Introduction

Description


This section can be used to:

- [view and filter network devices](#)
- filter by individual devices (name, model, etc.)
- configure individual devices
- add new devices
- add new interfaces

Viewing and filtering network equipment

Description

On accessing or entering the  EQUIPMENT menu, the following window will appear:



The window contains:

- Select all devices shown. If a filter is applied, only those meeting the filter requirements will be selected
- Filter devices by controller model (for example: RTX 600/V) or by description (for example: Fish cabinet).
- Apply/remove the filter for devices in alarm mode only
- Apply/remove the filter for devices in "Maintenance" mode only
- Apply/remove the filter for the groups associated with the devices (for example: meat, fish, etc.).
NOTE 1: the groups can be set on the device configuration page.
NOTE 2: a device can belong to several groups
- Show/hide the following filters:
 - Profile Type:** displays the devices and resources associated with a specific profile
 - Group Type:** displays the devices and resources associated with a specific group
 - Communication status:** displays devices that are recognized, mismatched, partially matched, or No-Link
 - Protocol Type:** displays devices using a specific protocol (Modbus or Micronet).
 - Fieldbus interface:** displays the devices for a specific interface or address.
- Drop-down menu to change the display type. Options:
 -  (**Cards**): display the devices on cards showing the linked image
 -  (**Grid**): display the devices on cards without the linked image
 -  (**Compact**): Simplified view of equipment data (statuses and 1 resource only)
- Enable entry of a new device (**Add Device**)
NOTE: the button is only visible if the current user is authorized to configure the network of controllers.
- View the resources in the foreground.
- Tab with basic information for a specific device. Click to view the details of that specific device.
- Only appears if one or more devices are selected (using the check box in the top left-hand corner of each tab) and:
 -  (**Maintenance**): put the selected devices into "Maintenance" mode
 -  (**Import**): apply a specific device profile to the selected devices
 -  (**Remove**): remove the selected devices from the configuration

Basic device information tab

Description

1 Meat cabinet 2
001 (00:01)@COM1 3

4 5 6 7 8 9

Meat cabinet probe	24,9 °C	
Valve 1 opening percentage	100,0 °C	
PLA00200 10	11 5,0 °C/°F	
Compressor 1	Active	
Defrost 1	Inactive	
Probe AI error 1	Confirmed	

High (Evaporator fan probe) Inactive

13 Show more

The tab contains:


- identifies status and selects device
 - = The device is connected
 - = The device has not yet been recognized
 - = The device is in No Link mode
 - = The device has not yet been included in the configuration
 - = The device partially corresponds to the set model
Note: the parameters and commands functions are not enabled
 - = The device does not correspond to the set model
Note: model change is required
 - = The device is in "Maintenance" mode
 - = Shown as the mouse passes over, used to select the device
- Name assigned to the device
- Controller address and fieldbus interface
- Cooling function status (if managed by the controller):
 - = Cooling active
 - = Cooling inactive
- Defrost function status (if managed by the controller):
 - = Defrost active
 - = Defrost inactive
- Evaporator fan status (if managed by the controller):
 - = Fans active
 - = Fans inactive
- Door status (if managed by the controller):
 - = Door open
 - = Door closed
- Alarm icon:
 - = No alarm active
 - = At least one alarm active
 - = All alarms have been viewed and acknowledged
- The 3 dots on the right-hand side can be used to:
 - (Edit):** change the device settings
 - (Maintenance):** put the selected devices into "Maintenance" mode

-  (**Import profile**): apply a specific device profile to the selected devices
 -  (**Export profile**): export a specific device profile
 -  (**Change model**): change the "Model" and "Device profile"
 -  (**Remove**): remove the selected devices from the configuration
10. View the resources in the foreground.
NOTE: if one or more alarms are selected in the foreground, the last 2 rows will be reserved for alarm resources
 11. Shows the values of the selected resources in real time
 12. Image associated with the device
 13. Appears when the resources in the foreground are more than those that can be displayed and can be used to scroll through them in the device tab.

Viewing equipment data

Description

On accessing or entering the  EQUIPMENT menu and selecting one of the devices, the following window will appear:



The screenshot shows the TelevisGo interface for a 'Meat cabinet 1'. The interface includes a navigation menu (1), a list of network devices (2), and a detailed view of the device's status and parameters. The detailed view includes a table of parameters and a table of resources.

Description	Value	Unit	Groups
Meat cabinet probe	25,0	°C	meat, defrost
Meat cabinet probe 2	**	°C	meat
Control probe 2	**	°C	
Temperature alarm probe 1	25,0	°C/F	meat
Temperature alarm probe 2	**	°C/F	
Defrost probe 1	25,6	°C/F	meat, defrost
Defrost probe 2	**	°C/F	meat
Evaporator fans probe	**	°C/F	

The window contains:

- Navigation menu
- List of network devices including display filters (see [Viewing network devices](#))
- Image associated with the device
- Name assigned to the device
- View link to any document associated with the controller. Only shown if included in the device settings
- Shows whether a reference to a website, a telephone number or an email address has been entered. Only shown if included in the device settings
 - **URL** (): used to enter the Url for a website or a local TelevisGo v10 address preceded by "/" (example: "/app/alarms")
 - **CALL** (): used to enter a telephone number. Requires an international prefix to be entered (for example: +39).
 - **MAIL** (): used to enter an email address
- Controller status icons (device status, alarm, cooling, defrost, evaporator fans)
- Actions**: drop-down menu with the following options (only shown if the current user is authorized to configure the network of controllers or maintenance):
 -  (**Edit**): change the device settings
 -  (**Maintenance**): enter the "maintenance" mode duration time. Click "Change" to enable it.

Maintenance mode

Duration *


-  (**Import**): apply a device profile to the selected devices
-  (**Export profile**): export a device profile
-  (**Change model**): change the "model" and "device profile"

-  **(Remove)**: remove the selected devices from the configuration
- 9.  **(Maintenance)**: Status and duration of the controller in maintenance mode. Setting takes place within the “Actions” drop-down menu and you can exit Maintenance mode using the switch to the right of the “Maintenance” button.
- 10. List of basic device information:
 - Model of the controller paired with the device
 - Controller address and fieldbus interface to which it is connected
 - Type of protocol used by the controller
- 11. Image to scan to view the user manual for the controller
- 12. Information relating to the device:
 - Controller model
 - Controller serial number
- 13. List of groups associated with the device
- 14. View the resources in the foreground. These resources are shown in the Device tab on the Devices page.
- 15. It can be used to select the following data tabs:
 -  **(Resources)**: list of resources
 -  **(Alarms)**: list of alarms
 -  **(History)**: historical data shown in the form of a table or chart
 -  **(Parameters)**: link to the list of parameters
 -  **(Commands)**: link to the list of commands
- 16. Show detailed data for the selected tab.

Network devices list

Description

On accessing or entering the  Equipment menu and selecting one of the devices, the following window will appear:



The window contains:

1. Select all devices shown. If a filter is applied, only those meeting the filter requirements will be selected
2. Filter devices by controller model (for example: RTX 600/V) or by description (for example: Fish cabinet).
3. Filter devices by category (for example: meat, fish, etc).
NOTE 1: the categories can be set on the device configuration page.
NOTE 2: a device can belong to several categories
4. Apply/remove the filter for devices in alarm mode only
5. Apply/remove the filter for devices in “Maintenance” mode only
6. Show/hide the following filters:
 - **Profile Type:** displays the devices and resources associated with a specific profile
 - **Group Type:** displays the devices and resources associated with a specific group
 - **Communication status:** displays devices that are recognized, mismatched, partially matched, or No-Link
 - **Protocol Type:** displays devices using a specific protocol (Modbus or Micronet).
 - **Fieldbus interface:** displays the devices for a specific interface or address.
7. List of basic device information (device profile associated with the device, controller address and fieldbus interface to which it is connected, type of protocol used by the controller and status icons)
8. The 3 dots on the right-hand side can be used to:
 -  (**Edit**): change the device settings
 -  (**Maintenance**): put the selected devices into “Maintenance” mode
 -  (**Import profile**): apply a specific device profile to the selected devices
 -  (**Export profile**): export a specific device profile
 -  (**Change model**): change the “Model” and “Device profile”
 -  (**Remove**): remove the selected devices from the configuration
9. Only appears if one or more devices are selected (using the check box to the left of each device) and shows:
 -  (**Maintenance**): put the selected devices into “Maintenance” mode. **NOTE:** the button is only enabled if the current user is authorized to manage maintenance

-  (**Import**): apply a specific device profile to the selected devices
 -  (**Remove**): remove the selected devices from the configuration
10. Used to enter a new device ([Add Device\(s\)](#))
NOTE: the button is only visible if the current user is authorized to configure the network of controllers.
 11. Offers access to the page used to define the network fieldbus interfaces ([Add/edit a fieldbus interface](#))
NOTE: the button is only visible if the current user is authorized to configure the network of controllers.
 12. Indicates the total number of network devices

Adding equipment

Description

On accessing or entering the  EQUIPMENT menu, if you select "**Add equipment(s)**" in the top right-hand corner or select one of the pieces of equipment, then click "**Add equipment(s)**" in the bottom left-hand corner, the following window will appear:

NOTE: the button is only visible if the current user is authorized to configure the network of controllers. The window that opens contains the following editable fields (those marked with a red asterisk are compulsory):

1. Select the controller model or select "Auto-Detection Modbus" or "Auto-Detection Eliwell" to automatically scan using Modbus protocol or Micronet/Eliwell protocol respectively.
2. Select the equipment profile to use, from:
 - **system**: automatically generated profile with minimal settings (provided by Eliwell)
 - **Eliwell**: pre-configured profile with the most common settings (provided by Eliwell)
 - **Custom**: custom profile (contact Eliwell Technical Support for system customization)
3. Select the fieldbus interface to which the controller is connected (for example: COM1). If the interface does not appear, you need to configure it first (see [Configuring Fieldbus Interfaces](#)).
4. Set the range of addresses to scan in order to detect the controller. Click  to add it. The list of ranges set appears under **Address list**. Alongside every range is a  button that can be used to delete it. For Modbus equipment, the address is displayed as 1 (00:01), where the first number identifies the Modbus address and the corresponding Micronet address is in brackets.
5. Show/hide settings relating to the protocol for the selected interface.
6. Additional settings relating to the protocol type. The interface type cannot be changed, in contrast to the serial transmission speed (**Baud Rate**) and the communication parameters (**Format**) represented by 3 characters, e.g. "8E1", with the following meaning:

8	Size = 8 bit	Options: 8 bit
E	Parity bit = Even	Options: n = none; E = even; o = odd
1	Stop bit = 2 bit	Options: 0 = 1 bit; 1 = 2 bit

7.  **SAVE:** save the settings and check them. If the settings are correct, the equipment will be added to the network list (see [Network devices list](#)).

8. **RESET**: reset the data entered on the screen
9. **MODBUS**: shown if the set interface is Modbus type and shows the addresses already occupied by other equipment ()
10. **MICRONET/ELIWELL**: shown if the set interface is Micronet/Eliwell type and shows the addresses already occupied by other equipment ()

Alarm indications (Warnings)

After clicking  **SAVE**, the system checks the data entered and shows a warning pop-up (warning image) in the following cases:

Where	Message	Reason/Solution
Addresses	The range contains addresses that are not valid for the protocol	At least one invalid address has been entered for the selected protocol. Entry is only completed for valid addresses
Addresses	The range contains the supervisor address	The supervisor address is included in the selected range. This address cannot be selected
Addresses	At least one existing equipment address has been entered	At least one existing equipment address has been entered. You will be asked to confirm overwrite or cancel entry

Automatic identification of the controller model

If “Auto-Detection Modbus” or “Auto-Detection Eliwell” was selected during configuration of the controller, the system will read the information field relating to the connected controllers.

“Auto-Detection Modbus” selection works for Eliwell equipment and for third-party Modbus equipment for which Eliwell provides the driver.


This process may take a few minutes.

The controllers identified successfully change from the initial description “Auto-Detection Modbus” or “Auto-Detection Eliwell” to the name of the identified model.

NOTE: make sure all equipment has been recognized correctly.

Equipment data settings

Once you have entered device viewing mode, use the “Configuration” drop-down menu to select  Edit and the following device setting window will appear:



The window contains:

- Navigation menu
- List of network devices with various display filters (see [Network devices list](#))
- Name assigned to the device
- Controller status icons (device status, alarm, cooling, defrost, evaporator fans)
- Actions:** drop-down menu with the following options:
 -  **(View)**: revert to “View device” mode
 -  **(Maintenance)**: put the selected device into “Maintenance” mode
 -  **(Import)**: apply a device profile to the selected devices
 -  **(Export profile)**: export a device profile
 -  **(Change model)**: change the “model” and “device profile”
 -  **(Remove)**: remove the selected devices from the configuration
- List of basic device information:
 - Model of the controller paired with the device
 - Controller address and fieldbus interface to which it is connected
 - Type of protocol used by the controller
- Image to scan to view the user manual for the controller
- IMAGE:** Image associated with the device. If you click on the image, you can upload images in ".jpg", ".jpeg", ".jfif", ".webp", ".png", ".apng", ".bmp", ".svg", ".svgz", ".xbm", ".ico", ".gif", ".tif", ".tiff", ".pjp", ".jpeg", ".avif" format with a maximum size of 5 MB.
 -  **Remove image:** used to remove the uploaded image
- Used to set the following information:
 - **Description:** assign the device name
 - **Model:** device model (optional)
 - **Serial Number:** device serial number (optional)
 - **Link:** used to enter a reference to a website, a telephone number or an email address
 - **URL** (): used to enter the Url for a website or a local TelevisGo v10 address preceded by "/" (example: "/app/alarms")
 - **CALL** (): used to enter a telephone number complete with international dialing prefix
 - **MAIL** (): used to enter an email address
 - **Link Label:** assign a name to the entered link
 - **File:** used to load a file to make available for download, for example the device manual or the controller parameters. Available file formats: ".pdf", ".txt", ".jpg", ".jpeg", ".jfif", ".webp", ".png", ".apng", ".bmp", ".svg", ".svgz", ".xbm", ".ico", ".gif", ".tif", ".tiff", ".pjp", ".jpeg", ".avif" with a maximum size of 25 MB.
 - **OPEN FOLDER** (): used to open explore resources and load a file
 - **REMOVE** (

): used to remove the loaded file


- **File Label:** assign a name to the loaded file

10. List of groups associated with the device. New categories can be entered by pressing “Add new group”
11. View the resources in the foreground. These resources are shown in the Device tab on the Devices page.
12. It can be used to select the following data tabs:
 -  (**Resources**) = list of resources that can be selected
 -  (**Alarms**) = list of alarms that can be selected
 -  (**History**) = view the data archive for the instrument in the form of a table or chart
 -  (**Parameters**) = link to the list of parameters
 -  (**Commands**) = link to the list of commands
13. Shows the information relating to the selected tab.

Device resources

Once you have entered equipment viewing mode, use the “Configuration” drop-down menu to select  EDIT.
Then select the TAB:  Resources.

The following window will appear:



The following fields appear at the top:

1. Filter the resources in the description column on the basis of a keyword
2. Show/hide the “Value” column for the resources
3. Enlarge the table to full-screen view
4. Can be used to drag the resource (or a group of resources selected using the check box) to a different position. Sort the list of resources in the foreground as shown in this TAB
5. Select/deselect a resource. Select multiple to apply the same settings
6. Add/remove a resource to or from the resources in the foreground
7. **DESCRIPTION:** view/edit the name of a resource
8. **VALUE: (only shown if point 2 is selected)** Show the resource value in real time
9. **UM:** view/edit the resource unit of measure
10. **GROUPS:** used for rapid selection of the resources to be shown in charts and historical tables
11. **HACCP:** identify whether the resource is entered in the HACCP report.
Note: several analogue resources can be selected, but only one digital resource (for example: defrost) for each device
12. **ENERGY:** identify whether the resource is entered in the “Energy report”
13. **HISTORY:** enable/disable saving in the data archive
14. **QUICK:** enable/disable data recording with frequent sampling and storage in the temporary database (recent data only)
15. **LOW/HIGH:** view/edit the alarm thresholds (see “Virtual alarms” section)
16. **COLOR:** assign a color to a resource for display on real-time and historical charts
17. **SWITCH:** enable (green)/disable (gray) reading and use of the resource. This setting takes priority over all the other resource settings.

Virtual alarms

When a value relating to each analogue resource is entered, the system will generate the corresponding “**virtual alarms**” inside the LOW/HIGH cell (point 15).

If, for example, you set:

Resource	Low	High
Analogue input 1	(A) 30	(B) 60
Analogue input 2	-	-
Dew point	-	(C) 45
Valve opening percentage	-	-
Door opening status	(D) 1	(E) 0

the following “virtual alarms” will be generated:

Resource	Alarm due to...	Description
(A) Low alarm (Analogue input 1)	Low	Activated when the value of analogue input 1 is < 30
(B) High alarm (analogue input 1)	High	Activated when the value of analogue input 1 is > 60
(C) High alarm (Dew point)	High	Activated when the value of the Dew point is > 45
(D) Low alarm (Door opening status)	Low	Deactivated when the value becomes 0
(E) High alarm (Door opening status)	High	Activated when the value becomes 1

The new alarms will inherit all the properties of the instrument to which they refer (option of putting them offline, choice of infill/color inside graphs and any activation delays).


If the analogue resource to which the “**virtual alarms**” refer is no longer present, the alarms will be deleted.

Equipment alarms

Once you have entered equipment viewing mode, use the “Configuration” drop-down menu to select  EDIT.

Then select the TAB:  ALARMS.

The following window will appear:



Description	Value	Delay	Groups	Color	Id	En...
Device Changed	-5.2	00:05:00		Not set	ALM00301	<input checked="" type="checkbox"/>


The following fields appear at the top:

1. Filter the resources in the description column on the basis of a keyword
2. Show/hide the “Value” column for the resources
3. Enlarge the table to full-screen view
4. Can be used to drag the resource (or a group of resources selected using the check box) to a different position. Sort the list of resources in the foreground as shown in this TAB
5. Select/deselect a resource. Select multiple to apply the same settings
6. Add/remove a resource to or from the resources in the foreground
7. **DESCRIPTION:** view/edit the name of a resource
8. **VALUE:** (only shown if point 2 is selected) Show the resource value in real time
9. **DELAY:** used to enter a delay before alarm activation
10. **GROUPS:** used for rapid selection of the resources to be shown in charts and historical tables
11. **COLOR:** assign a color to a resource for display on real-time and historical charts
12. **Id:** alarm type identification code
13. **SWITCH:** enable (green)/disable (gray) reading and use of the resource. This setting takes priority over all the other resource settings.

History

Once you have entered device viewing mode, select the TAB:  HISTORY.


The following window will appear:



NOTE: the TAB is only visible if the current user is authorized to view the data archive
The following fields appear at the top:

1. Select the resource/alarm **group** to view
2. Select data viewing in the form of a **Chart**
3. Select data viewing in the form of a **Table**
4. Select whether to show the data in the "History" or "Quick" (frequent sampling) column
5. **(Present if number 2 selected)** View the data chart
6. **(Present if number 3 selected)** View the data table
7. Enlarge to full-screen view.

Quick view across multiple equipments



Once its data is displayed (either as a Table or a Chart), you can:

- display the same group of resources data for another device selected from the Devices (1) drop down list
- display data for a different group of resources selected from the Groups (2) drop down list

Note: Groups and Devices selectors are available only when the History panel is opened from a device History panel.

Parameters

Once you have entered device viewing mode, select the TAB:  PARAMETERS.

The window containing the list of device parameters will appear.

Note: if the controller has not been recognized or is in No-Link, or the model is incorrect/does not correspond, the TAB is not enabled.

You can also access this screen by selecting:

 **FUNCTIONS > PARAMETERS**
and selecting the specific device.

NOTE: access to data is only permitted if the current user is authorized to view the device parameters.

Commands

Once you have entered device viewing mode, select the TAB: ▷ COMMANDS.

The window containing the list of device commands will appear.

Note: if the controller has not been recognized or is in No-Link, or the model is incorrect/does not correspond, the TAB is not enabled.

You can also access this screen by selecting:



FUNCTIONS > COMMANDS

and selecting the specific device.

NOTE: access to data is only permitted if the current user is authorized to view the device commands.

Alarms

Contents

This section includes the following topics:

Introduction	84
Viewing and filtering network alarms	85
Basic device alarm information tab	87
Alarm details	89

Introduction

Description

This section can be used to:

- view and filter devices in alarm mode
- view for how long a device has been in alarm mode and whether one or more relative alarms have been acknowledged
- access the screen showing a specific device in alarm mode by directly displaying the alarm resources.

Alarms

In order to verify the network devices, you need to set and enable the virtual “No-Link” alarm (loss of communication with the device) that the system inserts between the resources of all devices and algorithms.

NOTICE

INOPERABLE DEVICE


Set and activate the “No-Link” alarm for various devices to receive notifications relating to a lack of communication or anomalous operation linked to incorrect recognition of the device resources.

Failure to follow these instructions can result in equipment damage.

Viewing and filtering network alarms

Description

On entering the  ALARMS menu, the following window will appear:



The window contains:

- Select all devices shown. If a filter is enabled, only those meeting the filter requirements will be selected.
- Filter devices by controller model (for example: RTX 600/V) or by description (for example: Fish cabinet)
- Apply/remove the filter for the groups associated with the devices (for example: meat, fish, etc.).
Note 1: the groups can be set on the device configuration page.
Note 2: a device can belong to several groups
- Show/hide the following filters:
Communication status (device unknown, does not match, partially matches or No-Link)
- Protocol type (Modbus, Micronet)
- Fieldbus interface (address - for example 192.168.1.3)
- Show/hide confirmed alarms and update the device list according to alarms present and/or confirmed alarms
- Drop-down menu to change the display type. Options:
 -  (**Cards**): display the devices on cards showing the linked image
 -  (**Grid**): display the devices on cards without the linked image
- Drop-down "Configuration" menu for quick access to alarm configuration, with the following options:
 -  (**Categories**): set the alarm categories (see [Alarm categories](#))
 -  (**Actions**): set the actions to be taken in the event of an alarm (see [Actions](#))
 -  (**Intervals**): set the time intervals (see [Time intervals](#))

Note: the menu can only be seen by users authorized for "Alarm Configuration"
- View devices in alarm mode or quickly access alarm configuration, with confirmed network alarms based on the selection made in point (5).
- Tab with basic alarm information for a specific device. Click to access a detailed view of the device with the Alarms tab pre-selected.
- Alarm management panel shown if:
 - alarms for all devices are selected (1)
 - all alarms for one device have been selected using the check box in the top left-hand corner of the device tab
 - one or more alarms have been selected for a device using the check box to the left of each row

The following can be found in the panel:

 - **Note:** to enter a note to be linked to all selected alarms when they are confirmed.

- **Confirm:** to change the status of the “confirmed” alarms and save the note.


NOTE: confirming one or more alarms only changes the displayed information on the alarms page. Its history is tracked but it does not affect the actions.

Example: it does not change the behavior of an alarm relay. You will need to wait for the alarm condition to actually end for the relay output to be disabled.

- **Cancel:** cancels the operation. The alarm status is not changed and the note is not entered.

Basic device alarm information tab

Description



The tab contains:

- identifies status and selects device
 - ✓ = The device is connected
 - ⏸ = The device has not yet been recognized
 - ✗ = The device is in No Link mode
 - * = The device has not yet been included in the configuration
 - ⚠ = The device partially corresponds to the set model
Note: the parameters and commands functions are not enabled
 - ! = The device does not correspond to the set model
Note: model change is required
 - 🛠 = The device is in "Maintenance" mode
 - □ = Shown as the mouse passes over, used to select the device
- Name assigned to the device
- Controller address and fieldbus interface
- Cooling function status (if managed by the controller):
 - ❄ = Cooling active
 - ❄ = Cooling inactive
- Defrost function status (if managed by the controller):
 - 💧 = Defrost active
 - 💧 = Defrost inactive
- Evaporator fan status (if managed by the controller):
 - 🌀 = Fans active
 - 🌀 = Fans inactive
- Door status (if managed by the controller):
 - 🚪 = Door open
 - 🚪 = Door closed
- Alarm icon:
 - 🔔 = No alarm active
 - 🔔 = At least one alarm active
 - 🔔 = All alarms have been acknowledged
- The 3 dots on the right-hand side can be used to:
 - ✎ (**Edit**): change the device settings
 - 🛠 (**Maintenance**): put the selected devices into "Maintenance" mode
 - 📁 (**Import profile**): apply a specific device profile to the selected devices
 - 📁 (**Export profile**): export a specific device profile
 - 📁 (**Change model**): change the "Model" and "Device profile"
 - 🗑 (**Remove**): remove the selected devices from the configuration

10. Shows whether the alarm is active or acknowledged:

-  = Alarm active
-  = Alarm acknowledged

Note: if the alarm is active, it can be used to select a specific alarm using a check box that appears when the mouse moves over it, or after clicking.

Note: selecting the specific alarm for acknowledgment is subject to user authorization "Alarms acknowledge" (see [Group management](#)).

- 11. Alarm description
- 12. Indicates for how long the alarm has been active
- 13. View alarm details (see [Alarm details](#))
- 14. Image associated with the device.

Alarm details

Description

Save Print

1 2

Alarm details

3

Device: Banco Pesce
Code: ALM40268-6
Alarm: Probe AI error 6

Alarm trace

4

Date and time	Internal state	External state
29/05/2023 12:37:32	Active	Acquisition running
29/05/2023 12:39:49	Sleeping	Acquisition running

Active

5

Date and time	Action	Settings	Routing state	Retries
29/05/2023 12:37:32	Universal Modo_Eco	Banco Pesce: Auxiliary output On and Auxiliary output On	Done	2
29/05/2023 12:37:32	Universal Mail	email address: change@email.Address	Failed	99
29/05/2023 12:37:32	Universal Phone Call	Phone: +3900000000	Failed	100
29/05/2023 12:37:32	Universal SMS	SMS: +3900000000	Failed	101

Inactive

6

Date and time	Action	Settings	Routing state	Retries
29/05/2023 12:39:49	Universal Modo_Eco	Banco Pesce: Auxiliary output On and Auxiliary output On	Not performed: there are still active alarms managed by this action	0
29/05/2023 12:39:50	Universal Phone Call	Phone: +3900000000	Rerun	132
29/05/2023 12:39:50	Universal SMS	SMS: +3900000000	Rerun	132
29/05/2023 12:40:03	Universal Mail	email address: change@email.Address	Rerun	141

Alarm note

7

The tab contains:

1. **Save:** save changes to notes entered in point 7
2. **Print:** print alarm details
3. **Alarm details:** basic information relating to the alarm
 - **Device:** name of the device in alarm
 - **Code:** code for the active alarm
 - **Alarm:** description of the active alarm
4. **Alarm trace:** alarm history
 - **Date and time:** date and time at which the alarm occurred
 - **Internal state** = alarm condition (active/inactive)
 - **External state** = system status (acquisitions running, etc.)
5. **Active:** identifies the operations carried out on alarm activation
 - **Date and time:** date and time at which the alarm occurred
 - **Action** = action performed by the TelevisGo v10 (if programmed)
 - **Settings** = parameters relating to the action
 - **Routing state** = result of the action (Done, Rerun, Failed, etc.)
 - **Retries** = number of attempts carried out
6. **Inactive:** identifies the operations carried out on alarm deactivation
 - **Date and time:** date and time at which the alarm occurred
 - **Action** = action performed by the TelevisGo v10 (if programmed)
 - **Settings** = parameters relating to the action
 - **Routing state** = result of the action (Done, Rerun, Failed, etc.)
 - **Retries** = number of attempts carried out
7. Field used to edit or enter the note to be associated with the alarm.

History

Contents

This section includes the following topics:

Introduction	91
Alarm log	92
Data tables and charts	94


Introduction

Description

This section can be used to:

- view alarm history
- view the data archive in table form
- view the data archive in chart form
- view the energy reports in table form
- view the energy reports in chart form

Menu structure



Alarm log


In the following menu:

 **History > Alarm history**

The screen selects the type of interval to use:

- **Quick:** pre-set intervals (1, 2, 3, 6, 12 hours, 1 or 2 days, 1 week)
- **Custom:** custom interval with start and end date/time

Quick selection




The screenshot shows the 'Time intervals' section with the following elements:

- Quick (1)
- Dropdown menu showing 'Last hour' (2)
- Custom
- Include alarms with delay (3)

Make a selection as follows:

1. If not already selected, select the option '**Quick**' (set by default)
2. From the drop-down menu, select the desired time interval:
 - Last hour
 - Last 2 hours
 - Last 3 hours
 - Last 6 hours
 - Last 12 hours
 - Last day
 - Last 2 days
 - Last week
3. Choose whether or not to select alarms with a delay in signaling (they may not be active yet).

Custom selection



The screenshot shows the 'Time intervals' section with the following elements:


- Quick
- Custom (1)
- From** text box containing '02-04-2023 @ 14:49' (2)
- To** text box containing '03-04-2023 @ 14:49' (3)
- Include alarms with delay (4)

Make a selection as follows:

1. If not already selected, select the option '**Custom**'
2. In the box 'From', enter the start date/time of the desired time interval
3. In the box 'To', enter the end date/time of the desired time interval
4. Choose whether or not to select the box to include alarms with a delay in signaling (they may not be active yet).

Viewing alarm history

Once you have selected the desired time interval, click  to access the screen with the alarm history:



The screenshot shows the alarm history interface. On the left, there are three sections: 'Time interval' (1) with a dropdown menu showing 'Type: Last hour', 'From: 03/04/2023 15:44:18', and 'to: 03/04/2023 16:44:18'; 'Devices' (2) with a text input field; and 'Resources' (3) with a text input field. The main area (4) is a table with the following data:

	Device	Code	Alarm	Begin	Delay	End	Duration
(•)	999:14:14 TelevisGo	ALM99998	Modem signal strength low	18/06/10 16.27.41			
(•)	0.02:01 ID 974LX	ALM00300	NOLINK	09/07/10 9.46.43			
(•)	0.02:00 ID 974LX	ALM00300	NOLINK	09/07/10 9.46.49			
(•)	999:14:14 TelevisGo	ALM99999	Acquisitions stopped	20/07/10 16.11.18		21/07/10 16.11.20	1 day

At the top right, there is an 'Export' button and a 'Cancel filters' button (5). A back arrow is visible in the top left corner.

The screen components are as follows:


1. **Time interval:** indicates the time interval set on the previous page
2. **Devices:** used to filter the alarms by device name
3. **Resources:** used to filter the alarms by resource type
4. **Details:** shows the details relating to the alarms:
 - **Alarm note:** present if colored yellow (■)
 - **Alarm icon:**
 - **RED ((•))** = identifies an active alarm at the end of the time interval.
 - **GREEN ((•))** = identifies an alarm that ended before the end of the time interval.
 - **GREY ((•))** = identifies an alarm that is not yet active because the alarm delay has not yet expired.
 - **Device:** device name
 - **Code:** alarm code
 - **Alarm:** alarm description
 - **Begin:** alarm start date/time
 - **Delay:** indicates for how long the alarm has been delayed (and therefore not signaled)
 - **End:** date/time alarm ended
 - **Duration:** indicates the total duration of the alarm.
5. **Control bar:** see [Buttons and Selectors](#).

The "Alarm note" can be also entered/edited within that alarm (click on the alarm icon).

Data tables and charts

Page structure

Web application pages for viewing historical data and energy information:



The different parts of the page are:

1. **Selection toolbar:** used to activate or deactivate viewing of the following information:

-  : performs a search for data based on the settings in the selection windows described in point 2
-  : shows/hides the “Data archive” window
-  : shows/hides the “Profile” window
-  : shows/hides the “Time intervals” window
-  : shows/hides the “Resources” window
-  : shows/hides the “Legend” window (only available with charts)
-  : shows/hides the “Print/Export” window.

2. **Selection windows:** used to customize the search by setting the type of data, profile, time intervals, resources, etc. (see '[System general settings](#)').

3. **Data display:** data is displayed in the form of a table or a chart, depending on the settings selected previously.

This takes place when the  icon is clicked.

4. **Selection:** 4 types of information appear on this screen:

- Historical table
- Historical chart
- Energy report
- Energy chart.

Selection windows

The windows shown/hidden by pressing the icons in the selection bar are used as follows:

Icon	Window	Description of actions
	/	Filters settings according to the selection windows.
	<div data-bbox="424 461 868 824"> <p> Data archive </p> <p><input checked="" type="radio"/> HISTORY No undersampling (all data).</p> <p><input type="radio"/> HISTORY Undersampling. Number of records to show: <input type="text" value="1"/></p> <p><input type="radio"/> QUICK Temporary database.</p> <p><input type="radio"/> ENERGY Energy data over time. Time base multiplier: <input type="text" value="1"/></p> </div>	<p>Used to select the data to show:</p> <ul style="list-style-type: none"> HISTORY (no undersampling): Shows all logged data HISTORY (undersampling): Used to select the number of records to show QUICK (frequent sampling): Shows data from the temporary archive (only recent data) ENERGY (energy data over time): Used to select the time multiplication factor for calculation of the relative value for the energy resources (see Energy resource selection).
	<div data-bbox="424 842 868 1182"> <p> Profile </p> <p>HACCP </p> <p> Load profile and retrieve data</p> <p> Delete selected profile...</p> <p> Save current selection as...</p> </div>	<p>Used to:</p> <ul style="list-style-type: none"> Select a saved profile Create a new profile Save a profile that has just been created or edited Delete a profile saved previously <p>NOTE: after selecting a profile, click the button to apply it and view the data.</p>
	<div data-bbox="424 1200 868 1424"> <p> Time intervals </p> <p>Last hour </p> <p> 1 hour </p> </div>	<p>Used to select the display interval from a list of pre-set values (1 hour, 2 hours, 3 hours, 6 hours, 12 hours, 1 day, 2 days, 1 week) or by defining a "custom" value (by specifying the interval start and end date/time in "dd-MM-yyyy@ hh:mm" format). The software will then display the values present in the interval corresponding to your selection, beginning with the current time at which the archive is being searched (for example, if you set 2 hours, the values recorded in the last 2 hours will be shown).</p>
	<div data-bbox="424 1447 868 1671"> <p> Resources </p> <p>1 Network configurations</p> <p> Select resources...</p> </div>	<p>If you decide not to select a profile that has been created already, you can use this box to set which instruments and network resources to view.</p>
	<div data-bbox="424 1682 868 1989"> <p> Resources </p> <p>Equipment... </p> <p>Group... </p> <p>x Network configurations</p> <p> Select resources...</p> </div>	<p>Note: available only when accessing the data history page from from a specific device History panel</p> <p>Select an equipment from the drop down list to display the same group of resources for another device.</p> <p>Select a group from the drop down list to switch the view to the different group of resources for the currently displayed device.</p>

	<div data-bbox="424 219 868 555"> <p>Legend ✕</p> <ul style="list-style-type: none"> ● 0.00:01 Corrente-Fase2 ● 0.00:01 Energia-Reattiva ● 0.06:04 HT line suction pressure probe ● 0.06:04 LT line suction pressure probe ▼ 0.01:06 stand-by mode ▼ 0.01:06 No link </div>	<p>Pairs each line (using color and shape) to a parameter selected during selection of the system settings. NOTE: only visible if a chart is shown.</p>
	<div data-bbox="424 571 868 952"> <p>Print/Export ✕</p> <ul style="list-style-type: none"> <input type="checkbox"/> Show statistics <input type="checkbox"/> Show legend <input type="checkbox"/> Show header <input checked="" type="radio"/> Landscape print <input type="radio"/> Portrait print  Print  Export </div>	<p>Used to print or export the data shown.</p> <p>Other options only visible if a chart is shown: Selects whether the following should be shown during the printing or exporting process:</p> <ul style="list-style-type: none"> • statistics • legend • header. <p>It also selects whether the output should be oriented horizontally or vertically.</p>

HACCP profiles

During the profile definition phase there is the option of creating one or more profiles, categorized as **HACCP** profiles, that influence the way in which data is displayed and formatted during the printing phase.

In order to create an **HACCP** profile one of the following conditions must be satisfied:

- A. For each device you wish to enter in the profile, select only one analogue resource (typically the control probe) and only one machine status associated with the selected analogue probe (typically defrost status)
- B. For each device to be entered in the profile, select only analogue resources.

To the right of the temperature value an * (asterisk) is added if the machine status (typically defrost) is active.

In the case of Flash printing (periodical printing of real-time data) or real-time display, the system behaves as follows:

- In the event of an analogue resource error or "no-link" device, the system will search the historical data for the first previous valid temperature value
- The duration of the search window is defined in the configuration (default = 30 minutes).

Only profiles that satisfy the conditions described in points **A** and **B** can be marked as **HACCP** profiles. The user decides whether to mark a profile as **HACCP** by selecting the corresponding box, but the software offers this option only if the conditions are observed.

TelevisGo v10 makes a System-HACCP profile available, which corresponds to the HACCP selections in the configured devices, together with any **HACCP** profiles created by the user, and can be viewed on the data archive screen.

Historical table

To view the data saved on the TelevisGo v10, go to the following menu:

 **History > Historical Table**

The screen that opens is described in 'Page structure' with the relevant options available for selection.

Once you have made the selections, click  to load a selected profile or the  icon; the following screen will appear:

		Fruit island 1															
Time of Z1/11/2023	Analog input 1 (°C)	Modified parameters	Device state	Keyboard enabling	Compressor	Defrosting status	Fans	Auxiliary	Light	Alarm	Buzzer	Reduced set-point	Forced ventilation	Out1	Out2	Out3	
	14.35.00	23.5	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.40.00	23.6	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.45.00	23.7	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.50.00	23.8	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.55.00	23.7	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.55.30	23.6	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.56.00	23.5	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	14.59.15	23.4	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.00.00	23.4	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.05.00	23.6	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.10.00	23.8	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.15.00	23.8	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.20.00	24	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.25.00	24	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.20.00	24.2	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.25.00	24.2	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.30.00	24.1	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.35.00	24.2	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.40.00	24.3	1	1	0	1	0	1	0	1	0	0	1	1	1	0	1
	15.45.00		1	1	0	1	0	1	0	1	0	0	1	1	1	0	1

3

The different parts of the screen are:

-  / : used to expand/collapse the variations of asynchronous resources (digital inputs and outputs, statuses, alarms).
- Date/Time:** identifies the date/time the data was saved. There is then a series of columns with the previously selected resources and relative values read for each device at the indicated time.
- New records:** the initial screen will show the first 50 results by default. To view other values, select one of the following options:
 - Next 10:** shows the next 10 values
 - Next 50:** shows the next 50 values
 - Next 100:** shows the next 100 values
 - Next 200:** shows the next 200 values
 - All remaining:** show all values
(NOTE: in some cases this may take a few minutes).


Historical data chart

To view the historical data chart, go through the following menus:

 **History > Historical chart**

The screen that opens is described in "Page structure" with the relevant options available for selection.

Once you have made the selections, click  to load a selected profile or the  icon; the following screen will appear:



The different parts of the page are:

- Legend:** shows the color chosen when creating the device profile for each resource (see 'Device resources') and a symbol to identify the resource type (● = analogue resource and ▼ = digital resource).
- Resource chart:** the curve on the screen shows how the values read (y-axis) varied over time (x-axis). Each selected resource has its own line in the assigned color with the value trend over time (for example: ● Controller 1 - ColdRoom Analogue input 1).
- Value axes:** shows the y-axis for the different curves displayed. If the y-axes of several resources are compatible, it will show a single axis, otherwise it will show several y-axes on the right.
- Statistics:** shows the statistics for the analogue and digital resources displayed.

Click on the symbol of a resource to hide/show it.

If the hidden resource is an 'analogue resource', the corresponding line on the chart will be also hidden and the axes of the read values (one for each unit of measure up to a maximum of 3) will be sized according to the remaining values. If a digital resource (digital inputs/outputs, machine statuses and alarms) is hidden, the chart will disappear and its place will be taken by the next resource.

Click on the first row of the resource name and a window opens which can be used as follows:

- Change color:** used to change the color used in the chart
- Mark:** (digital resources only) used to view a vertical band in line with value 1 for the digital resource.

ANALOGUE RESOURCE	DIGITAL RESOURCE
<div style="border: 1px solid black; padding: 5px; width: fit-content; margin: auto;"> <p>Controller 1 ColdRoom Analogue input 1</p> <p style="color: orange;">Change color</p> </div>	<div style="border: 1px solid black; padding: 5px; width: fit-content; margin: auto;"> <p>Controller 1 ColdRoom Digital input 1</p> <p style="color: orange;">Change color</p> <p style="color: orange;">Mark</p> </div>

Read value axis (y ordinates)

Click on the value axis to open a new window with the following items:

- **Set as default:** visible only with 2 or 3 axes and used to view the values in the unit of measure of the selected axis on the chart
- **Change color:** used to customize the color of the axis and the corresponding grid
- **Change minimum/maximum:** used to customize the min and max values shown on the value axis
- **Set bands:** according to set values A and B (set to the closest value in the grid).

If more than 15 resources have been selected, the message at the top will appear: "You selected more than 15 resources. Chart performance may be critically low."

The chart shown is interactive: by moving the mouse over the rows of the various resources, the mouse cursor will take the shape ● (in the same color as the resource) and:

- **Within the chart:** the values and the moment at which they were recorded will be displayed
- **In the legend:** the values of all resources in their unit of measure will be displayed

Zoom: selection boxes used to select a specific time band to view are in the bottom right-hand corner:

- **1 hour:** the charts for the last hour of the selected time interval are shown (see previous page)
- **3 hours:** the charts for the last 3 hours of the selected interval are shown (see previous page)
- **Max:** the charts for the whole selected interval are shown (see previous page).

The interval can be edited by dragging the cursors  downwards.

NOTE: check that the orientation set on the printer used is the same as the type of printing selected.

Energy report

To view the history for energy resources, go through the following menus:

 **History > Energy report**

The screen that opens is described in "[Page structure](#)" with the relevant options available for selection.

Once selection is complete, click  to load a selected profile or the  icon to open the same screens as described for the data archive (see "[Historical table](#)").

The difference between one row and the next indicates the change in the resource monitored during the time period. Data is grouped by registration interval set for the energy resource (see [Selecting energy resources](#)).

A value greater than or equal to 1 can be entered in the text box as a multiple of the calculation time for the value relating to the energy resources.

The page will automatically calculate the value of the resulting period. To confirm the selected aggregation period click on **Set value**.

Energy chart

To view the energy chart, go through the following menus:

 **History > Energy chart**

The screen that opens is described in "[Page structure](#)" with the relevant options available for selection.

Once selection is complete, click  to load a selected profile or the  icon to open the same screens as described for the historical chart (see "[Historical chart](#)").

Functions

Contents

This section includes the following topics:

Introduction	102
Start/Stop acquisition	103
Scheduled actions start/stop	104
Commands	105
Parameters	107
List of controller parameters	108
List of algorithm parameters	109
Writing on more than one device	115
RVD (Remote Virtual Device)	116
Layout	117


Introduction

Description

This section can be used to manage:

- Start/Stop acquisition
- Commands
- device parameters
- the RVD function (if available for the device)
- layouts

Menu structure




Start/Stop acquisition

In the following menu:


 **Functions > Start/stop**

On entering the menu, one of the windows shown below will open:

- **Acquisitions not running:** the window below will appear. Click on **Start** to manually start them.
NOTE: If the acquisition are not manually restarted, the acquisitions will be automatically restarted after a predefined time.
NOTE: Logging will be stopped automatically in the event of repeated service restarts in a short space of time.



- **Acquisitions running:** the window below will be displayed. It is not possible to stop acquisitions manually.



You can check the acquisition status in the Status bar (see "Status icons").


Scheduled actions start/stop

In the following menu:


 **Functions > Start/stop**

Depending on whether the actions have commenced, when you enter this menu one of the windows shown below will open:

- **Scheduled actions not running:** the window below will appear. Click **Start** to start the scheduled actions running.



- **Scheduled actions running:** the window below will appear. Click **Stop** to stop the scheduled actions.




Commands

In the following menu:




The following screen will appear:



The different parts of the page are:

- Filter devices:** used to filter the devices by description
- Commands:** used to select the command/action to send to one or more devices. The list represents the grouping of all commands available on all devices in the network, plus any actions for writing "Manual Execution" parameters defined within the "Scheduled activities"
- Show table header:** show/hide table headers
- Device list:** used to select the individual devices by ticking the check box to the left of the address
- Expand/Collapse:** expands/collapses the list of devices in an interface
- Control bar:** see [Buttons and Selectors](#).

Once execution is complete, the following screen will appear:



The following information will appear:

- A sentence warning the user of any errors. On clicking the highlighted text, a pop-up opens with the full list of errors detected.
- The **Outcome** column where, for the selected devices, the following may appear:
 - Done:** the action was carried out successfully
 - Error:** if an error has occurred.
- If there are errors: click the label "**Error**" for a specific device to open a pop-up with a list of errors detected.

To view the full list of errors, click on the sentence (7) or on the sentence in red in the new yellow window (9); the following page will appear:

12 **Print**

Address: 0.02:00 - Description: RTX600/V - Name: 10

Label	Description	UM	Min	Max	Set	Device	Value	Outcome
rE	Type of setting	num	0	4	0	0	6	value off limit
rP1	Thermostat 1 temperature regulation probe		0	7	6		Pb6	error
dF3	---	---	---	---	---	---	4.0	not defined
dF4	---	---	---	---	---	---	4.0	not defined
dF5	---	---	---	---	---	---	4.0	not defined
dF6	---	---	---	---	---	---	4.0	not defined
dF7	---	---	---	---	---	---	4.0	not defined

Address: 0.02:01 - Description: RTX600/V - Name:

Label	Description	UM	Min	Max	Set	Device	Value	Outcome
rE	Type of setting	num	0	4	0	0	6	value off limit
rP1	Thermostat 1 temperature regulation probe		0	7	6		Pb6	error
dF3	---	---	---	---	---	---	4.0	not defined
dF4	---	---	---	---	---	---	4.0	not defined
dF5	---	---	---	---	---	---	4.0	not defined
dF6	---	---	---	---	---	---	4.0	not defined
dF7	---	---	---	---	---	---	4.0	not defined

The screen displays:

10. The data for the device on which the errors have been detected.
 - address
 - description
 - name assigned to the device.
11. The list of errors detected. It contains the following information relating to each error:
 - parameter label
 - description
 - unit of measure
 - default value
 - value set on the device
 - value the action attempted to write
 - type of error detected
12. The **Print** button used to print the full error report.

NOTE: incorrect selection of one or more commands (for example, “Device OFF”) can influence the proper running of the equipment. In the example, sending the command “Device OFF” physically switches off the device and prevents it from acquiring any data or performing any regulation. Always provide control systems outside of the TelevisGo v10 for functions that are critical to the application.

WARNING


LOSS OF CONTROL
 The installation designer must consider the potential failure modes of the control circuit and, for some critical control functions, provide a means for reaching a safe condition during and after a circuit failure. Examples of critical control functions are the emergency stop and end of travel stop, power supply cut-off and restarting.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

Parameters

In the following menu:

 **Functions > Parameters**

The following screen will appear:



The different parts of the page are:

1. **Filter devices:** used to filter by device description.
2. **Device list:** shows the list of network devices grouped by interface. The controls present are those for each individual device
3. **Parameters:** click the device row to access the selected device parameters
4. **Expand/Collapse:** expands/collapses the list of devices in an interface.
5. **Control bar:** see [Buttons and Selectors](#).

Only one device can be selected at a time.

Setting the value of some of the parameters incorrectly can affect the proper operation of the equipment, even if the values fall within the range of values that can be set (for example: setpoints, temperatures, etc.).

NOTICE

INOPERABLE DEVICE

Enable the TelevisGo v10 alarm thresholds for resources that are critical to the application.

Failure to follow these instructions can result in equipment damage.

List of controller parameters

The following screen will appear:




The different parts of the page are:

- Controller:** shows the information relating to the selected device: selected device Address, Description and Name
- Commands:** used to select the command to be sent to the device (only commands available on the selected controller are listed).
Click **"Execute"** to execute the selected command.
- Parameter map:** used to load/save a parameter map:
 - Save parameter map:** saves the parameter map for the controller in ".dat" format
 - Select file:** select the parameter map to load onto the controller in ".dat" format
 - Load parameter map:** load the parameter map onto the controller.
- Parameter filters:** apply filters to the parameter map for the controller. The filters are:
 - Group:** filter parameters by the group to which they belong
 - Label or MU:** filter parameters by name (Label) or unit of measure (MU)
 - Description:** filter parameters by their description.
NOTE: The "X" to the right of the heading resets applied filters.
- Parameter filters 2:** there are 2 pairs of check boxes which act independently from the previous filters:
 - Checked rows/Unchecked rows (*):** filters the checked or unchecked rows
 - Valid data/Invalid or missing values (*):** filters the rows with or without valid data.
(* If both check boxes in a pair are ticked, all rows are shown.
If neither of the check boxes in a pair are ticked, the table will be empty.
- Legend:** identifies the text color depending on whether the parameter is read/write (black) or read-only (blue).
- Control bar:** the following buttons are shown at the top: (see **Buttons and Selectors**):
 - Write on...:** opens a selection template for the devices onto which the map shown should be copied
 - Print:** print the map shown
- Parameter select:** tick the box to select/deselect one or more parameters.
- Label:** shows the label for the controller parameters (filtered or not).
- Description:** shows the description for the controller parameters.
- Value:** shows value read for the controller parameters (filtered or not) and can be used to change them instantly.
To edit a parameter, simply change its value and click Enter or exit the field
 - If writing is successful the cell around the edited field turns **green**
 - If writing is not successful (or the value is outside the range), the entire row turns **red**. The incorrect value continues to be shown. You therefore need to change it to a valid value or delete the field and move on to another parameter so that the system reads the current value from the instrument again
- : if shown, this means that the TelevisGo v10 is reading the values on the controller.
- UM:** shows the unit of measure (UM) for the parameters (if previously entered on the map and saved).
- Min:** shows the minimum value the parameter can assume and any reference to other parameters.
- Max:** shows the maximum value the parameter can assume and any reference to other parameters.

List of algorithm parameters

The following screen will appear:



The different parts of the page are:

1. **Controller:** shows the information relating to the selected device: selected device Address, Description and Name
2. **Commands:** to select the command to be sent to the device (the list groups together all commands available for all network devices).
Click **"Execute"** to execute the selected command.
3. **Parameter map:** used to load/save a parameter map:
 - **Save parameter map:** saves the parameter map for the controller in **".dat"** format
 - **Select file:** select the parameter map to load onto the controller
 - **Load parameter map:** load the parameter map onto the controller.
4. **Parameter filters:** apply filters to the parameter map for the controller. The filters are:
 - **Group:** filter parameters by the group to which they belong
 - **Label or MU:** filter parameters by name (Label) or unit of measure (MU)
 - **Description:** filter parameters by their description.

NOTE: The **"X"** to the right of the heading resets applied filters.
5. **Parameter filters 2:** there are 2 pairs of check boxes which act independently from the previous filters:
 - **Checked rows/Unchecked rows (*):** filters the checked or unchecked rows
 - **Valid data/Invalid or missing values (*):** filters the rows with or without valid data.

(*) If both check boxes in a pair are ticked, all rows are shown. If none of the check boxes in a pair are ticked, the table will be empty.
6. **Legend:** text color depends on whether the parameter is read/write (black) or read-only (blue).
7. **Print:** print the map shown (see [Buttons and Selectors](#)):
8. **Parameter select:** tick the box to select/deselect one or more parameters.
9. **Label:** shows the label for the controller parameters (filtered or not).
10. **Description:** shows the description for the controller parameters.
11. **Value:** shows a hypertext link or value read for the controller parameters (filtered or not) and can be used to change them instantly. Options are:
 - **view:** normally present for filters. Click to view the filter loaded by the designer; cannot be changed
 - **edit:** normally present for filters. Click to view the filter loaded by the designer; can be changed
 - **parameter value:** value read on the controller. A value change, if valid according to the specified limits and the value type, will automatically be sent to the controller for updating
 - **Value:** shows value read for the controller parameters (filtered or not) and can be used to change them instantly.

To edit a parameter, simply change its value and click Enter or exit the field


- If writing is successful the cell around the edited field turns **green**
- or, if writing is not successful (or the value is outside the range), the entire row turns **red**. The incorrect value continues to be shown. You therefore need to change it to a valid value or delete the field and move on to another parameter so that the system reads the current value from the instrument again

12.   : if shown, this means that the **TelevisGo v10 DP** is reading the values on the controller.

13. **UM:** shows the unit of measure (UM) for the parameters (if previously entered on the map and saved); in the case of filters, it identifies the type of resource (devices or resources).
14. **Min:** shows the following
 - **Parameters:** minimum value the parameter can assume;
 - **Master filters:** minimum number of devices;
 - **Subsidiary filters:** minimum number of resources allowing an output to be restored.
15. **Max:** shows the following
 - **Parameters:** maximum value the parameter can assume;
 - **Master filters:** maximum number of devices that can be selected with the filter;
 - **Subsidiary filters:** the maximum number of resources that can be selected with the filter.

“View” value

Click the “view” hypertext link to open a screen like the one below, showing details of the filter:




The various parts of the screen are:

1. Type of resource used
2. Resource ID
3. Resource name (optional)
4. Output

NOTE: the filter cannot be changed.

“Edit” value

Click the hypertext link to “edit” (10) a master filter and open the screen:



The master filter and subsidiary filter act independently of each other.

The types of output resources are a subset of the types of input resources; only network parameters and commands can be set as output resources.

For the subsidiary filters, the * symbol in the **MAX** field indicates no upper limit

If the minimum set number is greater than the maximum number, the set of elements is empty.

The selection and rule hierarchy is shown on the left. The buttons have the following meaning:

Button	Description
	Move the selector up a position
	Move the selector down a position
	Add a sub-rule (selector > interface; interface > device; device> resource)
	Modify selector or rule
	Delete selector or rule and all sub-rules

A filter consists of at least one selector. Each selector identifies a specific subset of resources and can be additive or subtractive.

An additive selector adds the resources it has filtered to the final set, whereas a subtractive selector removes the resources it has filtered.

NOTE: selector order is significant.

A subtractive filter only makes sense when used to filter the result of the additive filter before it.

To modify a selector, click the relative  icon.

For more information on the boxes appearing on the right of the screen (see "Scanning").

Once all changes have been made to selector properties, click  **Save**.

Click the hypertext link to **set (10)** a subsidiary input or output filter and open the screen:

Subsidiary input filter

Edit Subsidiary Input Filter - Selector suction setpoint

1 Type Analog
 Digital
 State
 Alarm
 Parameter

2 ID

3 Name

 Save
  Cancel
  Copy from default

⚠ WARNING

UNINTENDED EQUIPMENT OPERATION
 Frequent writing of EEPROM parameters can damage the system memory.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

Subsidiary output filter

Edit Subsidiary Output Filter - Selector offset suction setpoint

1 Type Parameter
 Command

2 ID

3 Name

4 Label

ⓘ Warning: The electronic devices could be damaged by too frequent EEPROM parameters writings.

 Save
  Cancel
  Copy from default

⚠ WARNING

UNINTENDED EQUIPMENT OPERATION
 Frequent writing of EEPROM parameters can damage the system memory.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

The different parts of the page are:

1. **Type:**

for a subsidiary input filter, select the type of element to apply the filter to, either:

- Analog resource
- Digital resource
- State resource
- Alarm
- Parameter

For a subsidiary output filter, select the type of element to apply the filter to, either:

- Parameter
- Command


2. **ID:** used to filter the resources by their identification number. It only accepts specific combinations of characters, numbers and wildcard characters (? and *). It consists of 3 upper case letters and 5 numbers followed by a hyphen or other text. For example: INP40001-1, ALM00300
3. **Name:** used to filter resources by their name translated into the language selected in the previous step. Allows the use of wildcard characters (? and *)
4. **Label:** only visible if the "Parameter" type is selected - (1). Used to select the input or output resource by entering its code (selection is case-sensitive).

Once all changes have been made to selector properties, click  **Save**.

Writing on more than one device

Using the "Device parameters list" screen as reference, click  **Write on ...** to access the device selection page where you can write the value of the parameters included in the previous page.


A window similar to this one will open:



The various screen components are:

1. **Filter devices:** used to filter the devices by description
2. **Fully compatible:** used to show only the devices that are fully compatible with the first ones where the new parameter values have been entered
3. **Device list:** shows the list of selectable devices to which apply the parameter writing should be applied. TelevisGo v10 and the reference device cannot be selected
4. **Control bar:** see [Buttons and Selectors](#).

If you click  **View the last operation report**, a screen like this will appear:




where the last writing operation performed is shown, along with information regarding on which devices and on which parameters. Click the  **Print** button to print the full report.

RVD (Remote Virtual Device)

In the following menu:

 **Functions > RVD**

The following screen will appear:



The different parts of the page are:

1. **Filter devices:** used to filter by device description.
2. **Device list:** shows the list of network devices grouped by interface. Only the devices where the function exists and is activated will be displayed.
3. **RVD access:** click a device row to access its RVD.
4. **Expand/Collapse:** expands/collapses the list of devices in an interface.
5. **Control bar:** see [Buttons and Selectors](#).

A picture of the selected device will be shown:



The Control bar is at the top (see ["Buttons and Selectors"](#)).

The chart representation is similar to that on the actual device.

The various operations running on the device screen (click buttons, view active LEDs, etc.) are equivalent to working directly on the device.


NOTE: The RVD function is only available for some devices.

Layout

In the following menu:

 **Functions > Layout**

The following screen will appear:



Press  **Rebuild all layouts**, for:

- **Layout Designer on external computer:** only upgrades the layout list uploaded to the system update page:

 **Computer > Update > System > Layout pages**

Reload any new or edited layouts from the system update page.

- **Layout Designer pre-loaded in TelevisGo v10 DP:** will update all layouts present (TelevisGo v10 DP imports any changes made to a layout) and any new layouts will be loaded. In this case, you do not need to load them using the system update page.

Click one of the names in the list to view the layout associated with it.


If the layout is parametric (valid for a number of devices that are the same and can be selected individually), on the right there will be a drop-down menu from which the user can select the device to be displayed.

In the drop-down menu, the devices will be subdivided as shown below:

- **Fully compatible:** devices shown at the start of the list, which have all resources present in the layout
- **Partially compatible:** devices shown at the end of the list, which have some resources present in the layout
- **Incompatible:** devices which are not shown, and have none of the resources present in the layout.

The same drop-down menu will also be available in the layout screen, and allows the user to switch devices simply by selecting the one required.

Press  to go back to the previous page and view the list of available layouts.



At the top of the general and parametric layout pages there is a **Control bar** (see "Buttons and Selectors"). Parameters are automatically upgraded only when you open a Layout screen. To manually update the values displayed, press  **Read parameters**.

When the mouse cursor is placed on an item, a window appears containing its characteristics.

To edit a parameter, select the value using the mouse, enter the value and press "Enter".

If a valid value is entered, a green message "**Done**" will appear above the text box; otherwise, a red "**Error**" message will appear.

NOTE: For further details regarding the creation/maintenance of a Layout, please refer to the manual: **9MA00237 MAN Layout Designer EN**

Settings

Contents

This section includes the following topics:

Introduction	120
Adding/editing a fieldbus interface	121
User management	127
Alarm configuration	130
Scheduler	138
Registration interval settings	150
System general settings	152


Introduction

Description

This section can be used to manage:

- interfaces
- users and groups of users
- alarms (categories, actions, time intervals)
- scheduled actions
- archive configuration
- General settings (Life Test, Alarms, Media, etc.)

Menu structure



Adding/editing a fieldbus interface

Go through the following menu sequence:

 **Settings > Interfaces > Physical network**

Adding an interface

To add an interface:

1. click  **Add**
2. in the "**Details**" box, select the type of network interface used (**SerialAdapter**, etc.)
3. enter the required information (see below)
4. click  **Save**

Modbus TCP / EthernetAdapter

 **Details**

SerialAdapter
 LanAdapter
 EthernetAdapter / Modbus TCP

Interface type
 Address . . .
 Port

Fieldbus ▼

The information on the screen is as follows:

- **Address:** set the IP address for the Modbus TCP interface
- **Port:** communication port for the device or Modbus/TCP gateway
- **Fieldbus:** types of selectable networks.

SerialAdapter

 **Details**

SerialAdapter

Interface type

Port

Protocol

LanAdapter

EthernetAdapter / Modbus TCP

Fieldbus

The information on the screen is as follows:

- **Port:** physical communication port used by TelevisGo v10
- **Protocol:** type of communication protocol.
 1. **Micronet & Modbus**
 2. **Micronet & Modbus with Smart Adapter** (Micronet with Modbus sub-network after a SmartAdapter)
 3. **Modbus** (Micronet & Modbus on the same network)
 4. **Micronet**
- **Fieldbus:** types of selectable networks.

LanAdapter

Details

SerialAdapter
 LanAdapter

Interface type
 Address: . . .
 Port:
 Protocol:

EthernetAdapter / Modbus TCP
Fieldbus:

Test utility

 This test works with LanAdapter only

The information on the screen is as follows:

- **Address:** set the IP address of the **LanAdapter**
- **Port:** physical communication port used by **TelevisGo v10**
- **Protocol:** type of communication protocol.
 1. **Micronet & Modbus**
 2. **Micronet & Modbus with Smart Adapter** (Micronet with Modbus sub-network after a SmartAdapter)
 3. **Modbus** (Micronet & Modbus on the same network)
 4. **Micronet**
- **Fieldbus:** types of selectable networks.

Note: we recommend you always use the “Test connection” button to check communication between **TelevisGo v10** and the **LanAdapter** interface device.

Fieldbus settings

The fieldbus type settings selects the values and times indicated in the table below:

Fieldbus	Time-out response (ms)	Inter-polling time (ms)	Retries	Ignored communication faults before No-Link	Usual Interface Type
BusAdapter / Wired RS485	300	0	2	2	SerialAdapter
RadioAdapter	800	0	5	2	SerialAdapter
SmartAdapter	600	0	2	2	SerialAdapter
LanAdapter	2000	500	2	2	LanAdapter
LanAdapter Wi-fi	2000	500	2	2	LanAdapter
LanAdapter (RadioAdapter)	3000	800	2	2	LanAdapter
EthernetAdapter / RS485	1500	100	2	2	EthernetAdapter / Modbus TCP
Modbus TCP	1500	100	2	2	EthernetAdapter / Modbus TCP

Editing an interface

To edit an interface:

1. in the **'Interfaces'** box, select the network to edit
2. click  **Edit**
3. update the data for the physical network
4. click  **Save**

Removing an interface

To remove an interface:

1. in the **'Interfaces'** box, select the network to remove
2. click  **Remove**
3. followed by "OK"

Buttons and selectors

Icon	Function	Description
	Add	Used to add a new interface
	Remove	Used to remove an interface
	Edit	Enables edit mode for an interface
	Save	Save the changes made to the interface
	Cancel	Cancel and exits without saving the changes made.
	Back	Takes you back to the Equipment > Add device page

Selecting energy resources

TelevisGo v10 allows you to treat the resources of some devices as energy utilities, i.e. measuring the electricity consumption of a plant. The resources recorded will be saved in a dedicated database that is separate from the one with saved historical data, and with a separate registration interval. In the following menu:

 **Settings > Interfaces > Energy Resources**

The page appearing is:



The different parts of the screen are:

1. **Registration interval:** used to set the calculation period for data relating to energy resources. To define the interval select the box. The following window will open:



Set the days, hours, minutes and seconds required and confirm with "OK". The minimum interval that can be set is 15 minutes.

2. **Control bar:** see [Buttons and Selectors](#).


Example: if you set a period of 1 hour, the system will calculate the corresponding consumption of the energy resource for every hour.

Selecting algorithms

In the following menu:

 **Settings > Interfaces > Algorithms**

The following screen will appear:



Interface	ID	Address	Devices
Algorithms	998	127.0.0.1	10
Address	Model	Description	Period
<input checked="" type="checkbox"/> 00:01	FloatingSuction	998.00.01 FloatingSuction	60
<input checked="" type="checkbox"/> 00:02	FloatingSuction	998.00.02 FloatingSuction	60
<input type="checkbox"/> 00:03	FloatingSuction	998.00.03 SumO2Probes	60
<input type="checkbox"/> 00:04	FloatingSuction	998.00.04 SumO2Probes	60
<input checked="" type="checkbox"/> 01:00	SaturationSensorBackup	998.01.00 SaturationSensorBackup	60
<input type="checkbox"/> 01:01	SaturationSensorBackup	998.01.01 SaturationSensorBackup	60
<input checked="" type="checkbox"/> 02:00	CentralizedDewPoint	998.02.00 CentralizedDewPoint	330
<input type="checkbox"/> 02:01	CentralizedDewPoint	998.02.01 CentralizedDewPoint	330
<input checked="" type="checkbox"/> 03:00	EnergyPatternDeviationAlert	998.03.00 EnergyPatternDeviationAlert	330
<input type="checkbox"/> 03:01	EnergyPatternDeviationAlert	998.03.01 EnergyPatternDeviationAlert	330

This page shows the list of algorithms previously loaded on TelevisGo v10 (see "Updating the system") and relevant settings.

The different parts of the page are:

- Description:** used to filter by description. The instances of an algorithm all implement the same logic, but should be applied to different input/output data. The number of instances replicated is a pre-set parameter in the algorithm:
 - The maximum number of algorithms managed at the same time by TelevisGo v10 is **16**
 - The maximum number of instances managed at the same time by TelevisGo v10 is **16**
 - The maximum number of instances per algorithm is **10**
- Address:** represents the address linked to each instance and is assigned automatically by the application.
- Model:** the model of each algorithm is set in the programming phase.
- Period:** represents the current cycle period of the instance. The period is expressed in seconds, it can take a value between 60 (1 minute) and 86400 (1 day).
- Control bar:** see [Buttons and Selectors](#).

The colors of the rows that will appear have the following meanings:

- BLACK:** virtual device selected
- GREEN:** virtual device available but not selected

Select the instances to be enabled on the virtual interface by ticking the relevant check box near the address (2) and press the  **Save** icon to store the algorithm instance configuration.

Notes:

- Before using an algorithm, consult the relevant manual which is available to download from the website www.eliwell.com
- Algorithm:** model containing a specific programming code
- Instance:** use of the model associated with one or more controllers according to algorithm operation
- When the user loads an algorithm, TelevisGo v10 (see [Updating algorithm drivers](#)), automatically enters the maximum number of instances anticipated for that algorithm without activating them
- Selecting the box on the left-hand side of an algorithm instance activates it.


User management

Viewing groups and users

In the following menu:

 **Settings > Users > General view**

The following screen will appear:



The different parts of the page are:

1. **Groups:** list of all groups recorded in the system.
2. **Users:** list of all users recorded in the system, divided by group.

Note: On first start-up, the following are present:

- 5 pre-registered groups
- 1 "Administrator" user.


Various users will therefore need to be created with the relevant permissions and belonging to specific groups.

Group management

In the following menu:

 **Settings > Users > Groups**

The following screen will appear:



The screenshot shows the Group Management interface with the following components:

- 4 Control bar:** Add, Edit, Remove, Save, Cancel
- 1 Groups:**

Name	Description
✓ Administrators	Default administrator group
✓ Operators	Default operator group
✓ Users	Default user group
✓ Readers	Default reader group
✗ Services	Default services group
- 2 Details:**
 - Enabled
 - Name*: Administrators
 - Description: Default administrator group
- 3 Permissions:**
 - Application/languages upgrade
 - Drivers update
 - Licence upgrade
 - Controller network and equipment configuration
 - Alarm management
 - Alarm acknowledgement
 - User/group management
 - Parameter access
 - Command access

The different parts of the page are:

- Groups:** lists all groups recorded in the system.
- Details:** used to set the name and description of a group (active only after pressing  **Add** or  **Edit**).
- Permissions:** used to set the permissions associated with the specific group, enabling/disabling the option of updating/configuring one or more functions (active only after pressing  **Add** or  **Edit**).
- Control bar:** see [Buttons and Selectors](#).

To edit the Group Permissions, you must be logged in as Administrator or have the necessary authorization credentials for User/group configuration.

The first time it is accessed, the following groups are present, with the corresponding permissions:

- **Administrators:** administrators
- **Operators:** operators
- **Users:** users
- **Readers:** readers
- **Services:** general services

For example: if we set the option "**Layouts - Writing permissions**":


- Check box ticked: users belonging to the group will have full control of the layout pages (they can change the values of variables, perform commands, etc.)
- Check box not ticked: users belonging to the group can only view the layout pages.

User management

In the following menu:

 **Settings > Users > Users**

The following screen will appear:



The screenshot shows the 'Users' management interface. At the top, there is a control bar with buttons for 'Add', 'Remove', 'Edit', 'Save', and 'Cancel'. Below this, the interface is split into two main sections:

- 1 Users:** A table listing users, grouped by 'Group'. The 'Administrators' group contains one user, 'Administrator', with a checkmark in the 'Enabled' column. The 'Description' for this user is 'Default administrator'.
- 2 Details:** A form for editing or adding a user. It includes:
 - 3 Enabled:** A checked checkbox.
 - 4 Group*:** A dropdown menu set to 'Administrator'.
 - 5 User name*:** A text input field containing 'Administrator'.
 - 6 Password:** A password input field with a red indicator dot on the right.
 - 7 Description:** A text area containing 'Default administrator'.
 - 8 Password expiration (dd/MM/yyyy):** A date input field set to 'dd/MM/yyyy'.
 - 9 Password expiry period:** A dropdown menu set to '90 days'.

The different parts of the page are:

- Users:** lists all users recorded in the system, divided by group.
When first accessing the page, only the "Administrator" user will be present.
- Details:** view/edit a user's data
- Enabled:** the tick enables the user
- Group:** select the group in which to enter the user. The group should already have been created.
- User name:** set the name assigned to the user.
- Password:** set the password assigned to the user.
The password must contain:
 - 8 characters
 - 1 numerical digit (0, 1, ... , 9)
 - 1 uppercase letter (A, B, ... , Z)
 - 1 lowercase letter (a, b, ... , z)
 - 1 special character (|\-!'£\$%^&*()_+~=&[]{};:'@#~<>./?)
- To the left of the password box is an indicator:
 - **RED:** indicates that the password does not meet the minimum requirements
 - **GREEN:** indicates that the password is valid
 - **GREY:** indicates that the password has not been changed
- Description:** enter any notes relating to the user. The 3 lines in the bottom right-hand corner can be used to enlarge the text box.
- Expiration:** after saving the user, this shows the expiry date of the password in dd/MM/yyyy format. If set not to expire, it will show "never".
- Expiry period:** selects the password expiry period.
The pre-set periods are:
 - 90 days
 - 180 days
 - 1 year
 - never
- Control bar:** see [Buttons and Selectors](#).

NOTE: Only an administrator (**Administrator**) can add, edit or remove users and groups.

NOTE: Each user can change their own password by selecting "Change password" from the current user menu (see [Status bar](#)).

NOTE: When the password expires, the user will be redirected straight to the change password page (see [Changing the password](#)). Once it has been changed, they will be taken to the "Home" page.


Alarm configuration

Overview

In the following menu:

 **Settings > Alarms > View**

The following screen will appear:



Level	Escalate	Name	Actions	Time intervals
1		Level 1	Mail	Always
1		Universal		
2	Escalate deactivated	Level 2	Mail	Always
2	Escalate active	Level 2 - Escalate	Mail	Always
3	Escalate deactivated	Level 3	Mail	Always
3	Escalate active	Level 3 - Escalate	Mail	Always
4	Escalate deactivated	Level 4	Mail	Always
4	Escalate active	Level 4 - Escalate	Mail	Always

The different parts of the page are:

- Level:** identifies the level assigned to the alarm category
- Escalate:** enable or disable the checking of higher levels:
 -  = escalate to higher levels active
 -  = escalate to higher levels deactivated.
- Name:** view the name assigned to the alarm category.
- Actions:** lists the alerts activated for the alarm category.
- Time intervals:** lists the time intervals in which the alarm category is active.

Alarm management rules

Alarms are categorized to allow association of a series of actions within specific time intervals

In the event of an **Alarm**, the system will check whether it is managed, on which device it occurred, whether it belongs to a valid category and if it was activated during a valid interval. If all conditions have occurred, the actions set in the valid alarm categories will take place in accordance with a level-based system.

TelevisGo v10 sends an alarm alert to all correctly configured and enabled recipients.

The methods used by TelevisGo v10 to send alarms are guided by the concepts of "Level" and "Escalate" (see [Alarm categories](#)).


Level	Expected behavior
Level x (where x=4,3,2,1)	The software checks the alarm categories starting from Level x , and runs the notifications for all those which satisfy the criteria.
Level x – Escalate (where x=4,3,2,1)	If at least one of the alarm categories in the previous point is marked as "Escalate", the software proceeds to check the higher level (from 4 to 1).

Alarm categories

To set the alarm categories, go through the following menus:

 **Settings > Alarms > Alarm categories**

The following screen will appear:



The different parts of the page are:

- Alarm categories:** view the set "Alarm categories".
- Name:** set the name to be assigned to the alarm category.
- Setting:** used to set the following characteristics:
 - Enabled:** enable/disable "Alarm category".
 - Escalate:** enable or disable the checking of higher levels.
 - : the "All devices" check box has been selected.
 - : a list of specific devices was selected.
 - : the "All alarms" check box has been selected.
 - : a list of specific alarms has been selected.
 - Level:** Depending on what has been set in points (6), (7), (8) and (9), the "Alarm Category" is assigned a level from 1 to 4 according to:

Level	Level 1	Level 2	Level 3	Level 4
Select devices	All	All	Select	Select
Select alarms	All	Select	All	Select

- Actions:** select which actions to execute.
- Time intervals:** select when to execute the selected actions. By default only 'Always: always' is present. The set time intervals are listed as an addition (see [Time intervals](#))
- All devices:** select all network devices.
- Filter devices:** used to filter the devices to which the actions are applied by description.
- All alarms:** select all network alarms.
- Alarms filter:** used to filter the alarms by description.
- Interface:** select all the devices in a network interface.
- Select devices:** select one or more devices from the list.
- Select alarms:** select which alarm types should be handled.
- Description:** the displayed description is as follows:

- A. If all the alarm types have the same alias (no ambiguity for the user): the common description will be displayed
 - B. If all the alarm types have different aliases: the generic description of the alarm type will be displayed.
14. **Icon** : if displayed, it acts as a visual alert for the user that the description shown on the left is generic and may not match the aliases they configured, and therefore the user should refer to the alarm ID to be certain which alarms are being managed.
 15. **Id**: alarm type identification code.
 16. **#**: shows the number of devices across the network that have the specific alarm types selected. To select alarm types refer to "[Equipment alarms](#)" section.
 17. **Control bar**: see [Buttons and Selectors](#).

TelevisGo v10 always and exclusively takes set categories into account, and always begins at Level 4, where present. If there are several categories at the same level, the device will run them all.

Once the Level 4 category actions are complete (if applicable), if at least one Level 4 category has the '**Escalate**' flag selected, the system will check for Level 3 categories and carry out the procedures. The same applies to the other levels.

If the '**Escalate**' flag is selected in a Level 4 category is selected, the system will check for the first configured category of a higher level and carry out the procedures, regardless of whether the level is 3, 2 or 1.

To select an alarm you must first select the device for which you wish to view the alarms, or select all devices to view the list of all alarms.


If several time intervals are associated with the same category, they are considered as grouped together (except in the case where one of the intervals is 'Always = always', which becomes 'always').

Actions

To set the actions to be performed in the event of an alarm, go through the following menus:

 **Settings > Alarms > Actions**

The following screen will appear:



The different parts of the page are:

1. **Actions:** all set "Actions" are shown.
2. **Enabled:** tick the check box to Enable/Disable the execution of the selected action.
3. **Type:** used to set the type of action being set.
4. **Name:** used to set the action. The field sequence varies according to the "Type" selected in point (3).
5. **Control bar:** see [Buttons and Selectors](#).

5 different types of action may be created:

- **TelevisTwin:** enter the IP addresses of a TelevisTwin to which any alarm messages should be sent
- **Mail:** enter an email address to which any alarm messages should be sent
- **SMS via modem:** enter the telephone number you want SMS messages to go to in the event of an alarm
- **Phone Call:** enter the telephone number you want to call in the event of an alarm
- **Commands:** set the commands to be sent to one or more devices in the event of an alarm.

Selecting from the drop-down menu (3) will vary the dependent controls (4).

Actions are only active when entered in an alarm category.

One of the following windows opens:

A - TelevisTwin	B - Mail	C - SMS via modem
<div data-bbox="225 286 604 551"> <p>Details</p> <p><input checked="" type="checkbox"/> Enabled</p> <p>Type: <input type="text" value="TelevisTwin"/></p> <p>Name: <input type="text"/></p> <p>Address: <input type="text"/> Port: <input type="text"/></p> <p>Address 1: <input type="text"/> Port: <input type="text"/></p> <p>Address 2: <input type="text"/> Port: <input type="text"/></p> <p>SMS: <input type="text"/></p> <p>Signal strength: Not available</p> <p>Send test SMS Make test phone call</p> </div>	<div data-bbox="639 286 1026 551"> <p>Details</p> <p><input checked="" type="checkbox"/> Enabled</p> <p>Type: <input type="text" value="e-mail"/></p> <p>Name: <input type="text"/></p> <p>email address: <input type="text" value="eliwell@se.com"/> <input type="button" value="Validate..."/></p> <p>Signal strength: Not available</p> </div>	<div data-bbox="1061 286 1441 551"> <p>Details</p> <p><input checked="" type="checkbox"/> Enabled</p> <p>Type: <input type="text" value="SMS via Modem"/></p> <p>Name: <input type="text"/></p> <p>Telephone number: <input type="text" value="+390000000"/> <input type="button" value="Validate..."/></p> <p>Signal strength: Not available</p> </div>
D - Phone Call		E - Commands
<div data-bbox="331 598 708 853"> <p>Details</p> <p><input checked="" type="checkbox"/> Enabled</p> <p>Type: <input type="text" value="Phone Call"/></p> <p>Name: <input type="text"/></p> <p>Telephone number: <input type="text" value="+390000000"/> <input type="button" value="Validate..."/></p> <p>Signal strength: Not available</p> </div>		<div data-bbox="954 598 1331 853"> <p>Details</p> <p><input checked="" type="checkbox"/> Enabled</p> <p>Type: <input type="text" value="Commands"/></p> <p>Name: <input type="text"/></p> <p>Device: <input type="text" value="Ambient monitor and TGO"/></p> <p>Command on activating alarm</p> <p>Command: <input type="text" value="Alarm silencing on output 1"/></p> <p>Command on inactivating alarm</p> <p>Command: <input type="text" value="Alarm silencing on output 1"/></p> </div>

Once all selections have been made, click  **Save** to save the changes or  **Cancel** to cancel them.

A. TelevisTwin:

- Name: enter the name assigned to the action
- Address: enter the IP address of the device (for example: 192.168.0.23) and the corresponding port (for example: 8080)
- Address 1: enter an alternative IP address 1 and the corresponding port
- Address 2: enter an alternative IP address 2 and the corresponding port
- SMS: enter the telephone number you want SMS messages to go to (for example: +39 333 7600000)
- Signal strength: indicates the signal strength of the modem connected to TelevisGo v10 (as a %)
- Send test SMS: sends a test text message to the entered number
- Test telephone call: tries to call the entered telephone number.

B. Mail:

- Name: enter the name assigned to the action
- e-mail: enter the email address to which alarm alerts should be sent
- Validate: is used to validate the email address. If it is correct, the LED turns **GREEN**.

C. SMS via Modem:

- Name: enter the name assigned to the action
- Telephone number: enter the telephone number you want SMS messages to go to (for example: +39 333 7600000)
- Validate: is used to validate the telephone number. If it is correct, the LED turns **GREEN**
- Signal strength: indicates the signal strength of the modem connected to TelevisGo v10 (as a %).

D. Phone Call:

- Name: enter the name assigned to the action
- Telephone number: enter the telephone number to be called (for example: +39 333 7600000)
- Validate: is used to validate the telephone number. If it is correct, the LED turns **GREEN**
- Signal strength: indicates the signal strength of the modem connected to TelevisGo v10 (as a %).

E. Commands:

- Name: enter the name assigned to the action
- Device: indicates which device within the network is to be targeted
- Command on activating alarm: indicates what the device has to do if an alarm is activated
- Command on inactivating alarm: indicates what the device has to do after an alarm has been deactivated.


Remember to enter the international dialing code of the Recipient before the telephone number, for both telephone calls and SMS messages (for example: for ITALY enter +39).

Time intervals

To set the time intervals, go through the following menus:

 **Settings > Alarms > Time intervals**

The following screen will appear:



The different parts of the page are:


1. **Time intervals:** shows all the set “Time Intervals”.
2. **Type:** used to set the type of time interval.
3. **Period:** used to set the time period associated with the interval (the fields vary according to the type of interval selected).
4. **Chart:** chart representing the set time interval.
5. **Control bar:** see [Buttons and Selectors](#).

3 different types of time interval can be created:

- **Daily**
- **Weekly**
- **Monthly**

Selecting from the drop-down menu will vary the dependent controls.

Depending on the type of interval selected, the following windows open:




A. Daily time period:

- Name: to enter the name assigned to the interval
- Interval: the 2 selection boxes are used to set the start and end time valid for every day (example: **08.00 > 19.00** indicates from 08.00 in the morning to 7.00 in the evening; **19.00 > 06.00** indicates from 7.00 in the evening to 06.00 the following morning)


B. Weekly time period:

- Name: to enter the name assigned to the interval
- Periodic: here you should set:
 - the days of the week involved (from → to)
 - the time period involved (from → to) on each day
- Continuous: here you should set:
 - the day of the week and the start time
 - the day of the week and the end time:



C. Monthly time period:

- Name: to enter the name assigned to the interval
- Periodic: here you should set:
 - the days of the month involved (from → to)
 - the time period involved (from → to) on each day
- Continuous: here you should set:
 - the day of the month and the start time
 - the day of the month and the end time:



NOTE: the "ALWAYS" time interval is pre-set as part of the system and cannot be deleted (it selects 24 hours for all days of the week).

Scheduler

Introduction

TelevisGo v10 can automatically run actions that have been scheduled by users in line with a programmable time schedule.

There are three types of scheduled activities:

- Send command to one or more devices.
- Write parameters to one or more devices.
- Data export

Scheduled activities can have one of three types of frequency:

- Periodic: the action is carried out periodically, with the frequency defined by the user
- Daily: the action is carried out every **n** days at one or more times during the day
- Weekly: the action is carried out every **n** weeks, on specific days and at one or more times during the day.

Each scheduled action has a validity interval, defined by a start date and an end date.

The action is therefore performed in accordance with the set schedule. If the action fails, TelevisGo v10 continues to attempt to execute it at user-defined intervals up to a maximum time, as set by the user. If the maximum duration is set to **0** or if it is less than the re-attempt interval, no further attempts will be made.

The scheduled actions apply to a selection of devices in the current configuration and are used to optimize activity.

If the user sets many actions to be carried out frequently, it may cause delays in the transmission of signals and/or malfunctioning. Similarly, generating frequent exports may cause an excessive number of files to be created which, in time, may slow the machine down or lead to malfunctions if they are not moved from the folder inside the TelevisGo v10 to an external network folder.

NOTICE

INOPERABLE DEVICE

- Do not use the "Scheduled actions" function to manage critical actions.
- Set up a network folder outside the TelevisGo v10 if you anticipate a lot of data exports being generated.

Failure to follow these instructions can result in equipment damage.

General view

In the following menu:

 **Settings > Scheduled actions > Summary**

The following screen will appear:

1 Type	2 Name	3 Description	4 Schedule	5 Next execution
	Defrost	Send command: Manual Defrost activation (1 device)	Every week on Sunday, Wednesday and Saturday at 09:30 and 12.30 (beginning on 31-Jul-11 22.00)	30-Jun-18 09.30
	Writing maps	Write parameter map: Map_1.dat (16 devices)	Execution on demand	-----
	Setpoint	Export data into 'C:\Eliwell\TelevisDB\Exports' using profile: DefaultGraph (13 devices)	Every week on Sunday at 16:05 (beginning on 8-Jun-18 12:02)	28-Jun-18 05.00

The different parts of the page are:

1. **Type:** identifies the type of scheduled action:

-  = Sending a command
-  = Writing parameters
-  = Data export

2. **Name:** is a user-defined label.

3. **Description:** describes the activity that will be performed; the number of devices it will be applied to is given in brackets.

4. **Schedule:** describes the frequency of the activity.


5. **Next execution:** states the next day/time the activity will be performed.

Managing scheduled actions

To edit the scheduled actions, enter the following menus in sequence:

 **Settings > Scheduled actions > Actions**

The following screen will appear:



The screenshot shows the 'Scheduled actions' configuration page. At the top, there is a control bar with buttons: Add, Remove, Edit, Save, Cancel, and Preview. The main content area is divided into four sections, each marked with a numbered circle:

- 1 Actions:** A list of existing actions: Defrost, Writing Map, and Setpoint, each with a checkmark and an icon.
- 2 Action:** Configuration for a new action. Fields include Name (text input), Type (dropdown menu set to 'Command'), Command (dropdown menu set to 'Device On'), and an 'Enabled' checkbox.
- 3 Schedule:** Configuration for the action's schedule. Fields include Type (dropdown menu set to 'Periodic'), Starting date, Ending date, Period, Retry duration (01:00:00), and Retry interval (00:05:00).
- 4 Devices:** Selection of devices to run the action on. It includes a 'Filter devices' search box and a table of available devices.

Interface	Address	Device
<input type="checkbox"/> Serial Adapter	COM1	4
Description		
<input checked="" type="checkbox"/>	1.00.04 RTX 600/V DOMINO ZERO (system)	
<input checked="" type="checkbox"/>	1.02.03 RTX 600/V DOMINO ZERO (system)	
<input type="checkbox"/>	1.11.01 Televisin (system)	
<input type="checkbox"/>	Controller 1 - demo	
<input type="checkbox"/> Algorithms	127.0.0.1	2
Description		
<input type="checkbox"/>	998.00:01 FloatingSuction	
<input type="checkbox"/>	998.00:02 FloatingSuction	

The different parts of the page are:

- 1. Actions:** list of actions.
- 2. Action:** section for creating/editing an action.
- 3. Schedule:** section for setting when to run an action.
- 4. Devices:** section for selecting the devices on which the actions will run.
- 5. Control bar:** see [Buttons and Selectors](#).

The part on the right is split into 3 sections:

Action

The **Action** section allows you to set the **Type** of action to be performed.

Type of action: Command

Action

Name **Enabled**

Type

Command

Instrument on

Instrument off
Energy saving function activation
Energy saving function deactivation
Economy Mode On
Economy Mode Off
Lights On
Lights Off
Keypad Locked

Used to set the type of **command** to run on the devices selected by the filter:

- **Name:** name associated with the action
- **Type:** Action = Command
- **Command:** drop-down menu displaying the complete set of commands for all the devices in the network configuration.

To make the action effective, click on "enabled".

Type of action: Parameter writing

Action

Name **Enabled**

Type

Type

File name

Warning: The electronic devices could be damaged by too frequent EEPROM parameters writings.

Used to set the name of the map file to apply to each execution of a **parameter map writing** action.

- **Name:** identifies the name associated with the action
- **Type:** Action = Writing parameters
- **Type:** Parameters map
- **File name:** name of the file containing the map to be uploaded.

For the TelevisGo v10 to be able to perform the operation, the map file must be uploaded from the system update page.

WARNING

UNINTENDED EQUIPMENT OPERATION
Frequent writing of EEPROM parameters can damage the system memory.
Failure to follow these instructions can result in death, serious injury, or equipment damage.

+ **Action**

Name **Enabled**

Type ▼

Type ▼

Parameters

Label (case sensitive)

Value +

Label	Value	
Set	-2	-
HAL	1	-
LAL	-5	-

! **Warning:** The electronic devices could be damaged by too frequent EEPROM parameters writings.

Used to manually enter the list of parameters to write and their value at each execution of the individual **parameter writing action**. At least one parameter must be entered.

- **Name:** identifies the name associated with the action
- **Type:** Action = Writing parameters
- **Type:** Parameters
- **Label:** name of the parameter to be uploaded
- **Value:** value to write in the parameter

To enter a new parameter, fill in the Label and Value fields and click +. The label/value pair will be added to the list below.

If a label ??? is shown in the table (Label not recognized), the TelevisGo v10 will overwrite it as soon as another pair of values is entered.

TelevisGo v10 checks for label duplications. Values associated with duplicated labels will be overwritten.

To remove a previously inserted label/value pair from the list, click the - button.

NOTE: for the TelevisGo v10 label there is a distinction between uppercase and lowercase letters (case-sensitive).

! **WARNING**

UNINTENDED EQUIPMENT OPERATION

Frequent writing of EEPROM parameters can damage the system memory.

Failure to follow these instructions can result in death, serious injury, or equipment damage.

Type of action: Data export

Action	
Name	<input type="text"/> <input checked="" type="checkbox"/> Enabled
Type	Data Export <input type="text"/>
Period	Flash <input type="text"/>
<input checked="" type="checkbox"/> Folder:	C:\Eliwell\TelevisDB\Exports <input type="checkbox"/> Export to CSV <input type="checkbox"/> Export to PDF <input type="checkbox"/> Print
<input type="checkbox"/> Email recipients:	<input type="text"/> ● <input type="button" value="Validate..."/>

Used to export data from the previous day (from 00:00 to 24:00) as selected via the filter.

- **Name:** identifies the name associated with the action
- **Type:** Action = Data export
- **Period:** immediate
- **Programming:** daily

One or more of the following actions can be set:

- **Folder:** the folder in which to save the data and its format (.csv, .pdf or both).
- **Print:** print data
- **Email recipients:** the emails to which the data should be sent. When an email is entered, it must be validated. If it is correct, the LED turns **GREEN**.

Action	
Name	<input type="text"/> <input checked="" type="checkbox"/> Enabled
Type	Data Export <input type="text"/>
Period	Daily <input type="text"/> Undersampling None <input type="text"/> <input type="checkbox"/> Export variations
<input checked="" type="checkbox"/> Folder:	C:\Eliwell\TelevisDB\Exports <input type="checkbox"/> Export to CSV <input type="checkbox"/> Export to PDF <input type="checkbox"/> Print
<input type="checkbox"/> Email recipients:	<input type="text"/> ● <input type="button" value="Validate..."/>

Used to export data from the previous day (from 00:00 to 24:00) as selected via the filter.

- **Name:** identifies the name associated with the action
- **Type:** Action = Data export
- **Period:** Daily
- **Programming:** daily
- **Undersampling** : if the value is **None**, all data from the previous day will be exported (from 00:00 to 24:00). If its **x** value is different, only the data read every **x** minutes/hours will be exported (where **x** = 5 min, 15 min, 30 min, 1h, 2h, 3h, 4h, 6h and 12h).
- **Export variations:** if selected, events (variations of the values) that have taken place at times other than those programmed will also be exported.

One or more of the following actions can be set:

- **Folder:** the folder in which to save the data and its format (.csv, .pdf or both).
- **Print:** print data
- **Email recipients:** the emails to which the data should be sent. When an email is entered, it must be validated. If it is correct, the LED turns **GREEN**.

Action

Name **Enabled**

Type

Period **Undersampling** **Export variations**

Folder: **Export to CSV** **Export to PDF** **Print**

Email recipients:

Used to export data from the previous week (from 00:00 Monday to 24:00 the following Sunday) as selected via the filter.

- **Name:** identifies the name associated with the action
- **Type:** Action = Data export
- **Period:** Weekly
- **Programming:** Weekly
- **Undersampling** : if the value is **None**, all data from the previous day will be exported (from 00:00 to 24:00). If its **x** value is different, only the data read every **x** minutes/hours will be exported (where **x** = 5 min, 15 min, 30 min, 1h, 2h, 3h, 4h, 6h and 12h).
- **Export variations:** if selected, events (variations of the values) that have taken place at times other than those programmed will also be exported.

One or more of the following actions can be set:

- **Folder:** the folder in which to save the data and its format (.csv, .pdf or both).
- **Print:** print data
- **Email recipients:** the emails to which the data should be sent. When an email is entered, it must be validated. If it is correct, the LED turns **GREEN**.

NOTES:

- multiple email addresses should be separated by “;”
- The profile for the exported data can be created/edited using the “Historical data” function
- The default is "System_HACCP" which exports the values of the first probe and defrost status of the instruments in the network.

Programming:

The **Schedule** section is used to define the **Type** of schedule.

Type of scheduling: Periodic

Schedule

Type

Starting date

Ending date

Period

Retry duration

Retry interval

Set time span
days.hours:minutes:seconds

: : :

Periodic schedule requires the user to define:

- **Type:** type of schedule
- **Start date:** start date and time of the schedule
- **End date:** end date and time of the schedule
- **Period:** how often to carry out the action (days:hours:minutes:seconds). A window opens (top left-hand corner) in which to enter the period, followed by clicking OK
- **Retry duration:** maximum duration of the action retry attempts in the event that an action fails
- **Retry interval:** how long to leave before performing the action again in the event that an action fails.

This type of event will be carried out for the first time at the time set in the **Start date** box.

In the example, the action will be carried out every day plus 6 hours (30 hours).

Type of scheduling: Daily

🔍 Schedule
Execution times

Type:

Starting date:

Ending date:

Period:

Retry duration:

Retry interval:

Time

03:00

Select a time

03 : 00

OK

Daily schedule requires the user to define:

- **Type:** type of schedule
- **Start date:** start date and time of the schedule
- **Start date:** end date and time of the schedule
- **Execution times:** one or more times during the day when the action must be executed. A window opens (top left-hand corner) in which to enter the time, followed by clicking OK. The time will be added to the list. Repeat the procedure to add new times.
To remove a time added to the list, click the button
- **Period:** how often in days the action must be executed
- **Retry duration:** maximum duration of the action retry attempts in the event that an action fails
- **Retry interval:** how long to leave before performing the action again in the event that an action fails.

This type of event will be carried out at the first available time, on the date and at the time set in the **Start date** box.
In the example, the action will be carried out every day at 3:00.

Type of scheduling: Weekly

🔍 Schedule
Execution times
Week

Type:

Starting date:

Ending date:

Period:

Retry duration:

Retry interval:

Time

09:30

12:30

Sunday

Monday

Tuesday

Wednesday

Thursday

Friday

Saturday

Select a time

12 : 30

OK


Weekly schedule requires the user to define:

- **Type:** type of schedule
- **Start date:** start date and time of the schedule
- **Start date:** end date and time of the schedule
- **Execution times:** one or more times during the day when the action must be executed. A window opens (top left-hand corner) in which to enter the time, followed by clicking OK. The time will be added to the list. Repeat the procedure to add new times.
To remove a time added to the list, click the button
- **Week:** on which days of the week the action is to be executed. If no day is selected, on saving, TelevisGo will automatically select Sunday.
- **Period:** every how many weeks the action must be executed
- **Retry duration:** maximum duration of the action retry attempts in the event that an action fails
- **Retry interval:** how long to leave before performing the action again in the event that an action fails.

This type of event will be carried out at the first available time, on the date and at the time set in the **Start date** box.
In the example, the action will be performed every week on Sunday, Wednesday and Saturday at 9:30 and 12:30.

Devices

The **Devices** section is used to select the devices belonging to the network to which the action being set is to be applied.



The different parts of the page are:


1. **All devices:** select all network devices.
2. **Filter devices:** used to filter network devices by description. The page shows only the devices which satisfy the filter.
3. **Interface:** used to select all devices with the same interface by ticking the relevant check box.
4. **Devices:** used to select the individual devices on an interface by ticking the relevant check box.

Printing exported data

To view a list of the **Data Export** procedures performed, enter the following menus in sequence:

 **Settings > Scheduled actions > Print**

The following screen will appear:



In the figure above, TelevisGo v10 shows a list of previously saved **Data Export** files and their details.

Customizing reports

The reports have no headings, unless this is expressly specified by the user.

The orientation of the report changes according to whether real-time data or historical data is being printed:

- **Real-time data:** the report will be in portrait
- **Historical data:** the report will be in landscape

Headings use the same graphic elements (logos, images, titles).

The following is an example of an historical report with the heading shown:

Time (Date)	0.00-04 EWDR 985 LX Analogue input 1	0.00-05 EWDR 985 LX Analogue input 1
08.57.16 (05/09)	-23.6	-7.4
09.12.16	-23.6	-7.4
09.27.16	-23.6	-7.4
09.42.17	-23.6	-7.4
09.57.16	-23.6	-7.4
10.12.16	-23.6	-7.4
10.27.16	-23.6	-7.4
10.42.17	-23.6	-7.4
10.57.16	-23.6	-7.4
11.12.16	-23.6	-7.4
11.27.16	-23.6	-7.4
11.42.17	-23.6	-7.4
11.57.15	-23.6	-23.3
12.10.33	-23.6	-7.4
12.23.50	-23.6	-7.4
12.38.51	-23.6	-7.4
12.53.51	-23.6	-7.4
12.57.33	-23.6	-7.4
13.12.33	-23.6	-7.4
13.27.33	-23.6	-23.3
13.42.33	-23.6	8.4
13.57.34	-23.6	8.4
14.12.34	-23.6	-7.4
14.27.34	-23.6	-7.4
14.42.34	-23.6	-7.4
14.57.35	-23.6	-23.3
15.12.34	-23.6	-7.4
15.27.34	-23.6	-7.4
15.42.34	-23.6	-23.3
15.57.35	-23.6	-7.4
16.12.34	-23.6	-7.4
16.28.03	-23.6	-7.4
16.43.03	-23.6	-7.4
16.58.03	-23.6	-7.4
17.13.03	-23.6	-7.4
17.28.04	-23.6	-7.4
17.43.03	-23.6	-23.3
17.58.03	-23.6	-7.4

	TITLE LINE Subtitle line 1 Subtitle line 2	
 Plant name: Eliwell Supermarket 04 April 2013 03:00:01 C70A97410	1: Active - 0: Sleeping	Page 1 of 3

To **customize** a report heading, access the following folder in TelevisGo v10:

C:\Eliwell\CustomReports

Once the editing/customization of one or more files in the list is performed, it is necessary to **restart the service** to apply the changes.

This folder contains the following files:

- logo-left.png**: contains the logo that will appear to the left of the heading (1).
- logo-right.png**: contains the logo that will appear to the right of the heading (3).
- ReportTemplate.xml**: this is the report template and can be used to set the three lines of text (2).

Editing PNG files (files A & B)

Replace the PNG files with the logos or images that need to be inserted in the report title.
The positions will be as follows:

- **logo-left.png**: logo/image that will appear to the left of the header (1)
- **logo-right.png**: logo/image that will appear to the right of the header (3)

The default files contain the Eliwell logo and the TelevisGo v10 (see example).

The images will be sized to adapt them on the report header.

The images will not be displayed if files are removed or if the file names do not correspond to the content in the template (file C).

Editing XML files (file C)

Edit the file using a text editor (for example: Notepad++).

There are two parts of the code that should be customised: one for real-time data reports and one for historical data reports.

1) Historical data

Edit the following text (line 4 of the file) (optional):

```
<historical gap="5" margin="20">
<customHeader logoLeft="logo-left.png" logoRight="logo-right.png" titleLine1="TITLE LINE"
titleLine2="Subtitle line 1" titleLine3="Subtitle line 2" />
<customValues>
```

Editable values in bold (see example image):

- **logo-left.png**: name of the image file to place to the left of the header (1).
- **logo-right.png**: name of the image file to place to the right of the header (3).
- **TITLE LINE**: text on the first line at the centre of the header (2), in bold.
- **Subtitle line 1**: text on the second line at the centre of the header (2).
- **Subtitle line 2**: text on the third line at the centre of the header (2).

If all boxes are left empty, the report will be produced without a header.

2) Real-time data (realTime)

Edit the following text (line 28 of the file) (optional):

```
<realTime gap="5" margin="20" orientation="portrait">
<customHeader logoLeft="logo-left.png" logoRight="logo-right.png" titleLine1="TITLE LINE"
titleLine2="Subtitle line 1" titleLine3="Subtitle line 2" />
<customValues>
```

Editable values in bold (see example image):

- **logo-left.png**: name of the image file to place to the left of the header (1).
- **logo-right.png**: name of the image file to place to the right of the header (3).
- **TITLE LINE**: text on the first line at the centre of the header (2), in bold.
- **Subtitle line 1**: text on the second line at the centre of the header (2).
- **Subtitle line 2**: text on the third line at the centre of the header (2).

If all boxes are left empty, the report will be produced without a header.

Registration interval settings

Contents

In the following menu:



Settings > Archive management > Summary

This screen summarizes all the settings on the TelevisGo v10 relating to data storage.

Control	
Historical database	
<i>Parameter</i>	<i>Current value</i>
Recording interval	5 minutes
Filling percentage	12.1%
Left registration time	>2 years
Oldest data	22 May 2023 11:30:00
Temporary database	
<i>Parameter</i>	<i>Current value</i>
Asynchronous data aggregation interval	1 minute
Maximum number of records	Modbus Tcp (80.59.196.141:30502)
Oldest data	28 August 2023 22:00:12
Manage	
<i>Parameter</i>	<i>Current value</i>
Maximum capacity	7 GB
Circularity-dedicated section size	10.0% (717 MB)
Most recent archive renewal date	Never accomplished

The settings for the following values are listed:

Historical database

- Recording interval
- Filling percentage
- Left registration time
- Oldest data

Temporary database

- Asynchronous data aggregation interval
- Maximum number of records
- Oldest data


Manage

- Maximum capacity
- Circularity-dedicated section size
- Most recent archive renewal date

Control

In the following menu:

Settings > Archive management > Control



The recording interval set (between 1 minute and 2 hours inclusive) is the storage interval (sample) for the values of the selected resources.

On this screen, press the  **Edit** icon to set:


- **Recording interval:** enter the value (hours:minutes:seconds) and press the  **Save** icon.
NOTE: This interval does not apply to **Machine states**, **Alarms** and **Digital resources**. In these cases, only changes in the variables themselves are recorded, and not in relation to the interval set.
- **Oldest data:** enter the desired date and press the  **Save** icon.
NOTE: if set, all data prior to the date entered will be deleted.
- **Asynchronous data aggregation interval:** enter the value and press the  **Save** icon.
NOTE: The allowed values are as follows: 00:00:01 (1 second), 00:00:15 (15 seconds), 00:00:30 (30 seconds), 00:01:00 (1 minute).

NOTE: access to this screen and editing the settings for controlling the data archive is reserved for system administrators and any authorized groups of users.

Manage

In the following menu:

Settings > Archive management > Manage



On this screen, press the  **Edit** icon to set:

Circularity-dedicated section size: enter the value and press the  **Save** icon.
NOTES:

- The adjustable value must fall between 5 % and 30 %. Values outside the range will generate an error.
- If "0.1" is entered, "10 %" will be saved; if "0.155" is entered, "15.5 %" will be saved; if a value with the "%" symbol is entered (for example, "15.5 %"), the value saved will be the same as the one entered ("15.5 %" in the example).
- access to this screen and editing the settings for managing the data archive is reserved for system administrators and any authorized groups of users, as it can affect system performance.

System general settings

⚠ WARNING

UNINTENDED EQUIPMENT OPERATION

- Install TelevisGo v10, SerialAdapter and EthernetAdapter in an environment in which EMC disturbance is below the limits specified in standard EN61000-6-1 (residential, commercial and light industry environments).
- Configure the "LifeTest" function to make sure the TelevisGo v10 is active. Non-receipt of the periodic email indicates a malfunction of the TelevisGo v10 or the email sending service.

Failure to follow these instructions can result in death, serious injury, or equipment damage.


System

This page is used to set the system language, the communication ports and the system life test notification sending times.

In the following menu:

 **Settings > General settings > System**

The following screen will appear:



The different parts of the page are:


1. **Languages:** set the language used in creating the alarm messages and communication with systems external to TelevisGo v10 (TelevisTwin or third-party systems). The system language setting impacts information relating to periodical exporting (.csv and .pdf files).
2. **Ports:** used to set the following ports:
 - **Web server:** identifies the port to be used for the WEB connection (example 443).
 - **Data transfer:** identifies the port to be used for data downloads (example: 8080).
3. **Email life test:** manages information relating to the sending of emails:
 - **Starting hour:** indicates what time the test should be carried out (example 05:00:00).
 - **Interval (hours):** indicates the test execution interval expressed in hours (example 6).
 - **Recipient:** indicates recipient/s to whom the test should be sent. If there are several recipients, separate addresses with ','.
4. **Validate...:** once the email addresses have been entered, the LED will turn **RED** to show that they have not been validated. Click "**Validate...**".
(NOTE: a mail server must have been configured in the section **Alarm management/Actions**). In the window that opens, enter the code received via email; the LED will turn **GREEN**. If one of the sending attempts fails, the LED will change color to **YELLOW**.
5. **Control bar:** see **Buttons and Selectors**.

Services

In the following menu:

 **Settings > General Settings > Services**

The following screen will appear:



3  Edit  Save  Cancel

1  **EcoStruxure Web Services (EWS) for IMP**

 Enabled

 Port [81 .. 65535]

 Language ▾

2  **TelevisTwin - Sending life test notifications**

 Twin - Life test - Sending period [1 minute .. 30 days]

 Twin - Life test - Delay on first send >= 0 seconds

 Twin - Life test - Retry interval [0 seconds .. 30 days]

 Twin - Life test - Retry duration [0 seconds .. 30 days]

The different parts of the page are:

1. **EcoStruxure Web Services (EWS) for IMP:** Manages the information of the EWS service:
 - **Enabled:** sets whether the EWS service is enabled or not
 - **Port:** Sets the connection port of the EWS service
 - **Language:** allows setting the language used in the data communication towards IMP.
2. **Sending life test notifications:** manages sending information for the Twin - Life test:
 - **Sending period:** indicates how often the life test should be carried out (example: 01:00:00).
 - **Delay on first send:** indicates how long to wait after start-up before sending a life report in hours (example: 00:15:00).
 - **Retry interval:** indicates the interval between 2 consecutive life report sending retries.
 - **Retry duration:** indicates the maximum interval within which life report sending attempts are made.
3. **Control bar:** see [Buttons and Selectors](#).


The life test will be sent to TelevisTwin if at least one "TelevisTwin" type action is configured on the system (see "[Alarm management/Actions](#)").

Alarms

In the following menu:

 **Settings > General Settings > Alarms**

The following screen will appear:



The screenshot shows the 'Alarms' settings page with the following sections and callouts:

- 1 General:** Contains 'Alarms - Retry interval' (00:01:00), 'Alarms - Retry duration' (01:00:00), and 'Alarms - Emergency recipient' (sms: +390000000).
- 2:** A red LED indicator next to the 'Validate...' button.
- 3 SMS:** Contains 'SMS alphabet' (Standard 7 bit) and 'Modem signal strength lower alarm threshold (%)' (40).
- 4 Email server configuration:** Contains fields for 'e-mail - Server - Address' (smtp.gmail.com), 'e-mail - Server - Port' (465), 'e-mail - Server - Sender address' (change@email.address), 'e-mail - Server - Authentication required' (checked), 'e-mail - Account - Name' (change@email.address), 'e-mail - Account - Password' (masked), 'Accept invalid certificate when SSL protocol is used by the email server' (checked), 'Email server timeout' (10000), and 'SSL protocol is used by the email server' (checked).
- 5 Test Utility (SMS):** Contains 'Message' (TelevisGo test text message) and 'Telephone number' (+390000000).
- 6 Test Utility (e-mail):** Contains 'Message' (TelevisGo test e-mail) and 'Address' (change@email.address).

The different parts of the page are:

- General:** used to set up the sending of alarms (see "Alarm management"):
 - Retry interval:** set the interval between 2 consecutive alarm sending retries.
 - Retry duration:** set the maximum alarm sending retry interval.
 - Emergency recipient:** set the telephone number to be called (for example: +390000000) and/or the email address (example: change@email.address) to set the telephone number to which an emergency message will be sent should the TelevisGo v10 database become corrupted and the recipients set by the user are no longer available. If several recipients are entered, they should be separated with “,”.

NOTICE

INOPERABLE DEVICE

- Set the emergency recipient to receive notifications relating to any TelevisGo v10 database malfunctions.
- Use a SIM card with an unlimited data plan for sending SMS messages and/or emails.

Failure to follow these instructions can result in equipment damage.

- Validate...:** once the telephone number has been entered, the LED will turn **RED** to show that it has not been validated. Click “Validate...”. In the window that opens, enter the code received via SMS; the LED will turn **GREEN**.
If one of the sending attempts fails, the LED will change color to **YELLOW**.
- SMS:** used to set the set up the sending of SMS messages:
 - SMS alphabet:** sets the type of alphabet to be used when sending SMS messages: **Standard 7 bit** (default) or **UCS-2** (Universal Character Set) or **Russian 7 bit**.
 - Modem signal strength lower alarm threshold (%):** sets the minimum modem signal threshold (as a percentage) which must be reached before a "Modem signal insufficient" alarm is activated.
- Email server configuration:** used to set the email server (**e-mail - Server**):
 - Address:** set the email server address.
 - Port:** set the email server connection port.
 - Sender address:** set the sender's email address.
 - Authentication required:** tell the system whether authentication is required.


- **Name:** sets the user name (if authentication is required).
 - **Password:** sets the user password (if authentication is required).
 - **Accept invalid certificate when SSL protocol is used by the email server:** used to allow invalid certificates when the SSL protocol is active.
 - **Email server timeout:** sets the maximum interval for attempting to communicate with the server before generating an error (timeout).
 - **SSL protocol is used by the email server:** sets whether the email server uses the SSL protocol.
5. **Test Utility:** used to instantly check that the settings entered are correct and operational by sending an SMS message.
 6. **Test Utility:** used to instantly check that the settings entered are correct and operational by sending an email.
 7. **Control bar:** see [Buttons and Selectors](#).

Media

TelevisGo v10 automatically detects the connectivity devices connected to it (MEDIA e.g. a LAN network or a GSM modem) and uses them to send alarm messages. In the following menu:

 **Settings > General Settings > Media**


The following screen will appear:



- The **Detected Media** box lists all elements located and the type of connection.
- The **Details** column shows the corresponding description.
- The **Detected** column indicates whether the specified media has been detected.

On clicking **Scan Peripherals**, the system starts scanning for media devices connected to TelevisGo v10.

TelevisGo v10 has a backup mechanism for alarm messages sent. From this page, you can decide in which order the system should sent alerts in.



For example, in the “e-mail - Priority” box, the primary medium to send alarm alerts via email to can be selected (Ethernet in the example provided). If there is no Ethernet connection, TelevisGo v10 will try to send the email using the secondary medium (a GSM modem in this case).

The order of priority for phoncall alarm messages is established in the same way.

Note: entering a secondary “Medium” is not compulsory.

Note: the drop-down menus list all media found for the type of notification, even if the specific one is not currently enabled.

PSTN, GSM and **GPRS** connections can also be configured from this page. Each of the three types of connection can be activated from the corresponding drop-down menu.

For PSTN and GSM connections, the following must be entered:

- Number of telephone provider with international dialing prefix (for example, **+39** for Italy)
- Dial-up connection user
- Dial-up connection user password.

<p> PSTN Dial Up Details</p> <p>Enable PSTN Dial Up <input type="checkbox"/></p> <p> PSTN Provider number <input type="text"/></p> <p> PSTN Username <input type="text"/></p> <p> PSTN Password <input type="text"/></p>	<p> Test utility</p> <hr/> <p><input type="button" value="Test connection"/></p>
<p> GSM Dial Up Details</p> <p>Enable GSM Dial Up <input type="checkbox"/></p> <p> GSM Provider number <input type="text"/></p> <p> GSM Username <input type="text"/></p> <p> GSM Password <input type="text"/></p>	<p> Test utility</p> <hr/> <p><input type="button" value="Test connection"/></p>

For GPRS connections, the service Access Point Name (APN) is required (for example, internet.mnc012.mcc345.gprs).

<p> GPRS Dial Up Details</p> <p>Enable GPRS Dial Up <input type="checkbox"/></p> <p> GPRS APN <input type="text"/></p>	<p> Test utility</p> <hr/> <p><input type="button" value="Test connection"/></p>
--	---

Others

In the following menu:

 **Settings > General Settings > Others**

The following screen will appear:

The screenshot shows a settings window with a control bar at the top containing a green circle with the number '2', an 'Edit' button, a 'Save' button, and a 'Cancel' button. Below the control bar is a section titled 'Sending life test notification' with a green circle and the number '1' to its left. This section contains four settings:

- Include parameters into the network naming snapshot file**: checked (checkbox)
- Show alarms resources in historical data**: checked (checkbox)
- Execution time of the data export tasks**: 00:00:00 [0 seconds ... 23 hours 59 minutes and 59 seconds]
- Start acquisition**: 05:00:00 [1 minute ... 1 day]

The different parts of the page are:

1. **Sending life test notification**: manages the life test sending information:
 - Include parameters into the network naming snapshot file
 - Show alarms resources in historical data
 - Execution time of the data export tasks
 - Start acquisition: indicates the period of inactivity after which the acquisitions are restarted automatically.
2. **Control bar**: see [Buttons and Selectors](#).

Computer

Contents

This section includes the following topics:

Introduction	160
Device settings	161
Updating the TelevisGo v10	162
Updating the system	163
Updating algorithm drivers	164
Updating device drivers	165
Reboot	166
License updating	166
System backup/restore	167
Activity logging	168


Introduction

Description

This section can be used to:

- manage network settings
- update the application, functions and languages
- update parameter maps, layout pages and various settings
- update algorithm and device drivers
- restart the application TelevisGo v10
- update the license
- backup and restore the system
- view the reports (.TXT) for activities carried out

Menu structure




Device settings

Setting the system name

In the following menu:

 **Computer > Information > General**

The following screen will appear:



The different parts of the page are:


1. **Plant name:** used to set the system name
2. **Control bar:** see [Buttons and Selectors](#).

Setting up network connections

In the following menu:

 **Computer > Information > Proxy Settings**

The following screen will appear:



Contact the network administrator for the network and Proxy data.

The different parts of the page are:

1. **Domain resolution:** Native DNS or Proxy.
2. **Ignore for local addresses:** when selected, TelevisGo v10 will not use the proxy server to resolve addresses within its own sub-network.
3. **Enabled:** if selected, the SOCKS server will require authentication.
4. **Protocol version:** SOCKS 4, SOCKS 4a, SOCKS 5 or HTTP Proxy.
5. **Server address:** IP address of SOCKS server.
6. **Server Port:** SOCKS server access port.
7. **User:** user name for SOCKS server authentication.
8. **Password:** password for SOCKS server authentication.
9. **Control bar:** see [Buttons and Selectors](#).

NOTE: having set the proxy parameters, reboot the system.

Updating the TelevisGo v10


The system can be updated by loading the relative update files.

Download the TelevisGo v10 update packages from the Eliwell website: www.eliwell.com.

To update the system, go through the following menus:

 **Computer > Update > TelevisGo**

The following screen will appear:



In this, the following updates can be made:

- **Application:** update the TelevisGo v10 application.
- **Functions:** update/upload the software applications "Offline Configurator" and "Layout Designer".
- **Languages:** update/upload the TelevisGo v10 system glossaries.

The application update package can be downloaded from the website www.eliwell.com and contains updates to device drivers

To update the dictionaries, download the relevant file from the website www.eliwell.com.

NOTE: To avoid overwriting local changes and notification message customization files, the dictionaries are not included in application updates.

NOTE: if you cannot find the driver for your device, contact Eliwell Technical Support (Technical helpline: **+39 0437 986 300** - email: Techsupp@se.com).

Updating the system


The system can be updated by loading the relative update files.

Download the TelevisGo v10 update packages from the Eliwell website: www.eliwell.com.

To upgrade the system, go through the following menus:

 **Computer > Update > System**

The following screen will appear:



Parameters map

Parameters map (.dat)

File name	Size	Date	
1 MsrRTX 600-V.dat	[260 Bytes]	[2/16/2016 6:16:47 PM]	<input type="button" value="Remove"/>

Layout pages

Layout pages (.xml)

File name	Size	Date	
1 Cabine.xml	3,140 Bytes	10/7/2016 3:46:40 PM	<input type="button" value="Remove"/>
2 Tacitazione.xml	935 Bytes	3/31/2016 6:16:47 PM	<input type="button" value="Remove"/>

Settings

General settings (.txt)

Scheduled actions (.xml)

Alarm categories

File name	Size	Date	
1 ScheduledActions.xml	[1,023 Bytes]	[2/5/2016 9:54:17 AM]	<input type="button" value="Remove"/>

In this, the following updates can be made:

- **Parameters map:** used to upload a map to for scheduled actions
- **Layout pages:** used to upload one or more layout pages (see "[Layout](#)")
- **General settings:** the procedure uses the file "Forced_setting.txt".

Updating algorithm drivers

The system can be updated by loading the relative update files.


Download the TelevisGo v10 update packages from the Eliwell website: www.eliwell.com.

To update the algorithms, go through the following menus:



Computer > Update > Algorithms drivers

The following screen will appear:



In this, the following updates can be made:

- **Algorithms drivers:** updates/uploads the algorithms implemented with the FREE Studio Plus programming environment.

To load a new algorithm (row 1) :

1. click **Select a file**
2. select the algorithm file (format TGA30K1025_FloatingSuction.bin)
3. click **Run** to load it.

The software will automatically open the Algorithms window

To update an algorithm (row 2):

1. click **Select a file**
2. select the algorithm file
3. click **Drivers update**.

The software will automatically open the Algorithms window

NOTE: if you are trying to update the algorithm using the **Run** function, the following message will appear on the screen: "**The algorithm is already present**".

Updating device drivers


The system can be updated by loading the relative update files.

Download the TelevisGo v10 update packages from the Eliwell website: www.eliwell.com.

To update the device drivers, go through the following menus:

 **Computer > Update > Device drivers**

The following screen will appear:



In this, the following updates can be made:

- **Device drivers:** used to upload/update the device driver.

Updating a driver overwrites any driver that is already present.

Make a backup copy of the driver before carrying the update (see "[System backup/restore](#)").

The **Remove** button removes the relevant configuration file/driver.

- (1) list of all drivers present on the TelevisGo v10.

NOTE: if you cannot find the driver for your device, contact Eliwell Technical Support.

Reboot

Having updated the Application or the License, you must reboot the TelevisGo v10 software to implement the updates. To do so, go to:

 **Computer > Reboot**

then press **Reboot**.



This procedure involves the disconnection of TelevisGo v10. If the login page does not appear automatically after a few minutes, close and reopen the browser.


License updating

The license can be updated (for example, to increase the number of connectable devices or activate additional functions).

In the following menu:

 **Computer > Update license**

Enter the 'Current code' on the screen, then the 'New code' (1) supplied by Eliwell, and press '**Start update**'. If the entered code is wrong an error message will be created.




System backup/restore

The system configuration can be backed up.
In the following menu:

 **Computer > Backup/Restore**

The following screen will appear:



Backup

Click  **Download current settings (1)**; a .zip file is created containing the “Equipment profile” and the “Scheduled actions”.

The user must save the file created.

Run a backup as soon as the device network customization and scanning, alarm configuration and scheduled actions setting processes have been completed.

Restore

Restore is used to load a set of previously archived settings to the TelevisGo v10.

(2) Select file...: to open a window and select the backup file to be restored.

(3) Once loaded, the name, size and date of the backup file will be visible (but the restore will not yet have been performed).

(4) Remove: used to cancel the previously uploaded file.

(5) Some check boxes above the **Apply (6)** button are used to select which settings to restore.

(6) Apply: the TelevisGo v10 will be restored according to the contents of the uploaded file **(3)**.

The restore function is used to re-apply the backup functions on the same system or replicate the information on different systems.

The restore procedure overwrites the system settings and cannot be canceled (the user is responsible for making a safety backup before carrying out the restore procedure).

If the restore procedure involves the network name, make sure that the network has been scanned.


Activity logging

TelevisGo v10 records the main operations carried out by users:



Computer > Activity logging

The page shows one or more text files which can be consulted by clicking **Open**.



The text files used to log activities belong to a group of files that are managed in a circular mode (maximum of 10 files), meaning the oldest files are overwritten. The language used to log data in these files is the system language.

Moreover, to facilitate the consultation in case of need, the user activities are tracked and also recorded in the application tracking file using the English language.

Below is a list of the activities that are logged in the files:

- Login - AutoLogin - Logout
- Data acquisition Start / Stop
- Scheduled actions Start / Stop
- Execution of Commands
- Execution of Commands from Parameters page
- Writing of parameters
- RVD access
- Device(s) added to the network configuration
- Device(s) removed from the network configuration
- Edit device configuration
- Device(s) in maintenance
- Device maintenance end
- Editing/creation/removal of Alarm Actions
- Editing/creation/removal of Intervals
- Editing/creation/removal of Scheduled Activities
- Editing and saving of System Names
- Updating: updating of files in the pages
 - Computer Updating
 - Backup / Restore
 - Naming
 - Device profile
 - Drivers
- Reboot
- Updating: file removal
 - Application
 - File name rules
 - Updating
 - Dictionaries
 - Drivers
 - Scheduler
 - Layouts
 - Parameter map file
- License updating
- Backup settings
- Restore settings
- Editing and saving of:
 - General settings > System

- General settings > TelevisTwin
- General settings > Alarms
- General settings > Media
- Editing and saving
 - Archive management > Control
- Editing and saving
 - Archive management > Manage
- Editing and saving
 - Computer > Information > Network settings.

Configuring HTTPS protocol

Contents

This section includes the following topics:

Certificates	171
Installing the certificate on other PCs	172
Installing a new certificate	173

Certificates


The following image is an example of the structure of the “**Eliwell CA**” certificate installed on the TelevisGo v10. It is a self-certification and by default is installed in the “**Trusted root Certification Authorities**” folder on the TelevisGo v10.



TelevisGo v10 only works in **HTTPS** mode by connecting to the URL: **HTTPS://[Machine name]**.
Operation in **HTTPS** can take place in 2 ways:

1. By installing the “**Eliwell CA**” certificate on each machine that needs to connect to TelevisGo v10.
NOTE: the certificate is self-signed by Eliwell, not recognized by the browsers, and does not constitute a guarantee of security for the user (see “[Installing the certificate on other PCs](#)”).
2. By purchasing and installing a certificate recognized by browsers and issued by an Authorized Certification Authority (Digicert, Verisign, etc.) on the TelevisGo v10 (see “[Installing a new certificate](#)”).

Installing the certificate on other PCs



At startup, the file **CertificateGo.cer** corresponding to the certificate will be generated in the TelevisGo v10 folder (see "Certificates").

Install the certificate "**Eliwell CA**", self-signed by Eliwell and not recognized by the browsers, on each machine that needs to establish a secure remote connection with TelevisGo v10.

To install it correctly, proceed as follows:

1. Copy the file to the machine on which you want to install the Certificate
2. Double-click on the certificate
3. In the window that opens, click "**Install Certificate...**" to launch the installation wizard
4. Click "**Next >**"
5. Select "Place all certificates in the following store"
6. Click "**Browse...**" and search for the file "Trusted Root Certification Authorities"
7. Click "**Next >**"
8. Click "**Finish**".

The certificate is now correctly installed on the machine and will allow remote communication with TelevisGo v10 via **HTTPS**.

Installing a new certificate

If the client decides to protect themselves further by requesting the issue of a Certificate signed by a recognized authority, to install it correctly on the TelevisGo v10 proceed as follows:

1. Install the certificate issued by the authority on the TelevisGo v10, in the **"Personal"** folder.
2. Go to **"Start"** and then **"Run"**
3. Enter **"inetmgr"** in the text box and press enter
4. At this point the **IIS** interface will open
5. Select the following sequence from the menu on the left: **TelevisGo -> Sites -> ReverseProxy**
6. Click **"Bindings..."** in the menu on the right
7. Now select the binding **"HTTPS"** and click **"Edit"**
8. Finally, in the SSL certificate field, open the drop-down menu and select the new certificate you have just installed, then click **"OK"**.

The certificate is now correctly installed and assigned to the TelevisGo v10.

Administrative tools

Contents

This section includes the following topics:

Restoring the disk image	175
Downloading files	176

Restoring the disk image


This function allows you to reinstall the software and the operating system in the event that:

- TelevisGo v10 operation has been compromised (virus or loss of performance)
- you want to restore the factory settings of the TelevisGo v10

This procedure will delete the entire contents of the hard disk: software, data and TelevisGo v10 settings.

To proceed, you need to:


1. In the system file "C:\", enter an empty file with the name "enablerestore".
Note: the file will be deleted at each reboot
2. Reboot the TelevisGo v10
3. During the reboot, press F7. A window similar to this one will open:



4. Use the Up/Down arrows to select "UEFI OS (PO: TS256GSSD452K2-AEN)" and click ENTER
5. In the next window, enter "eliwell" as the username and click ENTER
6. Then enter "eliwell" as the password and click ENTER.
The window does not show the password characters entered.

Note: the process takes 10/15 minutes.

Once the system reboot is complete, enter the menu:



- a. Send an email to Eliwell Technical Support (techsuppeliwell@se.com) with subject "TELEVISGO LICENSE". Indicate the product code and ID code (1) shown in the picture to calculate the new license code and the type of license to activate (LE or standard and the size).
- b. Eliwell Technical Support will email you the new license code to enter in the gray box (2).
- c. Click "Start update" (3).

NOTE: the factory settings may contain outdated versions of the software and/or operating system; check whether they need updating.

Downloading files

A .zip file containing information on the status of the system and its configuration can be downloaded in order to diagnose any problems.

To do so simply open a browser and enter:

Https://<Static IP address>/debug.rlx

The TelevisGo v10 address is the one used for the normal web interface use (e.g.: 192.168.1.50 or 198.168.1.51).

Remote data access protocol

Contents

This section includes the following topics:

Data protocol	178
---------------------	-----

Data protocol

TelevisGo v10 allows third-party clients to extract data saved in their own files and run remote procedures on the system using the TCP/IP communication protocol.
For further information, contact Eliwell Technical Support.

NOTE: information is only available in English.

FAQs

Contents

This section includes the following topics:

FAQs	180
------------	-----

FAQs

- **Function busy message:** to avoid blocking TelevisGo v10 DP functions, always use the logout button to exit the application. If you don't do this, the functions will remain busy until the work session times out (20 minutes), preventing them from being used by other users.
- **Device description:** the screens used to select devices/resources for accessing various system functions (parameters, RVD, etc.) offer the option of applying filters, which act on the "Description" of the device/resource). To simplify selection by applying filters, we recommend assigning easily recognizable descriptions.

Device naming as follows:

- Frozen food cabinet 1
- Frozen food cabinet 2
- ⋮
- Frozen food cabinet n
- Vegetable cabinet 1
- Vegetable cabinet 2
- ⋮
- Vegetable cabinet m
- Positive temperature controller
- Negative temperature controller

makes it easy to identify all devices within a group (for example: frozen food cabinets) simply by entering the string "**frozen**" in the filter; controllers can be identified using the string "**Controller**". The same concept can be extended to the naming of individual device resources/alarms.

- **Alarm detail: why is there an action when an alarm occurs, and not the action associated with the alarm reset?**
This happens when a category or action connected to the same alarm management category is removed. The system is no longer able to perform the activity associated with resetting that alarm.
- **Why does the system carry out an action associated with an alarm category, even if the validity period has elapsed?**
This happens if an alarm instance starts within a validity period. Management also continues through alarm reset periods, even if this occurs outside the validity period.
- **Why are some strings missing sometimes when I update drivers?**
This happens because updating drivers does not update dictionaries as well. To update dictionaries, go to the updates page and update dictionaries (see "[Updates](#)").

Eliwell Controls srl

Via dell'Industria, 15 Z.I. Paludi
32016 Alpago (BL) Italy
Telephone +39 (0) 437 166 0000
www.eliwell.com

Customer Technical Support

Telephone +39 (0) 437 166 0005
E techsuppeliwell@se.com

Sales office

Telephone +39 (0) 437 166 0060 (Italy)
Telephone +39 (0) 437 166 0066 (other countries)
E saleseliwell@se.com